PHILIPS 281571SB

MODEL

SERVICE MANUAL

Colour television Chassis GR2.1

AA

Service
Service
Service



Service Manual

Contents

Page

1. Block diagram and technical data 1.2
2. Connection facilities 2.1
3. Warnings and notes 3.1
4. Mechanical instructions 4.1
5. Detailed block diagram 5.1
6. Electrical diagrams and PCB layouts
   - Operation (Diagram A) 6.1
   - Tuner, IF and sound (Diagram B) 6.5
   - Video processing (Diagram C) 6.9
   - Power supply, synchronization, raster and line (Diagram D) 6.16
   - Picture tube module (Diagram F) 6.23
   - Mono IF/sound module (Diagram G) 6.30
   - Stereo IF/sound module (Diagram H) 6.35
   - NICAM IF/sound module (Diagram I) 6.41
   - Teletext module (Diagram J) 6.27
   - PIP module (Diagram K) 6.47
7. Electrical settings 7.1
8. List of fault messages and repair tips 8.1
9. Directions for use and menus 9.1
10. Electrical parts lists 10.1

Published by Consumer Electronics Printed in The Netherlands ©Copyright reserved Subject to modification

(GB) 4822 727 18334

Block diagram


DIAGRAM
PAGE
A P6.1
B P6.5
TUNER/IF/SOUND
G P6.30 MONO
H P6.35 STEREO
I P6.41 NICAM
IF/SOUND MODULE
TUNER
IF
R.L
EURO PANEL
CVBS IF
Y
C
ADD
CVBS EXT2
CVBS PIP
CVBS EXT1
CVBS EXT3
CVBS EXT1/EXT3
EXT2
EXT1
EXT3
CVBS
Y
C
A P6.1
CONTROL
µC
C P6.9
CHROMA PROCESSING
C
TDA4650/ TDA4510
R-Y
B-Y
TDA4660
TDA4585
TDA4680
R
G
B
Y
J P6.27
T.X.T.
CVBS P.I.P.
K P6.47
P.I.P.
F P6.23
CRT
RGB
CRT
D P6.16
SYNC
Y/CVBS
TDA2579
VERTICAL DEFLECTION
V
H
POWER SUPPLY
+280
5625
7625
220V
+148
+32
+16
-16
+5
HORIZONTAL DEFLECTION + LINE POWER SUPPLY
+200
-26
+8
+14
PRS.06915
T-26/106

Technical data

Mains voltage : 220 - 240 V (±10%)
Mains frequency : 50 Hz (± 10%)
Aerial input impedance : 75Ω - coax
Minimum aerial voltage : 40µV
Maximum aerial voltage : 32mV
Pull-in range colour synchronization : ±300Hz
Pull-in range horizontal synchronization : ±300Hz

Local operation functions:

P +; P -; ◿+; ◿−; install

Programmes: 0-59
VCR operation on programmes: 0-59

Indications:

- On Screen Display (OSD)
- LED:
  - standby (red)
  - operation (green)
  - RC5 reception (flashing yellow)
  - internal fault in µP (flashing)

Connection facilities

1. Specification of the terminal sockets

EXT1



1 – Audio ⊖→ R (0.5 V_{RMS}; ≤ 1 kΩ)
2 – Audio →⊖ R (0.2-2 V_{RMS}; 0.5 $V_{nom.}$; ≥ 10 kΩ)
3 – Audio ⊖→ L (0.5 V_{RMS}; ≤ 1 kΩ)
4 – Audio ⊥
5 – Blue ⊥
6 – Audio →⊖ L (0.2-2 V_{RMS}; 0.5 $V_{nom.}$; ≥ 10 kΩ)
7 – Blue →⊖ (0.7 V_{pp}; 75 Ω)
8 – RC5 ⊖→ (500-800 mV_{pp}) + CVBS status 1 →⊖
(0-2 V: int.; 9.5-12 V: ext.)
9 – Green ⊥
10 – –
11 – Green →⊖ (0.7 V_{pp}; 75 Ω)
12 – –
13 – Red ⊥
14 – –
15 – Red →⊖ (0.7 V_{pp}; 75 Ω)
16 – RGB status →⊖ (0-0.4 V: int.; 1-3 V: ext.; 75 Ω)
17 – CVBS ⊖→ ⊥
18 – CVBS →⊖ ⊥
19 – CVBS ⊖→ (1 V_{pp}; 75 Ω)
20 – CVBS →⊖ (1 V_{pp}; 75 Ω)
21 – Earth screen

EXT3



1 – Audio ⊖→ R (0.5 V_{RMS}; ≤ 1 kΩ)
2 – Audio →⊖ R (0.2-2 V_{RMS}; 0.5 $V_{nom.}$; ≥ 10 kΩ)
3 – Audio ⊖→ L (0.5 V_{RMS}; ≤ 1 kΩ)
4 – Audio ⊥
5 – –
6 – Audio →⊖ L (0.2-2 V_{RMS}; 0.5 $V_{nom.}$; ≥ 10 kΩ)
7 – –
8 – CVBS status 3 →⊖ (0-2 V: int.; 9.5-12 V: ext.)
9 – –
10 – –
11 – –
12 – –
13 – –
14 – –
15 – –
16 – –
17 – CVBS ⊖→ ⊥
18 – CVBS →⊖ ⊥
19 – CVBS ⊖→ (1 V_{pp}; 75 Ω)
20 – CVBS →⊖ (1 V_{pp}; 75 Ω)
21 – Earth screen

EXT2

1 – ⊥
2 – ⊥
3 – Y →⊖ (1 V_{pp}; 75 Ω)
4 – C →⊖ (1 V_{pp}; 75 Ω)

2x ◎ CINCH Audio →⊖ L + R (0.2-2 V_{RMS}; 0.5 $V_{nom.}$; ≥ 10 kΩ)

Audio out

2x ◎ CINCH Audio ⊖→ L + R (0.5 V_{RMS}; ≤ 1 kΩ)

Front



3,5 mm
≥ 8 Ω

2. Connecting equipment

Depending on the type of TV set, a variety of equipment can be connected. The exact number of pieces of equipment depends on the number of connectors on the back of the TV set (EXT1, 2 or 3). The wiring diagram in Fig. 2.1 shows which kinds of equipment can be connected. The wiring diagram shows the TV set with the maximum number of connectors possible for the GR2.1 chassis.

An RGB source (e.g. laserdisc player) can only be connected to EXT1. In order to switch the TV set to RGB operation, this RGB source must generate both a CVBS status signal at pin 8 and an RGB status signal at pin 16 of the euroconnector. It is not possible to switch the equipment to EXT1 in RGB operation using the remote control.



Fig. 2.1

Warnings

1. Safety regulations require that the unit should be returned in its original condition and that components identical to the original components are used. The safety components are indicated by the symbol ⚠.
2. In order to prevent damage to ICs and transistors, all high-voltage flashovers must be avoided. In order to prevent damage to the picture tube, it should be discharged using the method shown in Fig.3.1. Use a high-voltage probe and a multimeter (position DC-V). Discharge until the meter reading is OV (after approx. 30s).
3. **ESD** ⚠

   All ICs and many other semiconductors are sensitive to electrostatic discharges (ESD). Careless handling during repair can drastically shorten their life. Make sure that during repair you are connected by a pulse band with resistance to the same potential as the earth of the unit. Keep components and tools also at this same potential.
4. When repairing a unit, always connect it to the mains voltage via an isolating transformer.
5. Be careful when taking measurements in the high-voltage section and on the picture tube.
6. Never replace modules or other components while the unit is switched on.
7. It is recommended that safety goggles are worn when replacing the picture tube.
8. When making settings, use plastic rather than metal tools.
   This will prevent any short circuits and the danger of a circuit becoming unstable.
9. After repair the wiring should be fastened once more in the cable clamps for this purpose.
10. In order to prevent measuring errors, the heat sinks should not be used as reference points for measurements.
    The heat sink for the sound output amplifier (next to the channel selector) is connected to the -16 or -12 volts.
11. Together with the deflection unit and any multipole unit, the flat square picture tubes used form an integrated unit. The deflection and the multipole units are set optimally at the factory. Adjustment of this unit during repair is therefore not recommended.
12. The high-voltage cable in 21" units is glued in the line output transformer. This can therefore not be replaced.

Notes

1. The direct voltages and oscillograms should be measured with regard to the tuner earth (⊥), or hot earth (⊥ ⚡) as this is called.
2. The direct voltages and oscillograms given in the diagrams should be measured in the service default mode (see section 9). A colour bar signal, modulated on a picture carrier wave of 475.25 MHz, should be used as the video signal. A 1 kHz signal should be used for the sound (for all systems).
3. Where necessary, the oscillograms and direct voltages are measured with (┐┌) and without aerial signal (╳). Voltages in the power supply section are measured both for normal operation (①) and in standby (⏻). These values are indicated by means of the appropriate symbols.
4. The picture tube PCB has printed spark gaps. Each spark gap is connected between an electrode of the picture tube and the Aquadag coating.
5. The semiconductors indicated in the circuit diagram and in the parts lists are completely interchangeable per position with the semiconductors in the unit, irrespective of the type indication on these semiconductors.
6. The connectors used for the modules (board to board) are gold-plated and should only be replaced by the same type.
7. In the case of fault finding and/or repair to the teletext module, the accessibility of the circuit and the components can be increased by using extension cards.
   The order numbers of these extension cards are:
   * 6 times: 4822 395 30259
   * 8 times: 4822 214 31402
8. Both multisystem and single system units are discussed in this documentation.
   The term multisystem unit is used to refer to a unit that is suitable for the reception of PAL BGI and SECAM BGLL' systems.
   The term single system unit is used to refer to all other units (such as PAL BG, PAL/SECAM BG and PAL I units).
9. Blackline units can be recognized by the thick, protected high-voltage cable. Non-blackline units have a thin, unprotected high-voltage cable.



Fig. 3.1

Mechanical instructions

1. Removing the back plate

It is only possible to remove the back plate after removing the screws on the top, side, possibly on the underneath **and possibly under the EXT 3 connection** (see Fig. 4.1). In the case of subwoofer units, the subwoofer speaker on the carrier panel should also be unplugged.

2. Service position 1

Service position for module service and to measure test points

Unlock the chassis after the cables of the degaussing coil and any PIP module have been disconnected, and pull it backwards until all test points are accessible (see Fig. 4.2).
In order to make the tuner and the IF/sound module accessible, the bracket above these modules can be removed (see Fig. 4.3). With the exception of one fault message, the unit continues to function normally when the PIP module is not connected.

3. Service position 2

Service position for repair

Place the chassis on the heat sink on the tuner side after service position 1 is reached (see Fig. 4.4).
Warning: make sure that the heat sink of the sound output amplifier does not form a short circuit with the raster/line heat sink if the bracket of the euromodule has been removed!



Fig. 4.1



Fig. 4.2



Fig. 4.3



Fig. 4.4

Blockdiagram / Blockschaltbild / Schéma-bloc


B
P6.5
3001
1000
TUNER
+14
+5
MONO ONLY
VHF-L
VHF-H
UHF
7
8
10
17
IF
6M50
5
AGC
2M50
13
14
16
SCL
SDA
STEREO ONLY
1001
G
P6.30
MONO
H
P6.35
STEREO
I
P6.41
NICAM
IF/SOUND MODULE
+8
3M50
4M51
R IF
3M51
L IF
5M50
CVBS IF
1M50
CVBS EXT1.3
6M21
5B23
13M51
SDA
12M51
SCL
13M50
Bl/L
6M50
POS/ NEG
12M50
L
7312
HEF4053
12
CVBS
EXT1
1006
EURO MODULE
3M22
1B32
1M22
3B32
R EXT1
3M21
10B23
L EXT1
1M21
8B23
B
CVBS STATUS 1
G/V
R
RGB STATUS
CVBS IF
8M21
3B23
CVBS EXT1
10M21
1B23
CVBS EXT2
1M29
9G30
7B23
4M21
R EXT1,3
9B23
2M21
L EXT1,3
R IF
R EXT3
L IF
L EXT3
CVBS STATUS 3
CVBS IF
CVBS EXT3
EXT3
CVBS PIP
1G26
10P17
TP40
9854
C
P6.9
EXT2-2A (SVHS)
C
Y
8
4
7311
HEF4053
+14
16
12
13
5
3
14
4
9,10,11
EXT2
TP20
9677
TP37
9675
Y
TP19
15
7306
TDA4650
+14D
13
7305
TDA4570
9
7
2
1
3
B-Y
1
R-Y
TP1
TP2
7307
TDA4660
+6
3330
+6
3331
14
16
12
B-Y
11
R-Y
TP4
TP5
TP5
7308
TDA4565
+14D
CTI
2
1
17
7
B-Y
8
R-Y
12
Y
TP6
TP7
TP8
15
7373
PAL SW
3328
+14D
7307
EXT2 (SVHS)
+14
+8
4M17
5M17
3M17
1003
4T6
5T6
3T6
J
P6.27
TXT MODULE
5T7
5M18
R
6T7
6M18
G/V
7T7
7M18
B
3T7
3M18
F BL
OSD
B
G/V
R
DIAGRAM
PAGE
A
P6.16
D
P6.16
+14
7470
TDA2579
10
5
50Hz
15625Hz
1
2
17
11
12
3451
TP31
+32A
7502
7503
7500
3M16
V
1M16
TP41
2506
BCI
E/W
3588
+148
2524
6560
6561
PRC
+14
6549
TP37
7545
7546
5541
2545
3539
2546
6546
5534
4M15
H
1M15
7540
3538
2547
6547


TP1
650mV
1V1
10µs/div
TP3
900mV
3V8
TP2
440mV
0V9
TP4
1V2
TP5
1V3
TP6
1V
2V3
TP7
2V4
0V8
TP8
0V4
2V7
7240
TDA1521
TDA2613
LOUDSPEAKER MODULE
SUB WOOFER
1M19
3M19
M23
M24
R
L
8M51
10M51
11M51
2M51
5M51
6M51
3239
TP32
TP33
TP34
TP35
+8
+14
+16
-16
R EXT
L EXT
7312
HEF4053
9,10,11
EXT2
R EXT1,3
L EXT1,3
R EXT2
L EXT2
EXT2 -2B
3244
3245
SOUND PROT.
7248
7249
3327
7243
+14A
PROT.
A
P6.1
1986
TRANSM.
1003
REC·
TP17
7708
TMP47C1237
TMP47C1637
+5
µP
F.BL
G/V
B
OSD
TP13
TP12
MONO ONLY
UHF
VHF-H
VHF-L
POS/NEG
L'
I/BG
6707
+14C
SERVICE
TP15
TP16
TP14
TP18
SDA
SCL
POR
MEM
7710
ST24CCCP
K
P6.47
PIP MODULE
6G26
3G26
5P17
8P17
1G26
10P17
1P56
2P56
4P56
1P16
2P16
4P16
5M27
4M27
2M27
1M12
2M12
5M12
7309
TDA4680
+9
B-Y
R-Y
Y
TP6
TP7
TP8
MATR.
TP9
TP10
TP11
+14D
F.BL
F
P6.23
+200
4M13
1C19
1005
P.T.P.
3431
+190
7301...7305
7361...7365
7331...7335
5M14
3C20
3M14
5C20
2M14
6C20
TP51
TP52
TP53
1990
C.R.T.
8(7)
11(3)
6(9)
+12
+2
3432
7M14
1C20
+12A
+12B
5545
L.O.T.
VEHT
VFOCUS
VG2
BCI
TP36
3590
6590
7591
+32
B.C.F.
3588
+148
1559
6563
3570
6570
3585
6585
-26
6591
6592
TP38
6580
1580
5582
6560
6561
1M15
H
( ) → 21'
SK1
1600
220V 50Hz
6602-6605
-280
2605
3625
3624
7625
2625
TP29
TP28
TP30
7614
CNR50
SOPS
5625
6640
2640
5632
2641
6641
6630
5630
6675
2675
6670
7671
6661
2660
7661
5681
2661
6646
2646
6664
7672
3631
3634
3635
TP23
6666
6663
TP27
TP26
3673
3674
TP24
TP22
7600
TDA8385
PRS.06906
T28/107


TP9
10µs/div
1V7
2V5
TP10
10µs/div
1V9
2V5
TP11
10µs/div
1V7
2V
TP12
VOLUME 50µs/div
0V
5V
TP13
KEY PRESSED
0V
2V5
TP14
0V
2V7
TP14
0V
TP15
0.2ms/div
5V
TP16
0.2ms/div
5V
TP17
2ms/div
4V
TP18
5V
TP19
10µs/div
TP20
SVHS 20µs/div
0V4
TP21
2µs/div
TP21
5µs/div
TP22
2V4
TP23
TP24
12V
TP25
5µs/div
TP26
1V9
TP26
20ms/div
0V5
2V
TP5
10µs/div
1V
INSTALL
P+
P-
SK14
SERVICE
+14C
9709
+5
7710
7708
7307
7308
7306
7305
7309
2313
8.86MHz
2324
7.16MHz
3233
+6
+9
+14D
3759
9660
+5
1600
2AT
7614
TP28
TP29
TP30
+14A
9712
7600
TP21
TP22
TP23
TP24
TP25
TP26
TP27
+14D
3336
1242
1.6AT
TP20
9677
1240
1.6AT
WARNING! ON -16V LEVEL
+14B
9713
M17
TXT
1003
M18
1001 IF/SOUND MODULE
TP31
3451
3635
+148 +95
5625 SOPS TRANSFORMER
7625
2608
6675
+32
1534
315mAT
3525
3590
5541
TP36
TP37
7470
3467
+14E
+16B
TP32
TP33
-16A
TP34
TP35
7240
3239
3461
+5A
9613
5631
+148 +95
3521
7533
-26
6585
6570
+200
TP38
6591
9715
+14
7545
1000 TUNER
TP39
9675
TP40
9854
7311
7312
1580
1.6AT
+8
6563
1559
1AT
3516
+14E
3506
5545 L.O.T.
7546
3584
+148
3631
3634
3635
7600 TDA8385
PRS.06906 T28/107
MDA.02945 T28/106


2V5
1V7
2V
10µs/div
TP11
0V
5V
VOLUME 50µs/div
TP12
0V
2V5
KEY PRESSED
TP13
0V
2V7
TP14
INSTALL
+
-
P+
P-
SK14
SERVICE
+14C
9709
+5
7710
TP12
7708
TP15
TP16
TP17
TP18
40
39
35
33
3759
14
17
TP13
TP14
TP9
TP10
TP11
24
22
20
9660
+5
1500
2AT
7614
TP28
TP29
TP30
8
7
6
TP21
TP24
TP25
TP22
TP23
TP26
TP27
7600
2
16
12
7
8
10
9
+14B
9713
M17
3635
+148
+95
5625
SOPS TRANSFORMER
7625
2603
TXT
1003
TP31
3451
M18
6675
+32
1534
315mAT
3525
TV
3467
7470
+14E
10
3590
5541
TP36
TP37
+148
+95
5631
3521
TV
+5A
9613
3461
TV
7533
-26
6585
6570
+200
TP38
6591
9715
+14
7545
1580
1.6AT
+8
6563
5545
L.O.T.
7312
1559
1AT
3516
TV
+14E
3506
7546
3584
TV
1
MDA 02945
T28/106


0V
TP14
5V
0V
0.2ms/div
TP15
5V
0V
0.2ms/div
TP16
0V
4V
2ms/div
TP17
5V
0V
TP18
0V
200mV
10µs/div
TP19
0V4
700mV
SVHS 20µs/div
TP20
0V
1V5
2µs/div
TP21
1V6
0V
5µs/div
TP21
2V4
0V
TP22
0V
TP23
12V4
0V
TP24
1V1
0V
5µs/div
TP25
1V9
0V
TP26
0V5
2V
20ms/div
TP26
2V4
0V
TP27
0V4
1V3
20ms/div
TP27
0V8
12V3
5ms/div
TP28
4V8
1V7
10ms/div
TP28
0V8
-1V6
5ms/div
TP29
5V
0V
10ms/div
TP29
7V
-5V
5µs/div
TP30
7V
-5V
10ms/div
TP30
9V
0V
20µs/div
TP31
30mV
0V
0.2ms/div
TP32
800mV
0V
0.2ms/div
TP33
800mV
0V
0.2ms/div
TP34
30mV
0V
0.2ms/div
TP35
1V5
5V
10ms/div
TP36
9V
-8V
50µs/div
TP37
0V7
0V
50µs/div
TP38
840m
1V3
SVHS 10µs/div
TP39
2V
2V
10µs/div
TP40
7V5
12V5
TP41
130V
65V
TP51 1
130V
50V
TP51 2
115V
70V
TP51 3
120V
75V
TP52 1
120V
56V
TP52 2
115V
72V
TP52 3
120V
80V
TP53 1
120V
66V
TP53 2
110V
76V
TP53 3
PRS 06914
T 26/105

Controls / Bedienung / La C


A
1986
IR TRANSM.
EMET. IR
IR SENDER
TRANSM. RI
TRANSMISOR IR
1003
IR RECEIVER
RECEPTEUR IR
IR EMPFAENGER
RICEVITORE RI
RECEPTOR IR
VDD
VSS
E87
3M26
B1
RC5
2713 100u
2706 68u
7708
1) TMP47C1237
2) TMP47C1637
4V8 42
B2
B3
B4
C5
C6
C7
SDA
SCL
3757 2k2
3758 2k2
3756 100
3755 100
4311
7710 ST24C02CP
EEPROM
4721
1,2,3,4
B8
B9
B10
C11
2715 120p
2714 120p
4706
4708
4709
4700
RC5
CPU
I²C
2V7
1)4V9
3V1
1)4V9
B12
3759 100
1)0V..4V7
2717 2n2
3717 10k
3731 10k
3716 10k
B13
UHF
7711 BC848
B14
VHF-H
4715
7709 BC848
4720
B15
VHF-L
7712 BC848
4713
0V/0V8
+14A
3724 10k
B16
POS/NEG.
4712
4716
7703 BC848
3721 10k
3718 220
0V/3V
3725 10k
3722 10k
B17
L'
7704 BC848
3719 220
3726 10k
3723 10k
B18
I/BG
4704
4718
7705 BC848
3720 220
+14B
3754 15k
B19
PIP2
4450
4710
+14
3702 15k
B20
PIP1
4451
3750 27k
3701 27k
3779 10k
3778 56k
3777 27k
3776 5k6
3775 100
KEYBOARD
CLAVIER
TASTATUR
TASTIERA
TECLADO
P-
P+
INSTALL.
+14C
3729 910
3730 220
6707
A2
A1
K
6705 BZV55
4707
3727 100
1M33
1M34
SERVICE
3780 10k
2704 47n
4717
2M20
E88
4M26
E89
2705 120p
4V
0V
IDENT
MUTE
B21
D22
D23
0V/2V7
TV
+5
+14A

Controls / Bedienung / La Commande


3 4 5 6 7 8 9 10 11 12 13 14
E87
B1
3M26
RC5
1986
IR TRANSM.
EMET. IR
IR SENDER
TRANSM. RI
TRANSMISOR IR
1003
IR RECEIVER
RECEPTEUR IR
IR EMPFAENGER
RICEVITORE RI
RECEPTOR IR
VOO
VSS
2713 100u
2706 68u
2716 100n
5703 33u
7708
1) TMP47C1237
2) TMP47C1637
4V8
+5
3757 2k2
3758 2k2
3756 100
3755 100
7710 ST24C02CP
EEPROM
4721
1,2,3,4
2715 120p
2714 120p
4706
4708
4709
4700
2V7
1)4V9
3V1
1)4V9
RC5
CPU
AFC
I²C
3759 100
1)0V..4V7
2717 2n2
3717 10k
3731 10k
3716 10k
7711 BC848
7709 BC848
7712 BC848
4715
4720
4713
0V/0V8
+14A
3724 10k
4712
4716
3721 10k
7703 BC848
3718 220
0V/3V
3725 10k
3722 10k
7704 BC848
3719 220
3726 10k
3723 10k
4718
7705 BC848
3720 220
+14B
3754 15k
4450
4710
+14
3702 15k
4451
3750 27k
3701 27k
3703 15k
3704 10k
7701 BC848
3705 1k
+14C
4k7
7702 BC848
3707 22k
100p 2701
330k
0V9..4V2
0V2
2V4
2708 10n
4714
0V/8V2
0V/4V8
0V/8V9
4V3
0V
3736 100
4V8
2V2
27p 2712
1702 4.194
27p 2711
2V
G
4 MHz
8p2 2709
5701 56u
8p2 2710
4V2
VD
HD
BL
4V5
3V8
B
G/V
R
FBL
C24 C25 C26 C27
3777 27k
3776 5k6
3775 100
56k
INSTALL.
6707
A2
A1
3729 910
3730 220
K
4707
6705 BZV55
4V9
TV
3727 100
2704 47n
4717
2M20
E88
4M26
E89
1M33
1M34
SERVICE
2705 120p
4V
0V
IDENT
MUTE
B21 D22 D23
0V/2V7
704
3 4 5 6 7 8 9 10 11 12 13 14

Loudspeaker module
Lautsprecher-Platte
Module haut parleur


A
14
15
16
17
18
+148A
3732
3733
3734
+14C
3706
4k7
1)
7701
BC848
32V5
3710
6709
MZT33
2718
100n
4723
3705
1k
9706
2)
7702
BC848
9707
3711
1
3712
3713
V VARI
B39
3714
1M2
3708
330k
2702
10n
2703
470n
2707
10n
3735
100k
3728
1k
AFC
B38
2708
10n
4714
4701
EXT 2
B35
C37
C36
3753
15k
3749
27k
EXT 1
B34
3752
15k
3751
15k
3748
27k
4709
EXT 3
B33
3747
27k
CVBS STATUS 1
B32
FBOFF
B31
3736
100
CVBS STATUS 3
B30
3737
1k
POR
D29
+5
3781
4k7
2781
100n
2719
100n
3770
4k7
4V5
7706
BC848
0V3
3771
15k
3772
3k9
3769
22k
2721
4n7
6708
BZV55
12
+5
3743
4k7
7707
BC848
0V2
3741
12k
D28
3742
33k
B
FBL
C26
C27
B+C+D+E
CHASSIS GR2.1
CL06532002/010.AREF
040291

REMARKS/REMARQUES/ANMERKUNGEN/NOTE

PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEND IN GERÄTEN:
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS:
1) MONO
2) STEREO
3) 21"

*	1)	2)	3)
3710	24k	0	3k3
3712	22k	0	0
3713	22k	0	0
3732	10k	10k	3k3
3733	4k7	4k7	3k9
3734	4k7	4k7	3k9

1003	A 5	7703	H 8
1702	J13	7704	I 6
1986	A 3	7705	J 4
2701	E14	7706	K16
2702	E16	7707	L15
2703	E17	7708	B 9
2704	N 3	7709	F 5
2705	N 7	7710	D 3
2706	A11	7711	F 6
2707	E17	7712	G 4
2708	F14	9706	D16
2709	L14	9707	D15
2710	L14		
2711	K14		
2712	J14		
2713	B 7		
2714	D 7		
2715	D 6		
2716	A12		
2717	E 7		
2718	C17		
2719	J16		
2721	K16		
2781	J16		
3701	L 9		
3702	K 8		
3703	C13		
3704	C14		
3705	C14		
3706	C15		
3707	D14		
3708	D15		
3710	C15		
3711	D16		
3712	D16		
3713	D17		
3714	D18		
3716	E 9		
3717	E 8		
3718	H 9		
3719	I 7		
3720	J 5		
3721	H 8		
3722	I 6		
3723	J 5		
3724	H 5		
3725	I 6		
3726	J 3		
3727	N 5		
3728	E15		
3729	L 5		
3730	L 6		
3731	E 8		
3732	B17		
3733	B17		
3734	C17		
3735	E18		
3736	I15		
3737	J17		
3741	L16		
3742	L16		
3743	K15		
3747	H16		
3748	H15		
3749	G15		
3750	L 8		
3751	H16		
3752	G15		
3753	F15		
3754	K 6		
3755	C 4		
3756	C 4		
3757	C 3		
3758	C 3		
3759	E 8		
3769	K16		
3770	J15		
3771	K17		
3772	K17		
3775	L 4		
3776	L 4		
3777	L 3		
3778	L 3		
3779	L 3		
3780	N 3		
3781	J15		
4104	M 2		
4311	D 2		
4450	K 6		
4451	K 8		
4700	D 8		
4701	F15		
4704	J 3		
4706	C 8		
4707	N 6		
4708	C 8		
4709	C 9		
4710	K 7		
4712	H 5		
4713	G 4		
4714	F14		
4715	F 4		
4716	H 6		
4717	N 5		
4718	J 3		
4720	G 5		
4721	E 3		
4723	C17		
5701	L13		
5703	B12		
6705	M 7		
6707	M 5		
6708	K17		
6709	C16		
7701	C14		
7702	D14		


9251
9250
9246
30
31
10
11
2247
2244
9245
9247
9244

PCB 03166
T28/104



PRS 06912
T 26/105

Euro module
Euro-AV-Platte
Module Prise Péritélévision

ule
te
ur

PCB 03166
T28/104


EURO MODULE
1
2
3
4
A
B
C
D
SCL
SDA
V
+5
-
+14
CVBS PIP
R IF
L IF
SDA
SCL
+14
+8
PIP1
V
PIP2
CVBS EXT3
E26
E30
E32
E48
E23
EXT3
7801
7802
7800
6805
5800
3804
3802
3803
3805
3809
3816
3837
3813
2808
2809
2820
2819
2822
2802
2803
2800
2801
2831
2807
9000
9001
9002
9003
9004
9005
9006
9007
9008
9009
9010
CVBS IF
EXT 3
CVBS EXT1
CVBS STATUS3
CVBS EXT1/3
R EXT1/3
R EXT1
L EXT1/3
L EXT1


EURO MODULE
4
3
2
1
A
B
C
D
L IF
R IF
CVBS PIP
+14
-
+5
V
SDA
SCL
SDA
SCL
+14
+8
PIP1
V
PIP2
CVBS EXT3
EXT3
E48
E32
E26
E30
E23
7801
7802
7800
7820
7821
7822
7823
7824
6800
6801
6803
5800
4851
4852
4854
4855
4856
4858
3800
3801
3802
3803
3804
3805
3806
3807
3808
3809
3810
3811
3812
3813
3814
3815
3816
3819
3820
3821
3822
3823
3824
3825
3826
3827
3828
3829
3830
3831
3833
3834
3835
3836
3837
3838
2801
2803
2804
2805
2806
2807
2808
2809
2810
2811
2812
2813
2814
2815
2816
2817
2818
2819
2820
2821
2822
2823
2833
2834
9000
9001
9002
9003
9004
9005
9006
9007
9008
9009
9010
L EXT1
L EXT1/3
R EXT1
R EXT1/3
CVBS EXT1/3
CVBS STATUS3
CVBS EXT1
EXT 3
CVBS IF
PCB 03175
T28/107

E23	C3
E26	B2
E30	B1
E32	B3
E48	C4
2800	B3
2801	C4
2802	B3
2803	B4
2804	C2
2805	C2
2806	C2
2807	D1
2808	A4
2809	A4
2810	B4
2811	B4
2812	C1
2813	A1
2814	B1
2815	B2
2816	C4
2817	A3
2818	B2
2819	B3
2820	B2
2821	B3
2822	C2
2823	C2
2831	C1
2833	C3
2834	B3
3800	C4
3801	C3
3802	B4
3803	B4
3804	A4
3805	B4
3806	C3
3807	B3
3808	B3
3809	B3
3810	B3
3811	B3
3812	C1
3813	C3
3814	B1
3815	B1
3816	D4
3819	C2
3820	C2
3821	C2
3822	C2
3823	D2
3824	D2
3825	C1
3826	C2
3827	C1
3828	D2
3829	D1
3830	C1
3831	C1
3833	C3
3834	C3
3835	C2
3836	C3
3837	B1
3838	C2
4851	B3
4852	D3
4852	D3
4854	B3
4855	B2
4856	B2
4858	A3
5800	A3
6800	C1
6801	B3
6802	C2
6803	C2
7800	C1
7801	B2
7802	C3
7820	B1
7821	C2
7822	D1
7823	D2
7824	C3
9000	C4
9001	C3
9002	C4
9003	C4
9004	B2
9005	C2
9006	B2
9007	C2
9008	B1
9009	C3
9010	C2

Tuner / Kanalwähler / Sélecteur


B
1
2
3
4
5
6
7
8
9
10
A
B
C
D
E
F
G
H
I
J
K
L
M
N
O
1)
2001
150u
3001
27
+14
12V7
1000
6
UV916
7) U944
M
16
17
IF
B40
0V
2004
12p
DIV
AGC
B41
4V6
9V3
F.REF
4MHz
512
I²C
15
11
12
13
14
2V8
SDA
A2
SCL
3010
1k
A8
3V
2008
100p
2230
22n
38
32
3222
100k
-16A
2002
22n
3003
2k2
+5A
5V4
7003
BC817
4V7
2003
100n
1V4
(1V1..32VS)
VVAR1
3002
22k
A39
2)
3004
4k7
3006
4k7
3008
4k7
3009
1k
A13
7001
BC558
3007
A14
7002
BC558
3005
A15
7000
BC558
12V6
0V/12V
7
8
10
UV917
7) U743
5V6
2002
82n
9M50
7M50
8M50
1001
IF/SOU
2M50
3M50
3M51
4M51
5M50
AGC
CVBS
L IF
R IF
CVBS IF
25
26
B54
B50
B51
B46
A31
A32
CVBS IF
FBOFF
CVBS STATUS1
L IF
R IF
10M21
+5
3890
10k
3886
4k7
3887
5k6
2250
8n2
2251
8n2
0V
0V7
7805
BC848
2810
4n7
4711
CVBS STATUS1
RC5
3883
100k
3885
22k
1V3
2V
7810
BC848
4V
3884
100k
4306
3261
75
3262
75
47
1
2
3
A41
C42
C43
C44
C45
3859
100
3858
3857
3856
RGBSTATUS
3850
68
CVBS IF
B
G/V
R
3888
1k2
3253
150
3254
150
49
EXT1
20
18
16
14
12
10
8
6
4
2
21
19
17
15
13
11
9
5
3
3250
1k
4854
2255
470n
4857
R EXT1
B49
2256
270p
3860
3855
62
CVBS EXT1
B52
3851
75
3852
3853
3854
L EXT1
B48
4856
2254
470n
4855
3251
2257
270p


IF/SOUND MODULE ZF/TON MODUL MODULE FI/SON
G: MONO
H: STEREO/ESTEREO
I: NICAM
EURO MODULE
MODULO SCART
MODULO EURO
CVBS IF
B46
A12
+8
+14
B61
A9
A3
A17
A16
A18
A21
A38
A34
B47
SCL
SDA
BI/L
POS/NEG
I/BG
IDENT
AFC
EXT1
CVBS EXT 4852
B53
A20
A19
D86
D82
A4
A10
C69
CVBS EXT2
PIP1
PIP2
7823 BC848
7820 BC848
7800 BD943
7801 HEF4053
7802 HEF4053
7821 BC848C
7822 BC858
7824 BC848
7312 HEF4053
CVBS PIP
CVBS EXT1/3
CVBS EXT1
CVBS EXT3
EXT1
EXT2
EXT3
B47
B52
A33
B48
B49
B51
B50
A30
CVBS STATUS3
R IF
L IF
R EXT1
L EXT1
R EXT1/3
L EXT1/3
R EXT3
L EXT3
R EXT2
L EXT2
+14A
+14B
+14C
+5
+14
V
0V
11 12 13 14 15 16 17 18 19 20 21 22

REMARKS/REMARQUES/ANMERKUNGEN/NOTE
PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEND IN GERÄTEN:
PRESENTE IN MODELLI:
PRESENTE SOBRE MODELLOS:

1) STEREO
2) MONO
3) EXT2
4) NON EXT2
5) EXT3
6) NON EXT3
7) UK

Sound / Ton / Son


22
23
24
25
26
27
28
29
30
31
32
33
8M51
10M51
B60
B59
5M51
6M51
L EXT
R EXT
+16
1240 1.6AT
5240 27u
+16A
4223
+16B
2240 1000u
2237 100n
-16
5242 27u
1242 1.6AT
-16A
3220 3k9
2242 1000u
2239 100n
D62
PROT.
4863
1)
2)
+14A
3224 2k2
3225 2k7
2231 100u
3226 33k
2232 22n
3227 33k
7V6
7V5
7243 BC858
0V
3228 150
6248 1N4148
7249 BC848
7248 BC848
3229 5k6
2248 330u
2249 22n
3244 10k
3245 10k
6247 LL2C3V3
6246 LL2C3V3
3218 680
3238 1k2
TP36
7240 TDA1521
3242 33k
3243 33k
3246 330
3234 22k
7246 BC848
3236 5k6
2236 4n7
TP34
0V7
15V4
2241 100n
2243 22n
3247 100
2233 22n
3240 8R2
3249 100
3248 330
2234 22n
TP32
3219 680
3229 1k2
3235 22k
7247 BC848
3237 5k6
2238 6n8
-16V
TP33
2245 22n
4272
3241 8R2
6249 1N4148
3233 10k
2246 22u
3231 4k7
3232 100
7244 BC858
7245 BC848
3230 22k
6245 1N4148
2235 00X0
0V6
2M30
3M30
30mV
0.2ms/div
B61
E90
E91
A+C+D+E
39
4224
3M23
2M23
1M23
9247
2247 4u7
9251
1M19
3M19
9245
9246
9244
3M24
2M24
1M24
2244 4u7
1V3
SVHS 10µ
TP3
UNGEN/NOTE
EXT2
A35
4858
4867
7312 HEF4053
7311 HEF4053
4859
6V5
6V4
13V9 (1V7)
TP39
2V8 (1V7)
C56
C57
D58
4851
TP20
2V8 (0V4)
C55
4850
CVBS
B54
2V8 (2V)
TP40
3886 10k
3861 5k6
2800 47u
(..V)→ SVHS
3871 100
3869 100
3867 75
3882 470
3868 75
3880 1k
3881 470
5801 27u
2805 47p
CVBS EXT2
B53
470n
270p
800mV
TP33
TP34
7240 TDA2613
3239 1k2
3221 1k
4233
4237
4239
3243
3249 39
3248 330
2234 22n
TP35
2246 47u
3231 4k7
3230 22k
2235 22n
0V4
700mV
SVHS 20µs/div
TP20
2V
1V4
CHASSIS
CL06532


B
26
27
28
29
30
31
32
33
34
1)
2)
D62
PROT.
+14A
+16A
-16A
+16B
3224 2k2
3225 2k7
2231 100u
3226 33k
2232 22n
3227 33k
7V5
7V6
7243 BC858
3228 150
4863
6248 1N4148
7249 BC848
7248 BC848
3229 5k6
2248 330u
2249 22n
3244 10k
3245 10k
6247 LL2C3V3
6246 LL2C3V3
B59
B60
B61
3218 680
3219 680
R
L
3238 1k2
3229 1k2
TP35
TP36
TP32
TP33
7240 TDA1521
3234 22k
7246 BC848
3236 5k6
2236 4n7
3235 22k
7247 BC848
3237 5k6
2238 6n8
0V7
15V4
-16V
2241 100n
2243 22n
2245 22n
3240 8R2
3241 8R2
3242 33k
3243 33k
3246 330
3247 100
2233 22n
3249 100
3248 330
2234 22n
4224
4222
3M23
2M23
1M23
1M19
3M19
3M24
2M24
1M24
9247
2247 4u7
9251
9245
9250
9246
9244
2244 4u7
1L30
2L30
3L30
1L20
2L20
3L20
1L31
2L31
3L31
3L21
2L21
1L21
2246 22u
6249 1N4148
3232 100
3233 10k
3231 4k7
3230 22k
6245 1N4148
2235 00X0
7244 BC858
7245 BC848
0V6
2M30
3M30
30mV
0.2ms/div
840mV
1V3
SVHS 10µs/div
TP39
E90
E91
A+C+D+E
850mV
TP33
2V
10µs/div
TP40
550mV
0.2ms/div
23
200mV
24
800mV
TP34
7240 TDA2613
3239 1k2
3221 1k
4233
4237
2246 47u
2235 22n
4239
3249 39
3248 330
25
26
1V7
1V4
TP35
700mV
0V4
SVHS 20µs/div
TP20
PRS 06910 1 26/105
CHASSIS GR2.1
CL06532002/011.BREF 040291

1000	L 1	3229	L26	4222	G29
1000	C 1	3229	F28	4223	C24
1001	A 7	3229	C26	4224	C32
1006	D11	3230	O26	4233	N27
1240	B24	3230	H26	4237	N27
1242	F24	3231	O26	4239	L31
2001	K 1	3231	G26	4306	K 8
2001	B 1	3232	N27	4312	B11
2002	N 4	3232	G28	4314	C11
2002	F 2	3233	G29	4711	I 8
2003	G 3	3234	E26	4759	J 9
2004	M 4	3235	F26	4800	M11
2004	D 4	3236	E27	4850	M13
2008	G 4	3237	M27	4850	K25
2230	N 2	3237	F27	4851	F13
2230	F 1	3238	D27	4851	J25
2231	J27	3239	M28	4852	B15
2231	B27	3240	F30	4852	J18
2232	J29	3241	N29	4853	J20
2232	B29	3241	G30	4854	H18
2233	E31	3242	D29	4854	N11
2234	M31	3243	D30	4855	O 9
2234	F31	3243	M30	4855	F13
2235	O27	3244	K30	4856	O 8
2235	H27	3244	C29	4857	F15
2236	E28	3245	L30	4857	O11
2237	D24	3245	C29	4858	I22
2238	M28	3246	D30	4859	I23
2238	F28	3247	E30	4862	D19
2239	F25	3248	M31	4863	J30
2240	D24	3248	F31	4863	B30
2241	L29	3249	M30	4865	D19
2241	F29	3249	F30	4866	D19
2242	F24	3250	N10	4867	I24
2243	E30	3251	O 9	4900	M 7
2244	F33	3253	L10	5240	C24
2245	N29	3254	L10	5242	E24
2245	G30	3255	L21	5800	E12
2246	N26	3256	L21	5801	N23
2246	G26	3257	H20	6245	H26
2247	D33	3258	H21	6246	L30
2248	L27	3259	H21	6246	D30
2248	C27	3260	H21	6247	L30
2249	L27	3261	J 9	6247	C30
2249	C27	3262	J10	6248	B27
2250	H 1	3263	L19	6248	K27
2251	H10	3264	M19	6249	G28
2252	H21	3265	K19	6800	F16
2254	O 8	3266	L19	6801	H18
2255	N11	3800	G12	6802	H16
2256	N10	3801	L11	6803	I16
2257	O 9	3802	N15	7000	K 2
2262	L21	3803	N15	7001	K 4
2263	L21	3804	L13	7002	K 3
2264	K21	3805	L14	7003	G 3
2265	K21	3806	L12	7240	M28
2800	L12	3807	L12	7240	D28
2800	L23	3808	L13	7243	J29
2801	L13	3809	L13	7243	B29
2802	L13	3810	I18	7244	O27
2803	L14	3811	I18	7244	G27
2804	G14	3812	E16	7245	G29
2805	H13	3813	L12	7246	E27
2805	O23	3814	F17	7247	M27
2806	H14	3815	F17	7247	F27
2807	F17	3816	N15	7248	L28
2808	O16	3819	I12	7248	C28
2809	O16	3820	I12	7249	K27
2810	I 8	3821	H13	7249	C27
2810	L13	3822	I12	7311	I23
2811	L14	3823	G13	7312	I21
2812	F16	3824	G13	7800	E17
2813	F18	3825	E15	7801	F14
2814	E17	3826	G16	7802	J14
2815	I15	3827	G17	7805	I 7
2816	O17	3828	H17	7810	J 8
2817	L15	3829	H16	7820	E16
2818	G16	3830	G16	7821	G16
2819	I18	3831	I16	7822	G17
2820	F14	3833	J12	7823	F12
2821	F13	3834	I13	7824	I17
2822	H17	3835	F12	9244	F33
2823	F13	3836	I18	9245	D33
2831	I16	3837	E12	9246	E33
2833	J12	3838	I13	9247	C33
2834	J13	3850	M 6	9250	D34
2875	K19	3851	N 8	9251	D33
3001	J 1	3852	N 8		
3001	B 2	3853	N 8		
3002	N 5	3854	N 9		
3002	H 5	3855	O 7		
3003	F 3	3856	M 6		
3004	J 2	3857	L 6		
3005	K 5	3858	L 6		
3006	J 3	3859	L 6		
3007	K 5	3860	N 7		
3008	J 4	3861	L22		
3009	J 5	3867	M22		
3010	F 5	3868	M23		
3218	D26	3869	L23		
3219	M26	3871	L22		
3219	F26	3874	I19		
3220	F24	3875	J19		
3221	M26	3880	N22		
3222	G 1	3881	N23		
3222	N 3	3882	M23		
3224	I27	3883	J 8		
3224	B27	3884	K 8		
3225	J27	3885	J 8		
3225	B27	3886	H 8		
3226	J28	3886	L23		
3226	B28	3887	H 8		
3227	J28	3888	L 9		
3227	B28	3890	H 7		
3228	J30	3963	C31		
3228	B30	3963	K31		

Video


C
1)
B55
C
2300
22p
+14D
3300
5k6
7301
BC848
3V9
3V3
3301
2k7
3302
2k2
3304
4k3
6300
LL4148
3303
1k8
5301
3305
430
2305
33p
0V8=PAL
3V3=SECAM
2304
2n7
7302
BC858
3306
10k
0V=PAL
6V1=SECAM
2301
470p
2303
270p
2370
330n
2311
100n
6V=PAL
0V=SECAM
PAL SW.
E63
7306
TDA 4650
2312
10n
2310
10n
2317
82p
2318
100p
3311
390
3312
500
4303
5304
2316
27p
3308
330
3309
330
2319
27p
2353
100n
SECAM REF
IDENT
PAL NTSC
SECAM
PAL
SECAM
NTSC3.5
NTSC4.4
2xFq
HUE CONTROL
R-Y
B-Y
Bk
2321
22n
2322
22n
1300
8.86M
2313
22p
3313
3k3
2325
47n
2314
330n
2326
100n
2308
10n
2309
10n
2307
220p
10V3
12V2
2)
7305
TDA4510
3303
3k3
2301
18p
5301
2304
1n5
4302
2303
390n
2312
10n
2311
10n
3355
RES
2353
100n
2310
10n
REF
FF
H/2
(B-Y)REF
(R-Y)REF
8.88MHz
/2
2325
47n
2314
330n
3310
5k1
3313
10k
2322
22n
A
B
C
D
E
F
G
H
I
J
K
L
M
N
O
1
2
3
4
5
6
7
8
9
10
11

Video


2
3
4
5
6
7
8
9
10
11
12
13
14
1)
7306
TDA 4650
SECAM REF
IDENT
PAL NTSC
SECAM
PAL
SECAM
NTSC3.5
NTSC4.4
2xFq
HUE CONTROL
R-Y
B-Y
BK
2317 82p
2318 100p
3311 390
3312 500
4303
5304
2316 27p
3308 330
3309 330
2319 27p
2353 100n
2312 10n
2310 10n
+14D
3300 5k6
3301 2k7
3302 2k2
7301 BC848
3304 4k3
6300 LL4148
3303 1k8
5301
3305 430
2305 33p
2301 470p
2303 270p
2311 100n
2370 330n
2300 22p
2304 2n7
3306 10k
7302 BC858
0V8=PAL
3V3=SECAM
0V=PAL
6V1=SECAM
6V=PAL
0V=SECAM
PAL SW.
C
3V9
3V3
TP19
3V4
8V3
2321 22n
2322 22n
1300 8.86M
2313 22p
2325 47n
2314 330n
2326 100n
3313 3k3
2308 10n
2309 10n
2307 220p
2306 220p
7V6
5V8
2V6
2V7
8V2
10V3
1V3
7V
6V
2V5
3V6
3V1
12V2
D84
R-Y
B-Y
C66
C67
D85
18
19
20
C63
PAL
B56
A36
EX
..V = C
(..V) = EX
D83
A24
A25
A26
A27
D68
2)
7305
TDA4510
REF
FF
H/2
/2
8.86MHz
G
Bk
(B-Y)REF
(R-Y)REF
3355 RES
2353 100n
2310 10n
3303 3k3
2301 18p
2304 1n5
4302
2303 390n
2312 10n
2311 10n
4304
1300 8.86M
2313 22p
2325 47n
2314 330n
3310 5k1
3313 10k
2322 22n
3394


14
15
16
17
18
19
20
21
22
23
24
25
+14D
3332
390
+6
3330
10
3331
10
6310
BZX79 5.6V
2351
22n
2345
22n
7307
TDA4660
5V5
64us
G
VCO
3375
1k
2349
1n
1V3
2375
100p
TP2
C66
3376
1k
2352
1n
2376
100p
TP1
C67
D85
3314
10k
4323
1V
3315
1k8
6318
LL4148
3344
910
13
3V7
3316
1M
2327
10n
3358
1k
R-Y
2328
220n
4320
2359
100p
3359
1k
B-Y
2329
220n
4321
2346
100p
4322
8008
CTI
+14D
2350
22n
7308
TDA 4565
12V2
TP3
TP4
TP5
4V4
2333
220n
2V
D.L.
180ns
4V6
5V3
4V5
5V2
Y
10V7
3V7
3V
1V4
2331
100p
2330
100p
2332
330p
3356
45k6
3327
1k2
3325
270
3326
270
3328
47k
4317
4318
2334
220p
2335
220p
3374
82k
3372
4k7
7373
BC848
3373
1k
3329
82k
RES.
7V9=PAL
12V2=SECAM
4301
2340
22n
4308
2V9
TP7
4326
2341
22n
4307
TP6
2323
47n
2385
100p
TP8
7309
TDA 4680
HUE
MATR
R.B.B.
1V4
5V2
6316
1N4148
+9
3362
4k7
2358
22n
2357
22n
C63
PAL SW.
B56
4300
2384
100p
2320
3) 33p
4) 82p
2V7
(2V)
3307
680
5303
3) 47u
4) 39u
2368
3) 10p
4) 15p
2315
3) 10p
4) 15p
A36
EXT2
3343
100k
0V
(2V3)
7303
BC848
1V5
(1V1)
+14D
7310
BC848
1V
3342
1k
3361
1k3
3357
1k
5306
LAR 330ns
3360
1k
..V =
(..V) = EXT2
㉑
D83
A24
R
3353
2k2
A25
G/V
3352
2k2
A26
B
3351
2k2
A27
FBL
3354
220
㉒
3350
1k
3347
330
3369
100
3348
330
3368
100
3349
330
3367
100
3365
6) 150k
7) 120k
D68
NIL
17V
4M18
3M18
7M18
6M18
5M18
8M18
2M18
1M18
4T7
3T7
7T7
6T7
5T7
8T7
2T7
1T7
FBC
G/V
1003
SDA
SCL
2T6
1T6
+8
+14
5T6
6T6
4T6
3T6
2M17
1M17
5M17
6M17
4M17
3M17
10V2
13V9
1V3
4314
+8V
+14V
+14B
3394
100k
2V9
3V1
3V4
7372
BC848
7374
BC848
3395
68k
2V8
A5
A11
4316
13V9
7371
BC848
1V9
3339
1k5
6317
1N4148
3340
1k2
3338
1k
A17
B57
D76
BCL
2366
6u8
2367
10u
6315
1N4148
3366
18k
6367
BZX79C5V1
3370
3k3
PBCL
4V6
7370
BC848
0V
4309
2374
47p
3371
4k7
4319
F101
3323
470k
+5
4329
1P17
2P17
3P17
4P17
5P17
6P17
7P17
8P17
9P17
V
B69


C
25
26
27
28
29
30
31
32
33
34
A6
A7
SDA
SCL
3381 100
3380 100
2381 120p
2380 120p
2V8 27
3V1 28
680
+9
8V5
5
2362 100n
2342 100n
2343 100n
2361 100n
2360 100n
2344 100n
4V2
4V3
25 23 21
+14A
6303 BZX79C8V2
6302 BZX79C8V2
3334 18
3335 18
+14D
2339 100n
2355 100n
I²C
MATR Y
CUT OFF CONTROL
24 2V9
20 2V9
22 3V1
F100
F102
F104
TP9
TP10
TP11
14 1V4
2 5V2
3 5V2
4 5V2
1
15 4V7
12 5V2
11 5V2
10 5V2
13 0V
9 0V
16 3V8
17 7V4
18 6V4
19 6V4
R
G
B
FBL
4325
4324
3317 2K2
3318 10k
F103
2358 22n
2357 22n
2356 22n
2338 22n
2337 22n
2336 22n
2354 1u
2365 1u
2363 39p
1M12
2M12
3M12
4M12
5M12
1P16
2P16
3P16
4P16
5P16
G/V
1P56
2P56
3P56
4P56
5P56
+14
CVBS PIP
8P17
9P17
10P17
5M27
4M27
3M27
2M27
1M27
B42
B43
B44
B45
A+B+D+F
1V1
650mV
10µs/div
TP1
1V7
2V5
TP9
0V9
440mV
TP2
1V9
TP10
3V8
900mV
TP3
2V
TP11
0V
200mV
TP19
1V2
TP4
8V
20µs/div
18
1V3
1V
TP5
6V8
500mV
19
2V3
TP6
700m
20
0V8
2V4
TP7
9V
21
2V7
0V4
TP8
3V5
22
PRS 06909
T 26/105

REMARKS/REMARQUES/ANMERKUNGEN/NOTE

PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEND IN GERÄTEN:
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS:

1) PAL/SECAM
2) PAL
3) SECAM
4) MONO
5) PAL/SECAM STEREO
6) BLACK LINE
7) NON BLACK LINE

CHASSIS GR2.1

CL06532002/012.CREF
040291

1300	F 8	3329	G22
1300	M 7	3330	B17
2300	D 3	3331	B17
2300	J 3	3332	A16
2301	D 6	3334	B33
2301	J 5	3335	B34
2303	D 6	3338	M20
2303	L 5	3339	M19
2304	E 4	3340	M19
2304	L 4	3342	I18
2305	D 5	3343	H15
2306	F12	3344	F15
2307	F11	3347	K16
2308	F11	3348	K16
2309	F11	3349	K17
2310	B 8	3350	K15
2310	J10	3351	J15
2311	D 6	3352	J15
2311	L 6	3353	I15
2312	B 8	3354	J15
2312	L 6	3355	J 9
2313	G 8	3356	F22
2313	N 7	3357	H20
2314	G10	3358	D18
2314	M 8	3359	D16
2315	H18	3360	I21
2316	B 9	3361	I18
2317	A 9	3362	G25
2318	A 9	3365	K18
2319	B10	3366	L20
2320	G16	3367	K17
2321	F 8	3368	K17
2322	N 9	3369	K16
2322	F 8	3370	L21
2323	E24	3371	M22
2325	G 9	3372	G20
2325	M 8	3373	G20
2326	G10	3374	G21
2327	F16	3375	D15
2328	D19	3376	D15
2329	D19	3380	B27
2330	F21	3381	B26
2331	F20	3394	M14
2332	F21	3395	M16
2333	E20	4300	G15
2334	G23	4301	D23
2335	G23	4303	B 9
2336	G27	4304	K12
2337	G27	4307	D24
2338	G27	4308	D24
2339	C32	4309	M21
2340	D24	4314	M17
2341	D24	4316	K19
2342	C30	4317	F22
2343	C30	4318	G22
2344	C31	4319	M22
2345	C17	4320	D19
2346	E18	4321	D19
2349	D15	4322	A21
2350	C22	4323	E15
2351	C17	4324	G28
2352	D15	4325	F28
2353	B11	4326	D24
2353	J 9	4329	N22
2354	G29	5301	D 5
2355	C33	5301	K 5
2356	G26	5303	H16
2357	G25	5304	B 1
2358	G25	5306	H20
2359	D18	6300	D 5
2360	C31	6302	C32
2361	C30	6303	B32
2362	C29	6310	C16
2363	G29	6315	K20
2365	G29	6316	F25
2366	L19	6317	M19
2367	L20	6318	E15
2368	H17	6367	L21
2370	C 6	7301	D 4
2374	M22	7301	J 4
2375	D15	7302	E 5
2376	E15	7303	H16
2380	C27	7305	J 7
2381	C26	7306	C 7
2384	G15	7307	C16
2385	E24	7308	C20
3300	C 3	7309	C25
3300	J 3	7310	H18
3301	D 3	7370	L21
3301	K 3	7371	L19
3302	D 4	7372	N15
3302	K 4	7373	G21
3303	D 4	7374	N16
3303	J 4	8008	B21
3304	D 4		
3305	D 5		
3305	K 5		
3306	E 5		
3307	H16		
3308	B 9		
3309	B10		
3310	M 8		
3311	B 9		
3312	B10		
3313	F10		
3313	N 8		
3314	E15		
3315	E15		
3316	F16		
3317	F29		
3318	F30		
3323	K23		
3325	F23		
3326	F23		
3327	F22		
3328	F21		

Monocarrier / Hauptplatine / Châssis


G
F
E
1
2
3
4
5
INSTALL
SERVICE
P+
P–
+
–
3503
3605
3607
5605
M10
M11
1600
2600
3604
3606
5606
3627
2626
7625
6622
3622
2625
3626
2620
2617
3620
3617
6617
6621
3624
3625
2611
3610
5619
3619
9740
6612
TP28
TP30
TP29
7614
5625
6709
5703
2706
2661
5661
3887
3771
9660
7661
3658
6661
2710
9803
3779
9708
TP17
TP18
5701
7702
9712
TP15
TP16
7708
TP13
TP14
TP11
3737
9550
3734
2632
6630
2660
2646
9793
3671
2671
6649
3675
TP25
TP26
TP27
3634
6670
6680
6664
6648
7600
TP24
2663
TP21
TP22
TP23
3884
M40
3718
3759
3719
9801
TP12
9616
9639
3733
3736
9640
9624
9730
3727
3728
3730
3711
9774
3777
9702
2703
2707
M17
3338
9622
9653
9641
M14
9642
9659
9769
3369
3368
3367
9600
9514
TP9
TP10
TP11
7309
TP6
TP7
TP8
9770
2354
2366
2365
3351
3352
3353
3350
3347
3348
3349
6707
M26
6309
6308
M12
3384
9628
5303
5302
3333
3327
3374
3335
6316
9610
9608
9672
1003
M20
TP5
7308
TP4
TP3
3324
2313
1300
2314
3310
9300
TP19
TP20
9677
9711
9750
9673
9877
2718
2328
3332
2329
3247
3249
5306
7307
7306
7305
2370
3336
3337
1242
2231
9876
M39
3246
3248
TP1
TP2
3312
5304
2356
M23
M24
3242
3249
M30
9248
M19


D
C
B
A
M15
M13
M16
M17
M18
M21
M22
M27
M28
M29
M47
M50
M51
TV
1534
1599
1500
1617
TP23
TP31
TP32
TP33
TP34
TP35
TP36
TP37
TP38
TP39
TP40



PCB 03145
T21/051

32	5D
33	3G
34	4G
37	1F
38	5B
M10	1F
M11	1G
M12	4G
M13	2B
M14	4E
M15	1B
M16	3A
M17	3E
M18	3D
M19	5E
M20	4G
M21	4A
M22	3A
M23	5E
M24	5E
M26	4G
M27	3A
M28	1E
M29	3B
M30	5G
M35	4A
M39	5G
M40	3G
M47	2A
M50	4B
M51	4D
0049	3A
1000	5B
1003	4G
1240	5D
1242	5E
1300	5F
1534	2D
1559	2A
1580	3B
1600	1G
1702	2G
2001	5A
2231	5E
2240	5C
2242	5C
2246	5D
2248	5E
2250	3A
2251	3A
2252	3A
2254	3A
2255	3A
2264	4A
2265	4A
2313	4F
2314	4F
2328	5G
2329	5G
2333	4G
2354	4F
2355	5F
2364	5E
2365	4F
2366	4F
2367	4D
2370	5F
2456	4D
2458	3C
2465	3C
2466	4C
2468	4C
2469	4C
2471	4C
2473	4D
2502	1A
2506	2A
2509	2A
2520	1D
2522	1C
2524	2D
2526	2C
2528	1C
2531	1C
2532	1C
2533	2C
2538	3C
2539	3B
2545	1B
2546	1A
2547	1A
2549	1B
2550	1C
2551	2C
2559	2C
2560	2B
2563	2B
2570	2C
2574	3B
2580	3B
2585	2B
2590	3C
2600	1F
2603	1D
2605	1D
2607	1D
2611	1F
2617	1F
2620	1E
2625	1E
2626	1E
2630	2D
2631	2C
2632	2E
2640	3D
2641	3D
2646	2E
2652	3D
2653	3D
2660	2E
2661	2F
2662	3E
2663	3E
2664	3E
2671	2E
2675	2D
2676	2D
2703	3G
2706	2F
2707	4G
2713	5G
2800	5A
3001	5A
3218	5C
3219	5C
3221	5D
3222	5D
3224	5D
3230	5C
3239	5C
3240	5D
3241	5D
3242	5E
3243	5D
3246	5G
3247	5G
3248	5G
3249	5G
3250	3A
3251	3A
3253	3A
3254	3A
3255	4A
3256	4A
3265	4A
3266	4A
3310	5E
3312	5F
3323	4F
3324	4F
3327	4G
3332	5G
3334	4G
3335	4G
3336	5E
3337	5E
3338	4E
3340	3D
3347	4E
3348	4E
3349	4E
3350	4E
3351	4E
3352	4E
3353	4E
3365	3D
3367	4E
3368	4D
3369	4E
3374	4G
3450	2A
3451	4D
3452	4C
3457	3C
3461	4C
3467	3C
3470	4C
3471	4C
3473	4C
3483	3C
3502	1A
3503	1A
3504	2A
3506	3A
3507	2A
3513	3A
3516	3A
3520	1A
3521	2C
3525	2C
3534	1C
3535	1A
3538	2C
3539	1B
3542	2C
3545	2C
3546	3B
3550	1C
3551	2C
3552	2C
3553	2C
3560	2C
3570	2B
3582	3B
3585	2B
3588	1B
3589	1B
3590	3C
3603	1G
3604	1F
3605	1F
3606	1F
3610	2E
3617	1E
3619	1E
3620	1E
3622	1E
3624	1E
3625	1E
3626	1E
3627	1E
3631	2D
3634	3D
3635	3D
3647	3D
3649	3E
3658	2E
3671	2E
3675	2E
3711	3G
3718	3G
3719	3G
3720	3G
3727	3G
3728	3G
3732	3C
3733	3F
3734	2F
3736	3F
3737	2F
3759	3G
3771	2F
3777	3G
3779	2G
3850	4A
3855	4B
3860	4A
3869	5A
3871	5A
3874	4A
3880	4A
3881	4A
3882	4A
3884	3E
3887	2F
3888	4A
5001	5B
5240	5D
5242	4D
5301	5E
5302	4G
5303	4G
5304	5F
5306	5G
5530	1C
5534	1D
5541	1C
5541	2C
5549	1C
5554	2C
5582	3B
5588	1B
5605	1F
5606	1F
5619	1E
5625	1B
5625	2E
5630	2D
5631	2C
5632	3D
5661	2F
5701	2F
5703	2F
5801	4A
6245	5C
6302	4G
6303	4G
6309	4G
6316	4F
6317	3D
6465	3C
6503	1A
6546	1B
6547	1A
6548	2C
6549	2C
6551	1C
6561	2D
6563	2B
6570	2B
6571	2B
6580	3B
6585	2B
6591	3B
6592	3B
6612	2E
6617	1E
6621	1E
6622	1E
6630	2E
6640	3D
6641	2D
6646	2D
6648	3E
6649	2E
6660	3E
6661	2E
6663	3E
6664	3E
6670	3E
6675	2D
6707	4G
6709	2F
7240	5C
7305	5F
7306	5F
7307	5G
7308	4G
7309	4F
7311	5B
7312	4A
7470	4C
7500	2A
7502	1A
7503	2A
7533	1C
7534	1C
7540	3C
7545	1B
7546	1A
7600	3E
7614	2E
7625	1E
7661	2F
7708	2G
7710	2G
9248	5F
9249	5E
9300	5E
9502	1B
9505	4B
9520	1D
9530	1C
9534	2D
9549	1C
9550	2F
9551	3F
9600	4E
9605	3D
9607	1F
9608	4F
9610	4F
9611	2G
9612	4E
9613	3C
9614	4E
9615	3F
9616	3F
9617	3F
9618	2F
9619	3B
9620	3B
9622	4E
9623	3E
9624	3F
9626	2A
9627	3A
9628	4G
9629	3F
9630	3B
9631	4C
9632	3B
9634	3F
9635	3C
9636	3B
9637	4C
9638	3C
9639	3F
9640	3F
9641	4E
9642	4D
9643	4D
9644	4D
9645	3E
9646	5B
9647	5C
9648	4B
9649	3F
9650	2F
9651	3B
9652	2F
9653	4E
9654	4D
9655	4C
9656	5B
9657	4D
9658	3E
9659	4E
9660	2F
9662	4D
9663	4B
9664	3F
9665	2F
9666	3F
9668	2D
9669	3C
9670	3B
9671	3C
9672	4F
9673	5E
9674	4C
9675	4B
9676	5E
9677	5E
9678	4B
9679	3B
9681	3B
9684	3B
9685	3B
9686	4C
9687	4C
9688	5B
9690	5D
9691	3D
9692	2D
9693	2D
9694	1A
9695	2C
9696	2C
9697	3D
9699	3D
9700	4B
9701	2G
9702	3G
9703	2G
9704	4B
9705	3G
9707	3G
9708	2G
9709	2G
9710	4B
9711	4E
9712	4E
9713	3E
9714	3F
9715	3B
9717	3F
9718	4B
9719	5B
9720	3B
9721	3D
9723	2C
9724	3C
9725	3C
9727	1B
9728	1B
9729	1C
9730	3F
9732	3F
9733	3C
9734	3C
9735	1C
9736	2C
9737	2C
9738	3C
9739	3C
9740	1E
9741	2B
9742	2D
9743	3D
9744	4A
9745	4D
9746	5D
9747	5C
9748	5C
9749	4D
9750	4E
9751	4D
9752	4D
9753	4D
9755	4B
9756	4B
9757	5C
9758	4B
9759	4B
9760	5C
9764	4E
9765	3D
9766	4E
9768	3D
9769	4D
9770	4F
9772	2F
9773	3F
9774	3G
9775	2B
9777	4E
9778	5C
9779	4D
9780	4D
9781	5D
9783	5D
9784	5C
9785	5B
9786	4A
9787	4C
9788	4C
9789	4B
9790	1B
9791	3B
9792	3B
9793	2E
9796	3C
9797	4E
9798	3G
9799	3F
9801	3G
9803	2G
9806	4B
9843	4D
9854	4B
9869	5D
9876	5E
9877	4E

Power supply / Stromversorgung / Alimentation


D
+14E
3469 22
3468 6k8
2469 22u
2468 1u
2464 100n
3466 1k5
2466 4u7
2467 100n
3458 30k
2458 2n7
3457 10k
7V1
5V
2V9
4V5
11V7
7470 TDA2579
3462 18k
B58
Y 3470 3k3
2470 47p
15625Hz
H.REF.
DATA
IDENT.
3463 18k
3464 12k
IDENT
A22
4V7
2451 100n
6V2
7V5
50Hz
4V2
1V
0V7
2V7
3471 82K
2471 330n
2473 330n
3473 220K
2475 22n
3450 12k
3465 390k
2459 100n
3460 33k
4452
3461
2460
BC1
3467
FFB
D81
D99
D77
DEMAG.
8002
3603 9M1
3605 1k
3600 4M7
220V
M11
1600 2AT
2600 470N
5605 100u
5606 100u
3606 1k
2M10
1M10
1F32
2F32
1F10
2F10
2601 100n
3603 330
5600
3601
+B
6603 1N5061
6602 1N5061
2602
6604 1N5061
2604
6605 1N5061
2F33
2M28
3F33
1M28
1F33
3M28
284V
3) 286V
2603 RES
2605 220u 3) 68u
5625
3625 560k
3624 330k
13V1 (5V5)
7614-2A CNR50
3628 330k
V=
&
-3V (-0V5)
3619 15
5619 3u9 3) 4u7
7625 BUT12AF
2626 470p
2625 1n
3626 *
3627 *
2620 68n
5621 150u 3) 180u
4V6 (-0V7)
3620 120
6621 BYD33D
3610 15 3) 6R8
6610 LL4148
6611 BZV55F16
6612 BYD33D
2611 68u
-1V (2V8)
3629 6k8
2629 4n7
(...V)
6617 BZV85C5V1
2617 1u
3617 180
3622 47
6622 1N4148
2607 1n
2653
6675
2670 120p
6670 SFOR504
6661 BYD33D
4605
6669
2660
3648 27k
3647
6648
BZX79-F
3) BZX79-F
3651 100
BYI
A B C D E F G H I J K L M N O
1 2 3 4 5 6 7 8 9 10

REMARKS/REMARQUES/ANMERKUNGEN/NOTE

PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEND IN GERäTEN
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS:

1) 25"/28" BLACK LINE
2) 25"/28" NON BLACK LINE
3) 21"

*	1)	2)	3)
2460	4n7	1n	10n
3336	22	27	15
3337	22	27	15
3467	2M2	2M5	1M3
3546	1	5R6	39
3560	16k	20k	33k
3626	180	360	360
3627	-	360	360


10
11
12
13
14
15
16
17
18
19
20
21
+200
200V
2570
22u
148V
3)95V
+148
6571
BYD330
6570
BYD330
3570
6R8
1),2)5545
3)5545
F78
F79
F80
D74
F76
-26
(E/0) -27V8
6585
BYD330
3585
15
2585
10u
1),2)
+148
M15
M15
3589
470
3588
56
5588
33u
2588
2n2
9735
3)
F
VG2
+32
6485
1)BZX79-F8V2
2)BZX79-F10
3)BZX79-F15
+14
3546
11V7
10
3455
1k
6565
UZ-C10
6549
BAS11
12V3
7455
BC858
11V6
+32
3545
100
3)330
7545
BU508AF
7546
BUT11A
1M15
4M15
H
16 9V1
3456
6K8
2456
1u
2457
100n
3485
2K2
3542
820
6548
1N4148
2559
100u
4
5
5413
2
1
9502
2545
1n5
3)1n2
3539
680k
3)430k
6546
BY228-20
2546
1)10n
2)8n2
3)7n5
625Hz
7
11 1V
3543
100
0V4
7540
BC337
12V
2538
39n
3538
18K
6547
BYW95C/20
2547
22n
3)33n
2461
1n
8
12 0V4
9
17 1V4
3474
3K9
+14E
11V7
3483
33
3582
560
6580
BYV29F-400
6591
LL4148
6592
LL2C30
2465
220u
2580
1000u
1580
1.6AT
5582
15u
2574
2n2
+14
+14E
3459
82k
4452
50k
3461
3336
3337
+14A
+14D
12V
14V5
4221
2355
100u
+14B
+14C
4310
4315
3452
100
3451
100
TV
B82
A28
C83
C84
C85
C73
3M13
2652
1n
6640
BYD74B
+16V(6V5)
3)+12V6(3V8)
1) +16
2) +16
3) +12
2640
1000u
5632
27u
3659
100
2658
82n
2641
1000u
6641
BYD74B
1) -16
2) -16
3) -12
2653
1n
-16V(-6V5)
3)-12V6(-3V8)
B62
D70
D71
PROT
+5
3676
10K
A23
+32
6504
6630
BY229F
5630
RES
5631
27u
+148
2632
1n
9692
2631
100u
3)47u
148V(73V)
3)95V(36V7)
+148B
3631
220k
3)120k
+32
6666
LLZ-C36
3)LLZ-C4
2630
100u
3)47u
2636
2n2
3634
3K3
3)2K7
3635
1k
3637
100
3636
220k
2V4
(1V2)
3502
820
3535
820
6502
BYD74B
BYD330
6675
3)
32V4
3)39V8
+32
2676
1n
2675
1000u
4507
+32A
3675
120k
3)47k
6663
BZV55F15
3666
1k
2650
100n
7600
TDA8385
0V
1V1
8
11
9
2670
120p
3670
30k
2671
100n
3671
1k
7671
BC848
0V6
3672
10k
PROTECT
CONTROL
2
4603
7614-2B
CNR50
0V9
(1V4)
D99
6670
SFOR5043
1V9
10
12V4
16
0V
15
3
0V
4604
6661
BYD330
4605
6669
LL4148
3673
4K7
3674
1K1
6660
1N4148
CONTROL
START
5
1V2
(2V6)
7661
BD949
9V7
5661
33u
5V
+5
2660
680u
3661
180
2661
47u
4602
+5A
6646
BYD330
3649
33
6649
1N4148
2646
15u
2649
100n
0V4
13
0V1
14
0V2
12
0V2
3664
2K7
3663
4K7
2664
4u7
2662
270P
3)220P
2663
82P
3)100P
5V6
3648
27K
3647
36K
6648
BZX79-F12
3)BZX79-F10
6664
BZX79-F10
3)BZX79-F9V1
3669
1k
3668
1k
7672
BC848
3662
220
3660
100
7663
BC858
4V8
POR
A29
4V9
3658
6R8
6662
BZV55F5V1
6665
BZV55F4V7
3665
10k

Synchronization / Synchronisation


D
D74 F76 D77 F75
+32
1M13
3560
2560 33n
1) 2)
2590 680n
3591 470k
3590 100k
6590 LLZC43
7591 BC858
3592 680
PROT
D71
1559 1AT
6563 BYD74C
10V
+8
2539 100u
2563 2n2
3551 560
3552 560
3553 560
5554 LIN
2551 1u
6551 BYD33D
3550 15K
1) 2) 3 5549 1
2549 1) 470n 2) 390n
2550 390n 3) 470n
9549 3)
5534
5592 LLZC30
6561 BXZ79C47
6560 LL4148
16V8
1) 2) 1534 315mAT
2524 4u7
9534 3)
2533 1u
3) 3534 1
5530 3) 390u
9530 1) 2)
E/W
D72
PROT
D70
B86
C68
+32A
18V3 3) 15V4
7502 2SD1266P
6504 LL4148
2502 22u
17V8 3) 14V8
3502 820
6503 BYD33D
3503 1 3) 1R5
3535 820 3) 1K5
17V5 3) 14V6
4506
17V4 3) 14V2
6502 BZV55C43
3501 75 3) 100
7503 BD234
2500 220p 3) 470p
VD
D99
7500 BC337
0V7
V
NLL
3514 3K9
5V5 3) 10V6
7504 BC848
4V8 3) 9V9
3516 20k
3513 560
4504
7505 BC858
TV
2505 47n
3505 470
3M16
1M16
3506 150k
FFB
D81
2506 680u 3) 470u
3507 10k 3) 12k
2509 2u2
1) 2)
2507 22n
3517 2R2
3523 2R2
3508 2R2
3509 2R2
3504 100
3519 2R2
3529 2R2
3510 2R2
3511 2R2
3515 2R2
3540 39R
3520 680 1), 2)
2520 68u 1), 2)
3521 5k
3522 1K5 1), 2)
6519 LL4148
6518 LL4148
3512 10 1) 2)
3518 330 1) 2)
2522 330n 1) 2)
+14B
2528 1) 2) 180n
3536 1) 2) 8K2
2521 1) 2) 68n
3527 2K2 3) 33k
4501
BCI
D74
3526 82k 3) 100k
2526 1) 18n 2) 10n
3533 8K2
3532 10k 3) 15K
3531 100k 3) 0
2532 1u 3) 4u7
16V6 3) 8V2
2531 120n 3) 220n
3524 68k 1), 2)
9520 3)
4505
3530 1K 3) 0
3528 2K2 3) 680
7533 2SA1359
7530 BC848
0V6
1) 2)
7534 BC636
4500
3525 10k
-26
4503
16V 3) 7V8
CHASSIS GR2.1
A+B+C+D+F
CL06532002/013.DREF 040291
22 23 24 25 26 27 28 29 30

1534	F27	3503	K23	5554	D23
1559	B22	3504	L26	5582	F16
1580	F17	3505	K24	5588	C17
1600	J 2	3506	K26	5600	J 5
2355	G12	3507	L26	5605	I 3
2451	E 5	3508	L25	5606	J 3
2456	D12	3509	L25	5619	L 5
2457	D12	3510	M25	5621	L 6
2458	A 9	3511	M25	5625	I 8
2459	G 8	3512	N24	5630	I14
2460	H 8	3513	J25	5631	I17
2461	E11	3514	J25	5632	J12
2464	B 6	3515	M26	5661	N20
2465	F14	3516	J27	6485	B12
2466	B 7	3517	L24	6502	K22
2467	B 8	3518	N24	6503	J23
2468	B 6	3519	M24	6504	I22
2469	B 5	3520	M24	6518	N24
2470	C 5	3521	M25	6519	N24
2471	G 6	3522	M26	6546	D17
2473	G 6	3523	L25	6547	E17
2475	G 7	3524	N26	6548	D14
2500	L22	3525	N27	6549	C13
2502	J23	3526	L28	6551	D24
2505	J24	3527	L28	6560	F23
2506	L25	3528	N29	6561	F22
2507	L23	3529	M25	6563	B23
2509	L27	3530	N28	6565	C13
2520	M25	3531	M29	6570	A16
2521	M27	3532	M28	6571	A15
2522	N25	3533	M28	6580	F17
2524	F26	3534	F28	6585	B16
2526	L29	3535	K22	6590	B26
2528	L27	3536	M27	6591	F21
2531	M28	3538	E17	6592	F21
2532	M30	3539	D17	6602	I 5
2533	F28	3540	M26	6603	I 6
2538	E14	3542	D13	6604	J 5
2539	C23	3543	E13	6605	J 6
2545	D16	3545	D14	6610	M 1
2546	D18	3546	B13	6611	N 1
2547	E18	3550	D24	6612	N 1
2549	D26	3551	C22	6617	O 5
2550	D24	3552	C23	6621	M 6
2551	D24	3553	C23	6622	O 6
2559	D14	3560	B24	6630	I13
2560	B24	3570	A17	6640	I11
2563	C23	3582	F16	6641	J11
2570	A15	3585	B17	6646	N11
2574	F17	3588	B17	6648	N10
2580	F15	3589	B16	6649	N12
2585	B15	3590	B25	6660	N13
2588	C17	3591	B26	6661	M10
2590	B25	3592	B27	6662	O18
2600	J 3	3600	I 1	6663	L13
2601	I 5	3601	J 5	6664	O12
2602	I 6	3603	I 2	6665	O19
2603	J 7	3603	I 5	6666	J15
2604	J 6	3605	I 3	6669	M10
2605	J 8	3606	J 3	6670	L10
2607	O 9	3610	M 1	6675	K10
2611	N 1	3617	O 6	7455	C12
2617	O 5	3619	L 5	7470	B 6
2620	L 6	3620	M 6	7500	L23
2625	L 7	3622	N 6	7502	I23
2626	L 8	3624	K 2	7503	L23
2629	N 3	3625	K 2	7504	J26
2630	J14	3626	M 8	7505	J26
2631	J18	3627	M 8	7530	N29
2632	J13	3628	L 2	7533	N29
2636	J15	3629	N 2	7534	N30
2640	I11	3631	J16	7540	E14
2641	J11	3634	J16	7545	D15
2646	N11	3635	K16	7546	D16
2649	N13	3636	K15	7591	B27
2650	K14	3637	K15	7600	K14
2652	I11	3647	N10	7614-	K 5
2653	K10	3648	N10	7614-	L19
2658	J11	3649	N12	7625	L 7
2660	M10	3658	O18	7661	N19
2661	N20	3659	J10	7663	O19
2662	N17	3660	O19	7671	L12
2663	N18	3661	N18	7672	O16
2664	N16	3662	N18	8002	I 2
2670	L10	3663	N15	9502	O15
2671	L12	3664	N14	9520	N27
2675	L11	3665	O20	9530	F29
2676	L11	3666	K13	9534	F27
3336	F13	3668	O14	9549	D26
3337	G13	3669	O14	9692	J14
3450	G 8	3670	L11	9735	C17
3451	G11	3671	L12		
3452	G11	3672	L13		
3455	C12	3673	M12		
3456	D11	3674	N13		
3457	B 8	3675	K13		
3458	A 8	3676	I19		
3459	F11	4221	G15		
3460	G 1	4310	G14		
3461	G10	4315	G14		
3462	B 5	4452	G10		
3463	O 5	4500	N26		
3464	E 5	4501	L29		
3465	G 8	4503	N29		
3466	A 7	4504	J26		
3467	H 8	4505	N28		
3468	A 6	4506	K23		
3469	A 5	4507	L12		
3470	C 4	4602	N21		
3471	G 6	4603	L18		
3473	G 5	4604	M18		
3474	F11	4605	M10		
3483	F15	5530	F29		
3485	D13	5534	E26		
3501	K22	5541	D15		
3502	J22	5549	D25		

Mains module
Netzteil
Module secteur


2604
2605
5606
6604
2602
6602
2601
5601
5600
F10
F33
F32
3607
+280
DEG.

PCB.03172
T28/105



2µs/div
TP21



5µs/div
TP21 ⏻



TP22



TP23



TP24



5µs/div
TP25



TP26



20ms/div
TP26 ⏻

TP27



20ms/div
TP27 ⏻



5ms/div
TP28



10ms/div
TP28 ⏻



5ms/div
TP29



10ms/div
TP29 ⏻



5µs/div
TP30



10ms/div
TP30 ⏻



20µs/div
TP31



10ms/div
TP36



50µs/div
TP37



50µs/div
TP38



TP41



10µs/div
①



10µs/div
②



10ms/div
② ⏻



10µs/div
③



10ms/div
③ ⏻



10µs/div
④



10ms/div
④



10µs/div
⑤



10µs/div
⑥



10ms/div
⑥ ⏻



10µsdiv
⑦



10µsdiv
⑧



10µsdiv
⑨



10µsdiv
⑩



10µsdiv
⑪

PRS.06911
T-26/105


A
1
2
3
4
5
6547
6503
3502
3535
6503
7502
2502
2547
9694
3503
3501
3520
6502
3540
3504
3515
3509
3511
3508
3510
7500
2500
3923
3529
3517
3519
9626
A506
7503
3450
2509
3507
M47
2506
2508
3262
3261
2506
7504
2251
2250
7505
3254
3257
2266
3858
0049
3854
3859
3853
3852
3857
2264
2265
3866
3851
9744
3256
3255
3265
3860
3888
M45
2262
2263
3881
3880
3868
3882
3869
3862
3871
2001
3001
3004
3005
3006
A
L

Monocarrier / Hauptplatine / Châssis


B
C
D
E
M13
M15
M16
M17
M18
M21
M22
M24
M27
M28
M29
M50
M51
7240
7310
7312
7470
7545
7546
7533
7625
7600
5625
5541
5551
5549
5539



32	5G	2371	4G	3237	5G	35
33	4A	2372	4G	3238	5G	35
34	4A	2373	4G	3239	5G	35
37	1G	2374	4G	3240	5G	35
38	5G	2375	5G	3241	5G	35
M10	1G	2376	5G	3242	5G	35
M11	1A	2380	4A	3243	5G	35
M12	4A	2381	4G	3244	5G	35
M13	2G	2384	4A	3245	5G	35
M14	4G	2385	4G	3246	5A	35
M15	1G	2451	4G	3247	5A	35
M16	3G	2456	4G	3248	5A	35
M17	3G	2457	4G	3249	5A	35
M18	3G	2458	3G	3250	3G	35
M19	5G	2459	3G	3251	3G	35
M20	4A	2460	3G	3253	3G	35
M21	4G	2461	4G	3254	3G	35
M22	3G	2464	4G	3255	4G	35
M23	5G	2465	3G	3256	4G	35
M24	5G	2466	4G	3257	3G	35
M26	4A	2467	4G	3258	3G	35
M27	3G	2468	4G	3259	4G	35
M28	1G	2469	4G	3260	4G	35
M29	3G	2470	4G	3261	3G	35
M30	5A	2471	4G	3262	3G	35
M35	4G	2473	4G	3263	4G	35
M39	5A	2475	4G	3264	4G	35
M40	3A	2500	2G	3265	4G	35
M47	2G	2502	1G	3266	4G	35
M50	4G	2505	2G	3300	5G	35
M51	4G	2506	2G	3301	4G	35
0049	3G	2507	3G	3302	4G	35
1000	5G	2509	2G	3303	4G	35
1003	4A	2520	1G	3304	4G	35
1240	5G	2521	1G	3305	4G	35
1242	5G	2522	1G	3306	4G	35
1300	5G	2524	2G	3307	4A	35
1534	2G	2526	1G	3308	5G	35
1559	2G	2528	1G	3309	5G	35
1580	3G	2531	1G	3310	5G	35
1600	1A	2532	1G	3311	5G	35
1702	2A	2533	2G	3312	5G	36
2001	5G	2538	3G	3313	4G	36
2002	5G	2539	3G	3314	5G	36
2003	5G	2545	1G	3315	5G	36
2008	5G	2546	1G	3316	5A	36
2230	5G	2547	1G	3317	4G	36
2231	5G	2549	1G	3318	4G	36
2232	5G	2550	1G	3319	4G	36
2233	5A	2551	2G	3320	5G	36
2234	5A	2559	2G	3321	5G	36
2235	5G	2560	2G	3322	5G	36
2236	5G	2563	2G	3323	4G	36
2237	5G	2570	2G	3324	4G	36
2238	5G	2574	3G	3325	5A	36
2239	5G	2580	3G	3326	4A	36
2240	5G	2585	2G	3327	4A	36
2241	5G	2588	1G	3328	4A	36
2242	5G	2590	3G	3329	4A	36
2243	5G	2600	1G	3330	5A	36
2245	5G	2603	1G	3331	5A	36
2246	5G	2605	1G	3332	5A	36
2248	5G	2607	1G	3334	4A	36
2249	5G	2611	1G	3335	4A	36
2250	3G	2617	1G	3336	5G	36
2251	3G	2620	1G	3337	5G	36
2252	3G	2625	1G	3338	4G	36
2254	3G	2626	1G	3339	3G	36
2255	3G	2629	2G	3340	3G	36
2256	3G	2630	2G	3342	4A	36
2257	3G	2631	2G	3343	4A	36
2262	4G	2632	2G	3344	5G	36
2263	4G	2636	3G	3347	4G	36
2264	4G	2640	3G	3348	4G	36
2265	4G	2641	3G	3349	4G	36
2300	4G	2646	2G	3350	4G	36
2301	4G	2649	3G	3351	4G	36
2302	4A	2650	3G	3352	4G	36
2303	5G	2652	3G	3353	4G	36
2304	5G	2653	3G	3354	4G	36
2305	4G	2658	2G	3355	5G	36
2306	5G	2660	2G	3356	4A	36
2307	5G	2661	2G	3357	4G	36
2308	5G	2662	3G	3358	5A	37
2309	5G	2663	3G	3359	5A	37
2310	5G	2664	3G	3360	4A	37
2311	5G	2670	2G	3361	4A	37
2312	5G	2671	2G	3362	4G	37
2313	4G	2675	2G	3365	3G	37
2314	4G	2676	2G	3366	3G	37
2315	4A	2701	3A	3367	4G	37
2316	5G	2702	3A	3368	4G	37
2317	5G	2703	3A	3369	4G	37
2318	5G	2704	2A	3370	4G	37
2319	5G	2705	2A	3371	4G	37
2320	4A	2706	2G	3372	5G	37
2321	5G	2707	4A	3373	5G	37
2322	5G	2708	3A	3374	4A	37
2323	4G	2709	2G	3375	5G	37
2325	4G	2710	2G	3376	5G	37
2326	5G	2711	2A	3380	4G	37
2327	5A	2712	2A	3381	4G	37
2328	5A	2713	5A	3394	3G	37
2329	5A	2714	2A	3395	4G	37
2330	4A	2715	2A	3450	2G	37
2331	5A	2716	2A	3451	4G	37
2332	4A	2717	4G	3452	4G	37
2333	4A	2718	2G	3455	3G	37
2334	5A	2719	2A	3456	4G	37
2335	4A	2721	2G	3457	3G	37
2336	4G	2781	4G	3458	4G	37
2337	4G	2800	5G	3459	3G	37
2338	4G	2805	4G	3460	3G	37
2339	4G	2810	3G	3461	4G	37
2340	4G	2875	4G	3462	4G	37
2341	5G	3001	5G	3463	3G	37
2342	4G	3002	5G	3464	3G	37
2343	4G	3003	5G	3465	3G	37
2344	4G	3004	5G	3466	4G	37
2345	5A	3005	5G	3467	3G	37
2346	5A	3006	5G	3468	4G	37
2349	5G	3007	5G	3469	4G	37
2350	4A	3008	5G	3470	4G	37
2351	5A	3009	5G	3471	4G	37
2352	5A	3010	5G	3473	4G	37
2353	5G	3218	5G	3474	3G	37
2354	4G	3219	5G	3483	3G	37
2355	5G	3220	5G	3485	3G	37
2356	4G	3221	5G	3501	1G	37
2357	4G	3222	5G	3502	1G	37
2358	4G	3224	5G	3503	1G	37
2359	5A	3225	5G	3504	2G	37
2360	4G	3226	5G	3505	3G	37
2361	4G	3227	5G	3506	3G	37
2362	4G	3228	5G	3507	2G	37
2363	4G	3229	5G	3508	2G	37
2364	5G	3230	5G	3509	2G	37
2365	4G	3231	5G	3510	2G	37
2366	4G	3232	5G	3511	2G	37
2367	4G	3233	5G	3512	2G	37
2368	4A	3234	5G	3513	3G	37
2369	4A	3235	5G	3514	3G	37
2370	5G	3236	5G	3515	2G	37



32	5G
33	4A
34	4A
37	1G
38	5G
M10	1G
M11	1A
M12	4A
M13	2G
M14	4G
M15	1G
M16	3G
M17	3G
M18	3G
M19	5G
M20	4A
M21	4G
M22	3G
M23	5G
M24	5G
M26	4A
M27	3G
M28	1G
M29	3G
M30	5A
M35	4G
M39	5A
M40	3A
M47	2G
M50	4G
M51	4G
0049	3G
1000	5G
1003	4A
1240	5G
1242	5G
1300	5G
1534	2G
1559	2G
1580	3G
1600	1A
1702	2A
2001	5G
2002	5G
2003	5G
2008	5G
2230	5G
2231	5G
2232	5G
2233	5A
2234	5A
2235	5G
2236	5G
2237	5G
2238	5G
2239	5G
2240	5G
2241	5G
2242	5G
2243	5G
2245	5G
2246	5G
2248	5G
2249	5G
2250	3G
2251	3G
2252	3G
2254	3G
2255	3G
2256	3G
2257	3G
2262	4G
2263	4G
2264	4G
2265	4G
2300	4G
2301	4G
2302	4A
2303	5G
2304	5G
2305	4G
2306	5G
2307	5G
2308	5G
2309	5G
2310	5G
2311	5G
2312	5G
2313	4G
2314	4G
2315	4A
2316	5G
2317	5G
2318	5G
2319	5G
2320	4A
2321	5G
2322	5G
2323	4G
2325	4G
2326	5G
2327	5A
2328	5A
2329	5A
2330	4A
2331	5A
2332	4A
2333	4A
2334	5A
2335	4A
2336	4G
2337	4G
2338	4G
2339	4G
2340	4G
2341	5G
2342	4G
2343	4G
2344	4G
2345	5A
2346	5A
2349	5G
2350	4A
2351	5A
2352	5A
2353	5G
2354	4G
2355	5G
2356	4G
2357	4G
2358	4G
2359	5A
2360	4G
2361	4G
2362	4G
2363	4G
2364	5G
2365	4G
2366	4G
2367	4G
2368	4A
2369	4A
2370	5G
2371	4G
2372	4G
2373	4G
2374	4G
2375	5G
2376	5G
2380	4A
2381	4G
2384	4A
2385	4G
2451	4G
2456	4G
2457	4G
2458	3G
2459	3G
2460	3G
2461	4G
2464	4G
2465	3G
2466	4G
2467	4G
2468	4G
2469	4G
2470	4G
2471	4G
2473	4G
2475	4G
2500	2G
2502	1G
2505	2G
2506	2G
2507	3G
2509	2G
2520	1G
2521	1G
2522	1G
2524	2G
2526	1G
2528	1G
2531	1G
2532	1G
2533	2G
2538	3G
2539	3G
2545	1G
2546	1G
2547	1G
2549	1G
2550	1G
2551	2G
2559	2G
2560	2G
2563	2G
2570	2G
2574	3G
2580	3G
2585	2G
2588	1G
2590	3G
2600	1G
2603	1G
2605	1G
2607	1G
2611	1G
2617	1G
2620	1G
2625	1G
2626	1G
2629	2G
2630	2G
2631	2G
2632	2G
2636	3G
2640	3G
2641	3G
2646	2G
2649	3G
2650	3G
2652	3G
2653	3G
2658	2G
2660	2G
2661	2G
2662	3G
2663	3G
2664	3G
2670	2G
2671	2G
2675	2G
2676	2G
2701	3A
2702	3A
2703	3A
2704	2A
2705	2A
2706	2G
2707	4A
2708	3A
2709	2G
2710	2G
2711	2A
2712	2A
2713	5A
2714	2A
2715	2A
2716	2A
2717	4G
2718	2G
2719	2A
2721	2G
2781	4G
2800	5G
2805	4G
2810	3G
2875	4G
3001	5G
3002	5G
3003	5G
3004	5G
3005	5G
3006	5G
3007	5G
3008	5G
3009	5G
3010	5G
3218	5G
3219	5G
3220	5G
3221	5G
3222	5G
3224	5G
3225	5G
3226	5G
3227	5G
3228	5G
3229	5G
3230	5G
3231	5G
3232	5G
3233	5G
3234	5G
3235	5G
3236	5G
3237	5G
3238	5G
3239	5G
3240	5G
3241	5G
3242	5G
3243	5G
3244	5G
3245	5G
3246	5A
3247	5A
3248	5A
3249	5A
3250	3G
3251	3G
3253	3G
3254	3G
3255	4G
3256	4G
3257	3G
3258	3G
3259	4G
3260	4G
3261	3G
3262	3G
3263	4G
3264	4G
3265	4G
3266	4G
3300	5G
3301	4G
3302	4G
3303	4G
3304	4G
3305	4G
3306	4G
3307	4A
3308	5G
3309	5G
3310	5G
3311	5G
3312	5G
3313	4G
3314	5G
3315	5G
3316	5A
3317	4G
3318	4G
3319	4G
3320	5G
3321	5G
3322	5G
3323	4G
3324	4G
3325	5A
3326	4A
3327	4A
3328	4A
3329	4A
3330	5A
3331	5A
3332	5A
3334	4A
3335	4A
3336	5G
3337	5G
3338	4G
3339	3G
3340	3G
3342	4A
3343	4A
3344	5G
3347	4G
3348	4G
3349	4G
3350	4G
3351	4G
3352	4G
3353	4G
3354	4G
3355	5G
3356	4A
3357	4G
3358	5A
3359	5A
3360	4A
3361	4A
3362	4G
3365	3G
3366	3G
3367	4G
3368	4G
3369	4G
3370	4G
3371	4G
3372	5G
3373	5G
3374	4A
3375	5G
3376	5G
3380	4G
3381	4G
3394	3G
3395	4G
3450	2G
3451	4G
3452	4G
3455	3G
3456	4G
3457	3G
3458	4G
3459	3G
3460	3G
3461	4G
3462	4G
3463	3G
3464	3G
3465	3G
3466	4G
3467	3G
3468	4G
3469	4G
3470	4G
3471	4G
3473	4G
3474	3G
3483	3G
3485	3G
3501	1G
3502	1G
3503	1G
3504	2G
3505	3G
3506	3G
3507	2G
3508	2G
3509	2G
3510	2G
3511	2G
3512	2G
3513	3G
3514	3G
3515	2G
3516	3G
3517	2G
3518	2G
3519	2G
3520	1G
3521	2G
3522	1G
3523	2G
3524	1G
3525	2G
3526	1G
3527	1G
3528	1G
3529	2G
3530	1G
3531	1G
3532	1G
3533	1G
3534	1G
3535	1G
3536	1G
3538	2G
3539	1G
3540	1G
3542	2G
3543	3G
3545	2G
3546	3G
3550	1G
3551	2G
3552	2G
3553	2G
3560	2G
3570	2G
3582	3G
3585	2G
3588	1G
3589	1G
3590	3G
3591	3G
3592	3G
3603	1A
3604	1G
3605	1G
3606	1G
3610	1G
3617	1G
3619	1G
3620	1G
3622	1G
3624	1G
3625	1G
3626	1G
3627	1G
3628	1G
3629	2G
3631	2G
3634	3G
3635	3G
3636	3G
3637	3G
3647	3G
3648	3G
3649	3G
3658	2G
3659	2G
3660	2G
3661	2G
3662	2G
3663	3G
3664	3G
3665	3G
3666	3G
3667	2G
3668	3G
3669	3G
3670	2G
3671	2G
3672	3G
3673	3G
3674	3G
3675	2G
3676	2G
3701	3G
3702	3G
3703	2A
3704	2A
3705	2A
3706	2A
3707	3A
3708	3A
3710	2A
3711	3A
3712	3A
3713	3A
3714	3A
3716	3A
3717	3A
3718	3A
3719	3A
3720	3A
3721	3G
3722	3G
3723	3G
3724	3G
3725	3G
3726	3G
3727	3A
3728	3A
3729	4A
3730	4A
3731	3A
3732	3G
3733	3G
3734	2G
3735	3A
3736	3G
3737	2G
3741	2G
3742	2G
3743	2G
3747	2A
3748	2A
3749	2A
3750	3G
3751	2A
3752	2A
3753	2A
3754	3G
3755	2A
3756	2A
3757	2G
3758	2G
3759	3A
3769	2G
3770	2A
3771	2G
3772	2G
3775	3A
3776	3A
3777	3A
3778	2A
3779	2A
3780	2A
3781	4G
3850	4G
3851	4G
3852	4G
3853	3G
3854	3G
3855	4G
3856	4G
3857	4G
3858	3G
3859	3G
3860	4G
3861	5G
3866	5G
3867	5G
3868	4G
3869	5G
3871	5G
3874	4G
3875	4G
3880	4G
3881	4G
3882	4G
3883	3G
3884	3G
3885	3G
3886	2A
3887	2G
3888	4G
3890	3G
4221	4G
4222	5G
4223	5G
4224	5A
4233	5G
4237	5G
4239	5A
4300	4G
4301	4G
4302	4G
4303	5G
4304	5G
4305	4G
4306	3G
4307	4G
4308	4G
4310	4G
4312	4G
4314	4G
4315	4A
4316	3G
4317	4A
4318	4A
4319	4G
4320	5A
4321	5A
4322	5A
4323	5G
4324	4G
4325	4G
4326	5G
4328	4A
4329	5G
4450	3G
4451	3G
4452	3G
4500	2G
4501	2G
4503	1G
4504	3G
4505	1G
4506	2G
4507	2G
4602	3G
4603	2G
4604	2G
4605	2G
4700	2A
4701	2A
4704	3G
4706	3A
4707	3A
4708	2A
4709	2A
4710	3G
4711	3G
4712	3G
4713	3G
4714	3A
4715	3A
4716	3G
4717	4A
4718	3G
4720	3A
4721	2A
4723	3A
4850	5G
4851	4G
4852	4G
4853	3G
4854	3G
4855	3G
4856	4G
4857	4G
4858	4G
4859	4G
4860	4G
4862	4G
4863	4G
4865	4G
4866	4G
4867	4G
5001	5G
5240	5G
5242	4G
5301	5G
5302	4A
5303	4A
5304	5G
5306	5A
5530	1G
5534	1G
5541	1G
5541	2G
5549	1G
5554	2G
5582	3G
5588	1G
5605	1G
5606	1G
5619	1G
5625	1G
5625	2G
5630	2G
5631	2G
5632	3G
5661	2G
5701	2G
5703	2G
5801	4G
6245	5G
6246	5G
6247	5G
6248	5G
6249	5G
6300	5G
6302	4A
6303	4A
6309	4A
6310	5A
6315	4G
6316	4G
6317	3G
6318	5G
6367	4G
6464	3G
6465	3G
6502	1G
6503	1G
6504	1G
6518	2G
6519	2G
6546	1G
6547	1G
6548	2G
6549	2G
6551	1G
6560	2G
6561	2G
6563	2G
6570	2G
6571	2G
6580	3G
6585	2G
6590	3G
6591	3G
6592	3G
6610	1G
6611	1G
6612	2G
6617	1G
6621	1G
6622	1G
6630	2G
6640	3G
6641	2G
6646	2G
6648	3G
6649	2G
6660	3G
6661	2G
6662	2G
6663	3G
6664	3G
6665	2G
6666	3G
6669	2G
6670	3G
6675	2G
6705	2G
6707	4A
6708	2G
6709	2G
7000	5G
7001	5G
7002	5G
7003	5G
7240	5G
7243	5G
7244	5G
7245	5G
7246	5G
7247	5G
7248	5G
7249	5G
7301	4G
7302	4G
7303	4A
7305	5G
7306	5G
7307	5A
7308	4A
7309	4G
7310	4A
7311	5G
7312	4G
7370	4G
7371	3G
7372	3G
7373	5A
7374	4G
7455	4G
7470	4G
7500	2G
7502	1G
7503	2G
7504	3G
7505	3G
7530	1G
7533	1G
7534	1G
7540	3G
7545	1G
7546	1G
7591	3G
7600	3G
7614	2G
7625	1G
7661	2G
7663	2G
7671	3G
7672	3G
7701	2A
7702	3A
7703	3G
7704	3G
7705	3G
7706	2G
7707	2G
7708	2A
7709	3A
7710	2A
7711	3A
7712	3G
7805	3G
7810	3G
9248	5G
9249	5G
9300	5G
9502	1G
9505	4G
9520	1G
9530	1G
9534	2G
9549	1G
9550	2G
9551	3G
9600	4G
9605	3G
9607	1G
9608	4G
9610	4G
9611	2A
9612	4G
9613	3G
9614	4G
9615	3G
9616	3G
9617	3G
9618	2G
9619	4G
9620	3G
9622	4G
9623	3G
9624	3G
9626	2G
9627	3G
9628	4A
9629	3G
9630	3G
9631	4G
9632	3G
9634	3G
9635	3G
9636	3G
9637	4G
9638	3G
9639	3G
9640	3G
9641	4G
9642	4G
9643	4G
9644	4G
9645	3G
9646	5G
9647	5G
9648	4G
9649	3G
9650	2G
9651	3G
9652	2G
9653	4G
9654	4G
9655	4G
9656	5G
9657	4G
9658	3G
9659	4G
9660	2G
9662	4G
9663	4G
9664	3G
9665	2G
9666	3G
9668	2G
9669	3G
9670	3G
9671	3G
9672	4G
9673	5G
9674	4G
9675	4G
9676	5G
9677	5G
9678	4G
9679	3G
9681	3G
9684	3G
9685	3G
9686	4G
9687	4G
9688	5G
9690	5G
9691	3G
9692	2G
9693	2G
9694	1G
9695	2G
9696	2G
9697	3G
9699	3G
9700	4G
9701	2A
9702	3A
9703	2A
9704	4G
9705	3A
9707	3A
9708	2A
9709	2A
9710	4G
9711	4G
9712	4G
9713	3G
9714	3G
9715	3G
9717	3G
9718	4G
9719	5G
9720	3G
9721	3G
9723	2G
9724	3G
9725	3G
9727	1G
9728	1G
9729	1G
9730	3G
9732	3G
9733	3G
9734	3G
9735	1G
9736	2G
9737	2G
9738	3G
9739	3G
9740	1G
9741	2G
9742	2G
9743	3G
9744	4G
9745	4G
9746	5G
9747	5G
9748	5G
9749	4G
9750	4G
9751	4G
9752	4G
9753	4G
9755	4G
9756	4G
9757	5G
9758	4G
9759	4G
9760	5G
9764	4G
9765	3G
9766	4G
9768	3G
9769	4G
9770	4G
9772	2G
9773	3G
9774	3A
9775	2G
9777	4G
9778	5G
9779	4G
9780	4G
9781	5G
9783	5G
9784	5G
9785	5G
9786	4G
9787	4G
9788	4G
9789	4G
9790	1G
9791	3G
9792	3G
9793	2G
9796	3G
9797	4G
9798	3A
9799	3A
9801	3A
9803	2A
9806	4G
9843	4G
9854	4G
9869	5G
9876	5G
9877	4G

Picture tube module 21" / Bildröhren Modul 21" / Module support tube imag


CRT MODULE 21"
BCI
f
⊥f
+200
PEAK
BEAM LIMIT
G/V
B
⊥
R
CUT OFF
+14
Vg2
C19
C20
C21
C22
G1
G2
G/V
A
B
C
D
1
2
3
4

C19	A1
C20	B4
C21	C2
C22	C1
2301	A4
2331	B4
2361	C4
2391	D2
2392	D2
2411	D4
2412	D4
2421	D4
2431	D2
2432	D3
2433	D1
2434	A1
3301	B4
3302	A4
3303	A4
3304	A4
3310	A3
3311	A3
3312	A3
3313	A2
3314	B1
3315	A3
3316	A3
3331	B4
3332	B4
3333	B4
3334	B3
3340	B3
3341	B3
3342	B3
3343	B2
3344	B2
3345	D3
3361	C4
3362	C4
3363	C4
3364	C4
3370	C3
3371	C3
3372	C3
3373	D3
3374	D1
3375	C3
3376	C3
3377	C3
3391	D2
3392	D2
3393	D2
3394	D2
3395	D3
3396	B3
3397	B3
3398	B3
3411	D3
3412	D4
3413	D4
3414	D4
3415	D4
3421	D4
3422	D4
3423	D3
3431	A2
3432	B4
3433	B2
3434	B1
3435	D1
3436	D1
4000	C4
4002	D4
4005	D3
4006	C4
4009	B3
4010	B3
4011	B4
4012	D2
4014	D3
5401	B1
6301	B2
6331	C2
6345	D3
6361	D3
6421	D4
7301	B4
7303	A4
7304	B3
7305	B3
7332	C3
7333	C4
7334	C3
7335	B2
7345	D3
7362	D3
7363	C4
7364	D3
7365	D3
7391	D2
7411	D3
7421	D4
9000	B2
9001	C4
9002	D4
9003	A2
9004	C3
9006	C3
9007	A2
9008	C3


CRT MODULE 21"
Vg2
C22
TP51
TP52
G/V
G2
G1
C19
BCI
f
⊥f
+200
D
C
B
A
1

Picture tube module 25"/28" / Bildröhren Modul 25"/28" / Module support tu


CRT MODULE 25"/28"
AQUADAG
PEAK
WHITE LIMIT
G/V
B
⊥
R
CUT OFF
+14
BCI
f
⊥f
+200
C19
C20
C21
G1
G/V
G2
A
B
C
1
2
3
4
5

C19	C1
C20	B5
C21	B2
2301	B4
2331	C5
2361	A5
2391	C3
2392	C3
2411	C4
2412	C5
2421	C5
2431	C2
2432	C3
2433	A2
2434	A2
3301	B4
3302	B4
3303	A4
3304	B4
3308	B4
3309	B4
3310	A4
3311	A4
3312	B3
3313	A3
3314	C2
3315	B3
3316	B4
3331	B5
3332	C5
3333	B5
3334	C4
3338	C4
3339	C4
3340	C3
3341	C4
3342	C4
3343	C4
3344	C3
3345	C3
3361	A5
3362	A5
3363	A5
3364	A5
3368	A4
3369	A4
3370	A3
3371	A3
3372	A4
3373	A3
3374	A1
3375	A3
3376	A4
3377	A4
3391	C3
3392	C3
3393	C2
3394	C3
3395	C3
3396	B4
3397	B3
3398	B4
3411	C4
3413	C5
3414	C5
3415	C5
3421	C5
3422	C5
3423	C3
3431	C1
3432	A5
3433	C1
3434	A2
3435	B1
3436	A1
4000	B5
4002	C5
4003	C3
4005	C3
4007	B3
4008	A3
4008	C4
4011	A4
5401	C2
6301	B3
6331	C3
6345	C3
6361	A3
6411	C4
6421	C5
7301	B4
7302	B4
7303	B4
7304	B3
7305	B3
7331	C4
7332	C4
7333	C5
7334	C4
7335	C3
7345	C3
7361	A4
7362	A5
7363	A4
7364	A4
7365	A3
7391	C2
7411	C5
7421	C5
8000	A2
9000	A4
9001	C5
9002	C5
9003	A3
9004	C4
9006	B3
9007	B3
9008	A3
9009	A1


CRT MODULE 25"
+200
⊥f
f
BCI
C19
TP51
TP52
G/V
G2
C
B
A
1

dule 21” / Bildröhren Modul 21” / Module support tube image 21”


2
3
4
A
B
C
D
3481
3313
9003
3310
3311
3312
3304
9000
3343
3340
3341
3342
3334
3344
7335
9008
7334
7332
3371
9005
9004
3364
3372
3370
9001
C21
B
7365
7363
7362
7391
2391
3373
7411
9002
3393
3394
2432
2411
3415
3413
2431
2392
3432
PEAK
BEAM LIMIT
G/V
B
R
CUT OFF
C20

C19	A1
C20	B4
C21	C2
C22	C1
2301	A4
2331	B4
2361	C4
2391	D2
2392	D2
2411	D4
2412	D4
2421	D4
2431	D2
2432	D3
2433	D1
2434	A1
3301	B4
3302	A4
3303	A4
3304	A4
3310	A3
3311	A3
3312	A3
3313	A2
3314	B1
3315	A3
3316	A3
3331	B4
3332	B4
3333	B4
3334	B3
3340	B3
3341	B3
3342	B3
3343	B2
3344	B2
3345	D3
3361	C4
3362	C4
3363	C4
3364	C4
3370	C3
3371	C3
3372	C3
3373	D3
3374	D1
3375	C3
3376	C3
3377	C3
3391	D2
3392	D2
3393	D2
3394	D2
3395	D3
3396	B3
3397	B3
3398	B3
3411	D3
3412	D4
3413	D4
3414	D4
3415	D4
3421	D4
3422	D4
3423	D3
3431	A2
3432	B4
3433	B2
3434	B1
3435	D1
3436	D1
4000	C4
4002	D4
4005	D3
4006	C4
4009	B3
4010	B3
4011	B4
4012	D2
4014	D3
5401	B1
6301	B2
6331	C2
6345	D3
6361	D3
6421	D4
7301	B4
7303	A4
7304	B3
7305	B3
7332	C3
7333	C4
7334	C3
7335	B2
7345	D3
7362	D3
7363	C4
7364	D3
7365	D3
7391	D2
7411	D3
7421	D4
9000	B2
9001	C4
9002	D4
9003	A2
9004	C3
9006	C3
9007	A2
9008	C3


CRT MODULE 21”
1
2
3
D
C
B
A
2433
2431
2392
3393
3374
3436
3435
Vg2
C22
G/V
TP52
G2
C21
TP51
TP53
G1
3344
3314
3434
5401
3433
9007
2434
C19
BCI
+200
3431
9000
9006
9008
3391
3392
3372
3377
3342
3343
3340
6301
3313
9003
3310
3312

dule 25”/28” / Bildröhren Modul 25”/28” / Module support tube image 25”/28”


2
3
4
5
A
B
C
3371
2433
AG
2434
3313
9003
3372
3370
9006
7365
7364
7361
7362
3364
3432
3313
3311
3310
3304
3312
7305
7304
7302
PEAK
WHITE LIMIT
G/V
B
R
CUT OFF
C20
9007
9006
3340
3341
3342
9004
3334
9001
9002
3344
7335
7334
7331
7332
7411
7391
2391
3343
3393
3394
2432
2411
3415
3414
2431
2392

C19	C1
C20	B5
C21	B2
2301	B4
2331	C5
2361	A5
2391	C3
2392	C3
2411	C4
2412	C5
2421	C5
2431	C2
2432	C3
2433	A2
2434	A2
3301	B4
3302	B4
3303	A4
3304	B4
3308	B4
3309	B4
3310	A4
3311	A4
3312	B3
3313	A3
3314	C2
3315	B3
3316	B4
3331	B5
3332	C5
3333	B5
3334	C4
3338	C4
3339	C4
3340	C3
3341	C4
3342	C4
3343	C4
3344	C3
3345	C3
3361	A5
3362	A5
3363	A5
3364	A5
3368	A4
3369	A4
3370	A3
3371	A3
3372	A4
3373	A3
3374	A1
3375	A3
3376	A4
3377	A4
3391	C3
3392	C3
3393	C2
3394	C3
3395	C3
3396	B4
3397	B3
3398	B4
3411	C4
3413	C5
3414	C5
3415	C5
3421	C5
3422	C5
3423	C3
3431	C1
3432	A5
3433	C1
3434	A2
3435	B1
3436	A1
4000	B5
4002	C5
4003	C3
4005	C3
4007	B3
4008	A3
4008	C4
4011	A4
5401	C2
6301	B3
6331	C3
6345	C3
6361	A3
6411	C4
6421	C5
7301	B4
7302	B4
7303	B4
7304	B3
7305	B3
7331	C4
7332	C4
7333	C5
7334	C4
7335	C3
7345	C3
7361	A4
7362	A5
7363	A4
7364	A4
7365	A3
7391	C2
7411	C5
7421	C5
8000	A2
9000	A4
9001	C5
9002	C5
9003	A3
9004	C4
9006	B3
9007	B3
9008	A3
9009	A1


CRT MODULE 25”/28”
1
2
3
C
B
A
+200
BCI
C19
3431
2431
2392
3433
3393
7391
5401
3392
3314
3344
TP51
TP53
G2
G/V
TP52
C21
3435
9007
9006
6301
9009
3374
3434
8000
AQUADAG
6361
9008
3436
3373
9003
2435
3313
3312
3370
3371

Picture tube module /


3
4
D
C
B
A
+14
CUT OFF
R
B
G/V
PEAK
BEAM LIMIT
8211 015 0300 4

PCB.03181
T28/107

5"/28"


4
5
C
B
A
+14
CUT OFF
R
B
G/V
PEAK
WHITE LIMIT
8211 015 0296 5

PCB.03177
T28/106


F
DIAGRAM F
SCHEMA F
1005
PICTURE TUBE MODULE/MODULE SUPPORT TUBE IMAGE/BILDRÖHREN
+14A
7M14
1C20
13V8
3432
39
7345
BC858
2432
47u
6345
LLZC10
3345
680
11V9
+12A
+12B
3411
1k8
3) 1K5
3413
220
3415
220
7V7
7411
BC548
2V4
+2
3V
2411
330u
6411
1) 2)
BZV79C3V0
3412
470
3)
3414
62
3) 47
2412
100n
3311
15k
+200
4M13
1C19
1) 213V
2) 203V
3) 206V
3431
180
+190
2431
100n
120k
R
5M14
C100
3C20
2V9
2371
27p
3301
130
3302
1k5
2) 3k6
3) 1k6
2301
1) 2) 68p
3) 22P
2V9
2k7
+190
3393
82k
1) 100k
3394
30k
1) 127k
2392
4u7
44V
7391
BF423
3392
100k
3391
100k
42V
2391
27p
3396 1)
120k
141V
C101
1M14
7C20
0V
4000
3395
68k
1V6
120k
B
2M14
C102
6C20
2V9
2373
27p
3331
130
3332
1k5
2) 3k6
3) 1k6
2331
1) 2) 56P
3) 22P
2V9
2k7
+12A
3422
6k8
+12B
3423
470k
7421
BC858B
C103
CUT OFF
6M14
2C20
8V3
10V3
2421
47p
3421
82k
3375
RES
140V
4M14
4C20
120k
G/V
3M14
C104
5C20
3V1
2372
27p
3361
130
3362
1k5
2) 3k6
3) 1k6
2361
1) 2) 68P
3) 22P
3V
2k7
C+D
A
B
C
D
E
F
G
H
I
J
K
L
M
N
O
1
2
3
4
5
6
7
8

Bildröhren Modul / Module support tube image


F
RÖHREN MODUL/MODULO CRT/MODULO TUBO DE IMAGEN
8 9 10 11 12 13 14 15 16 17 18
A B C D E F G H I J K L M N O
+190
+190
3311 15k 1) 12k
3315 120k 1)
3316 120k 1)
3307 4k7 3)
3306 4k7 3)
3305 4k7 3)
270 3312
1) 98V
2) 89V
3) 98V
1) 209V
2) 200V
3) 209V
98V2
+12B
3310 330
7304 BF422
7301 BF422
7302 BF422
3304 120k
3309 47 1)
3308 1) 47 2) 1
11V5
7305 BF423
1) 10V6
2) 11V7
3) 10V8
1) 97V
2) 88V
3) 97V
2V9
7303 BC848
3303 2k7
+2
+190
4007 3314 1k5
3344 1k5
4008 3374 1k5
6301
6331
6361
BAV103 (3X)
8000
25"/28"
21"
1990
R
B
G/V
8 7
11 3
6 9
10 5
9 4
5 6
7 8
F
C21
D79
D78
2C19 7V2
D73
3C19
2M13
1) 15u
2) 82u
3) 33u
5401
3433 1
3434 1k5
+190
3435 1k5
2433 33n
3436 1M8
C22
D80
B.C.I.
4C19
D75
2434 330p
+190
+190
3396 1) 120k
3397 1) 120k
3341 1) 15k 2)
3398 RES
3337 4k7 3)
3336 4k7 3)
3335 4k7 3)
3342 270
3313 270
1) 141V
2) 96V
3) 137V
141V
+12B
3340 330
7334 BF422
7331 BF422
7332 BF422
7335 BF423
3334 120k
3338 47 1)
3339 1) 47 2) 1
11V5
1) 139V
2) 94V
3) 99V
1) 10V5
2) 11V7
3) 10V8
2V9
7333 BC848
3333 2k7
+2
4005
3343 270
6421 LL4148
4002
+12
+190
+190
3375 RES
3376 RES
3377 RES
3371 1) 10k 2) 15k
3367 4k7 3)
3366 4k7 3)
3365 4k7 3)
3372 270
3373 270
1) 209V
2) 200V
3) 203V
140V
+12B
3370 330
7364 BF422
7361 BF422
7362 BF422
7365 BF423
3364 120k
3368 47 1)
3369 1) 47 2) 1
11V5
1) 139V
2) 92V
3) 135V
1) 140V
2) 93V
3) 137V
1) 10V6
2) 11V7
3) 10V8
3V
7363 BC848
3363 2k7
4011
+2
65V 130V TP51 1
50V 130V TP51 2
70V 115V TP51 3
75V 120V TP52 1
56V 120V TP52 2
72V 115V TP52 3
80V 120V TP53 1
66V 120V TP53 2
76V 110V TP53 3

SEE SERVICE
MANUAL "REMARKS"
SIEHE ANMERKUNGEN
IN DER SERVICE
DOKUMENTATION
VEDERE NOTE SU
DOCUMENTATIONE
VER OBSERVACIONES
EN ET DOCUMENTACION

REMARKS/REMARQUES/ANMERKUNGEN/NOTE

PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEND IN GERÄTEN
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS:

1) 25"/28" BLACK LINE
2) 25"/28" NON BLACK LINE
3) 21"

PRS.06913
T-26/105

CHASSIS GR2.1

CL06532002/017.FREF
040291

1005	A 3
1990	D17
2301	E 6
2331	I 6
2361	O 6
2371	E 3
2372	N 3
2373	I 3
2391	H 6
2392	G 5
2411	C 5
2412	C 7
2421	K 6
2431	D 6
2432	B 6
2433	H14
2434	I13
3301	E 5
3302	E 6
3303	E 8
3304	D 8
3305	C 9
3306	B 9
3307	B 9
3308	D 9
3309	D 9
3310	C10
3311	B 8
3312	B11
3313	G11
3314	D13
3315	B 9
3316	B 9
3331	I 5
3332	I 6
3333	I 8
3334	H 8
3335	G 9
3336	G 9
3337	F 9
3338	H 9
3339	H 9
3340	G10
3341	G 9
3342	G10
3343	I11
3344	D13
3345	B 5
3361	N 5
3362	N 6
3363	N 8
3364	M 8
3365	L10
3366	L10
3367	K10
3368	N 9
3369	N 9
3370	M10
3371	L 9
3372	L10
3373	L11
3374	D13
3375	L 8
3376	L 8
3377	L 9
3391	G 7
3392	G 6
3393	G 5
3394	G 5
3395	H 5
3396	G 8
3397	G 8
3398	G 9
3411	B 6
3412	C 6
3413	B 7
3414	C 7
3415	B 7
3421	K 6
3422	J 5
3423	J 6
3431	D 4
3432	A 4
3433	F14
3434	F15
3435	H14
3436	H14
4000	H 5
4002	J11
4005	I11
4007	D13
4008	D13
4011	N10
5401	F14
6301	E12
6331	E12
6345	B 5
6361	E12
6411	C 6
6421	J10
7301	D10
7302	D 9
7303	E10
7304	C10
7305	D10
7331	H 9
7332	H10
7333	I10
7334	H10
7335	H10
7345	B 5
7361	M 9
7362	M10
7363	N10
7364	M10
7365	M10
7391	G 6
7411	B 7
7421	J 5

Teletext / Videotext / Teletexte

TXT–DECODER–DECODIFICATORE TELETESTO–DECODEUR TELETEXTE–DECODIFICADOR DE


J
SDA
SCL
+12
+8
CVBS
2M17 2T6
1M17 1T6
4M17 4T6
6M17 6T6
5M17 5T6
1M18 1T7
3M17 3T6
+5d
6820 LL4148
2801 10n
27.28
7800 PCF84C81/074
µC
I²C
RAM 128x8
ROM 8Kx8
C.P.U.
G ~ 6MHz
1802 6MHz
RES
3803 100
2805 120p
3802 100
2804 120p
3904
3900
5801 22µ
3826 15
2825 100µ
2793 47n
+12f 13V
3917 +12g
3918 +12h
3922
+8
2792 100n
3845 68
3846 68
7846 BD943
5800 47µ
2800 100µ
+5a 5.0V
+5d
3906 +5c
+5b
5814 10µ
2849 15µ
2812 100n
6847 BYD33G
3901
5847 3µ3
2846 220µ
3847 82
7849 BC858
5.8V
3798 120
0.8V
7802 BC848
3849 1k
3848 180
2845 100µ
6848 LLZ F5V1
+5a
3800 10k
7801 BC848
3914
0V
0.8V
1,4,12,13,14,20,21,22
1.5V
3921
2814 560p
3814 1k
VCS 0.5V
7830 SAA5231/V6
2815 100n
+12h
13V
1.7V
+12g
2823 470p
10V
3816 68k
SAND
2V
2827 47n
2829 47µ
2828 47n
3827 3k3
3828 1k2
2830 47n
4.5V
4.6V
6.1V
VCO
2824 68n
5.7V
G ⏍
φ
+12h
3815 1k5
11.5V
1)
+8
3836 47k
3833 1k
7831 BC558A
7832 BC548B
2834 100µ
3837 1k
3831 880
3830 82
2832 2µ2
4.9V
2798 12p
3838 47k
3832 1k
2836 120p
5834 27µH
3834 680
3829 150
2799 220p
3835 560
3919
2833 2µ2 2)
3920
2 2.3V
3 3V 2817 15p
4 5.9V 2818 1n
5 3.8V 2819 470p
6 3V 2820 22n
8 5.7V 2821 270p
A B C D E F G H I J K L M N O
1 2 3 4 5 6 7 8 9 10

DOR DE TELETEX


J
7810
KM6264AL-15
3797
10
2811
100n
+5a
26 28
RAM
RAM
8Kx8
D0 Q0
D7 Q7
D0 15
D1 16
D2 17
D3 18
D4 19
D5 13
D6 12
D7 11
OE 22
WE 27
CS 20
14
10 9 8 7 6 5 4 3 2 21 23 24 25
A0 A1 A2 A3 A4 A5 A6 A7 A8 A9 A10 A12 A11
3843 1k2
3841 1k2
3842 1k2
3839 1k2
3840 1k2
3823 1k2
3822 1k2
3821 1k2
3820 1k2
3819 1k2
3818 1k2
2803 RES
2802 RES
1802 6MHz
RES 3801
7820
SAA5243P/E/M2/N
D0 D1 D2 D3 D4 D5 D6 D7 A0 A1 A2 A3 A4 A5 A6 A7 A8 A9 A10 A12 A11
26 25 24 23 22 27 28 29 30 31 32 33 34 35 36 37 2 39 3 40 38
4.4V 2.7V
+5b
5 WE
4 OE
8 O/E
3817 1k2
+12f
3813 270
2V
3812 3k3
3824 3k3
3825 3k3
2810 100n
6813 LLZ-C7V5
1.5V SDA 20
1.5V SCL 19
I²C
0.5V VCS 10
12
2V SAND 11
6.1V F6 9
T1 → T2
4.4V TTC 7
TTD 6 1V
CPU
G ABCDE
13 R 0.3V
14 G 0.3V
15 B 0.3V
6812 LL4148
6811 LL4148
6810 LL4148
R 5T7 5M18 R
G 6T7 6M18 G
B 7T7 7M18 B
2796 18p
2795 18p
2794 18p
+5c
3807 5k6
6809 LL4148
3913 8T7 8M18
3908
3809 2k7
+5c
3808 10k
7812 BC846B
3795 3k9
3915 4T7 4M18 NIL
NIL
7811 BC848B
0.3V
16 PO 0.2V
3810 33k
3811 22k
0.3V
+5c
3805 1k2
+5c
7803 BC848B
2T7 2M18
17 4.9V F.BL.
3910
3796 120
3804 100
6814 LL4148
F.BL. 3T7 3M18 FBL
2797 18p
CCT
21
1.5V 15
16 1.5V
5 1.5V
6 1.5V
5803
29 7µ
2828 2830 47n
6V
6.1V 18 20
VCO
17 7.1V F6 ④
6.0MHz
+12f
2816 27p
5816 15µ
⑤
G ~ ÷ 2
11 1V
12 13V
2826 15p
⑥
9 2822 100p
TTC
1801 13.875 MHz
14 4.4V ⑦
15 4V 2813 10n TTD ①
13
① TTD 3.5V 0V
② VCS 5V 0.3V
③ SAND 5V 2.2V 0V 64µs
④ F6 6V 2.3V 6.0MHZ
⑤ CLOCK 1V 680mV 13.875MHz
⑥ CLOCK 800mV 6.9MHz
⑦ TTC 6V 2.2V 6.9 MHz
11 12 13 14 15 16 17 18 19 20 21
A B C D E F G H I J K L M N O

REMARKS/ REMARQUES/ ANMERKUNGEN/ NOTE

PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEEND IN GERAETEN:
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS:

1) SCAN
2) NON SCAN
3) NON ES

CHASSIS GR2.1

PRS 06854
T-08 104

1801	L1
1802	E1
2792	E3
2793	D4
2794	I 2
2795	I 2
2796	I 2
2797	L2
2798	M2
2799	M4
2800	F5
2801	A8
2802	E1
2803	E1
2804	C6
2805	B6
2810	G1
2811	A1
2812	G5
2813	M1
2814	J5
2815	J7
2816	J1
2817	N7
2818	N7
2819	N7
2820	N8
2821	N8
2822	L1
2823	J8
2824	K5
2825	D4
2826	L1
2827	J9
2828	J9
2829	J1
2830	J1
2832	M5
2833	O3
2834	M2
2836	M3
2845	G4
2846	G3
2849	G5
3795	J2
3796	K1
3797	A1
3798	G5
3800	F6
3801	E1
3802	C6
3803	B6
3804	L1
3805	K1
3807	I 1
3808	J1
3809	J1
3810	J1
3811	J1
3812	G1
3813	G2
3814	J6
3815	L5
3816	J8
3817	G1
3818	F1
3819	F1
3820	E1
3821	E1
3822	E1
3823	E1
3824	G1
3825	G1
3826	D5
3827	J9
3828	J1
3829	M4
3830	M4
3831	M4
3832	M3
3833	L3
3834	N4
3835	N3
3836	L3
3837	M2
3838	M3
3839	F1
3840	F1
3841	E1
3842	E1
3843	E1
3845	E4
3846	F4
3847	G4
3848	H4
3849	H5
3900	D3
3901	F3
3904	C3
3906	F5
3908	I 1
3910	K1
3913	I 2
3914	G6
3915	J2
3917	D5
3918	E5
3919	D4
3920	N6
3921	I 6
3922	E7
5800	E5
5801	D3
5803	I 1
5814	F5
5816	J1
5834	N3
5847	F4
6809	I 1
6810	H1
6811	H1
6812	H1
6813	G2
6814	L2
6820	A8
6847	F3
6848	H5
7800	B9
7801	F7
7802	G6
7803	K1
7810	A1
7811	J1
7812	J1
7820	F1
7830	K5
7831	L4
7832	L3
7846	F4
7849	G5

1801	L12
1802	E10
2792	E3
2793	D4
2794	I 20
2795	I 20
2796	I 20
2797	L20
2798	M2
2799	M4
2800	F5
2801	A8
2802	E11
2803	E11
2804	C6
2805	B6
2810	G19
2811	A16
2812	G5
2813	M12
2814	J5
2815	J7
2816	J12
2817	N7
2818	N7
2819	N7
2820	N8
2821	N8
2822	L11
2823	J8
2824	K5
2825	D4
2826	L12
2827	J9
2828	J9
2829	J10
2830	J10
2832	M5
2833	O3
2834	M2
2836	M3
2845	G4
2846	G3
2849	G5
3795	J20
3796	K19
3797	A15
3798	G5
3800	F6
3801	E11
3802	C6
3803	B6
3804	L19
3805	K18
3807	I 18
3808	J19
3809	J18
3810	J18
3811	J18
3812	G18
3813	G20
3814	J6
3815	L5
3816	J8
3817	G18
3818	F12
3819	F12
3820	E13
3821	E13
3822	E14
3823	E18
3824	G18
3825	G19
3826	D5
3827	J9
3828	J10
3829	M4
3830	M4
3831	M4
3832	M3
3833	L3
3834	N4
3835	N3
3836	L3
3837	M2
3838	M3
3839	F17
3840	F17
3841	E17
3842	E17
3843	E16
3845	E4
3846	F4
3847	G4
3848	H4
3849	H5
3900	D3
3901	F3
3904	C3
3906	F5
3908	I 17
3910	K18
3913	I 20
3914	G6
3915	J20
3917	D5
3918	E5
3919	O4
3920	N6
3921	I 6
3922	E7
5800	E5
5801	O3
5803	I 11
5814	F5
5816	J12
5834	N3
5847	F4
6809	I 18
6810	H19
6811	H19
6812	H19
6813	G20
6814	L20
6820	A8
6847	F3
6848	H5
7800	B9
7801	F7
7802	G6
7803	K19
7810	A17
7811	J19
7812	J19
7820	F13
7830	K5
7831	L4
7832	L3
7846	F4
7849	G5

1290 TXT FLOF MODULE


A
B
C
D
E
F
1
2
3
4
T6
T7
2846
5801
3826
6849
6847
3845
3846
5847
2825
2800
2845
2849
7846
3800
7800
8005
9804
9805
9803
1802
7810
3797
5814
7820
5816
9800
1801
5803
7830
9802
3814
9801
2829
3829
3830
2832
2833
2834
5834
7832
7831


A
B
C
D
E
F
1
2
3
4
7831
2834
7832
5834
2833
2832
5814
3797
3830
3829
2849
2845
2800
7846
3800
7849
7800
1802
7810
7811
7812
7820
9801
2829
3814
9802
7830
5803
5847
3845
3846
6847
2825
8005
6849
9804
9805
9803
7803
3826
5801
2846
T6
T7
5816
9800
1801

T6	A 4
T7	C 4
1801	F 3
1802	C 2
2792	E 1
2793	B 3
2794	C 3
2795	C 3
2796	C 4
2797	D 4
2798	E 1
2799	E 2
2800	B 3
2801	C 3
2802	C 2
2803	C 2
2804	B 3
2805	B 3
2810	E 4
2811	C 2
2812	D 1
2813	E 2
2814	E 2
2815	F 3
2816	F 4
2817	F 2
2818	F 2
2819	F 2
2820	F 3
2821	F 3
2822	F 3
2823	E 2
2824	E 2
2825	B 3
2826	F 3
2827	E 3
2828	E 3
2829	E 2
2830	E 3
2832	F 2
2833	F 1
2834	F 1
2836	E 2
2845	B 2
2846	C 4
2849	B 2
3795	D 3
3796	D 3
3797	C 2
3798	C 3
3800	C 2
3801	C 2
3802	B 3
3803	B 3
3804	D 3
3805	D 3
3807	D 2
3808	D 2
3809	D 2
3810	D 2
3811	D 2
3812	E 3
3813	E 4
3814	E 2
3815	F 2
3816	E 2
3817	D 2
3818	C 3
3819	C 3
3820	C 3
3821	C 2
3822	C 2
3823	C 2
3824	E 3
3825	E 3
3826	B 4
3827	E 3
3828	E 2
3829	E 2
3830	E 2
3831	E 2
3832	E 2
3833	E 1
3834	E 2
3835	E 2
3836	F 1
3837	E 1
3838	E 1
3839	C 2
3840	C 2
3841	C 2
3842	C 2
3843	D 2
3845	A 3
3846	B 3
3847	A 3
3848	B 2
3849	B 3
3900	B 4
3901	B 3
3904	B 3
3905	C 4
3906	D 1
3908	D 2
3910	D 3
3913	D 3
3914	C 2
3915	D 3
3917	E 3
3918	F 3
3919	E 2
3921	E 2
3922	B 2
5800	B 2
5801	B 4
5803	E 3
5814	C 1
5816	E 4
5834	E 1
5847	A 3
6809	D 3
6810	E 4
6811	E 4
6812	E 4
6813	E 3
6814	D 3
6820	C 3
6847	B 3
6848	B 2
6849	C 3
7800	B 3
7801	C 2
7802	C 3
7803	D 3
7810	D 2
7811	D 2
7812	D 2
7820	D 3
7830	E 3
7831	E 1
7832	E 1
7846	A 2
7849	B 3
8005	C 3
9800	F 4
9801	E 2
9802	E 3
9803	D 3
9804	C 3
9805	D 3



G

MONO IF/SOUND MODULE
MODULO IF/AUDIO MONO
MODULO SONIDO MONO FI

REMARKS/REMARQUES/ANMERKUNGEN/NOTE
PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEND IN GERÄTEN:
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS:

1) MULTI-SYSTEM
2) SINGLE-SYSTEM
3) UK
4) NON UK

1
2
3
4
5
6
7
8
9
A
B
C
D
E
F
G
H
I
J
K
L
M
N
O
1)
2100
12p
2102
6p8
5101
0u36
2104
47p
2110
0p47
2105
39p
2106
1p5
+14V
2107
39p
5100
0u75
2101
27p
2k2
3102
6102
BA682
6103
BA682
100k
3100
6101
BA682
2111
4n7
5k6
3101
+14
470
3056
7035
BC338
+12
10k
3055
2050
330u
3022
150
2) 0
7M50
8M50
IF
9M50
5010
1) 0u39
2) 0u56
2020
12p
2021
12p
2023
56p
5005
0.27u
6005
BA682
3024
2k2
+14
5k6
3025
2022
22p
2025
4n7
1010
1) OFWG 3950
2) OFWG 1961
3) OFWJ 1952
2,3
+12
4021
27k
3013
4014
4019
3012
5k6
2M51
AGC
2011
10u
3014
82k
2M51
4013
+14
1M51
6M50
POS/NEG
13M50
L'

und module / Mono ZF/Tonmodul / Module FI/son mono


10
11
12
13
14
15
16
17
18
19
20
21
7100
TDA3843
7101
TDA3827
7000
TDA2549
7102
BC848
7030
BC858
7031
BC848
+14
+5
+12
+14V
+12V
12V
3105 270
6112 BZV55C
2125 100u
2124 10n
3108 33k
2118 680u
2107 39p
2109 27p
5102 0u34
3102
6103 BA682
6104 BA682
3101 5k6
3103 100k
2108 4n7
2115 4u7
2117 2u2
2116 10u
3131 1k
2129 330n
3132 3k9
3104 47
2114 4n7
2113 22u
2132 22n
2133 22n
4) SFT5.5 1102
1103 1) 3) SFT6.0
3107 150
5105 0u83
2137 1) 3) 820p 2) 1n
3118 4K7 2) 2k2
2127 330n
2126 8n2
2138 390p
2139 390p
3120 4k7
6108 BA682
3112 4k7
3119 4k7
2143 22n
3117 100k
3116 2k7
5039 22u
6037 BA682
5037 1u35
2036 120p
3037 3k9
3036 4k7
4010
2035 6p8
2037 120p
2049 100n
2044 22n
5035 0u34
3058 6k8 2)
3044 1k
IF
2047 100n
2014 1) 4n7 2) 22n
2013 4n7
4021
3013 27k
3014 82k
4018
3030 22k
3031 470k 1)
2015 680n
2016 4n7
3017 82k
3016 100k
3015 100k 2) 47k
2012 4u7
2019 4n7
3041 220
2042 12p
5036 0u36
2039 15p
2041 4n7
2040 4n7
5038 0u25
3038 4k7
3040 4k7
6038 BA682
3039 3k9
2038 4n7
3019 47k
4015
3020 27k
2017 100n
3021 22k 2) 18k
5041 1) 22u 2) 27u
4016
4100
3042 100 2) 220
5042 1) 5u6 2) 10u
1042 4) TPS5.5
1043 1) 3) TPS6
3052 470 2) 560
3049 18k
3048 2k
3050 2k7
4012
3046 680
3047 8k2
6039 LL4148
2018 470n
3051 56k
2048 47u
AFC
EXT1
11M50
10M50


G
21
22
23
24
25
26
27
28
29
30
A
B
C
D
E
F
G
H
I
J
K
L
M
N
O
L IF
3M51
R IF
4M51
3109
22k
3108
33k
2134
22u
3121
100k
+14V
3144
1k8
3143
1k8
2151
100u
+5
14
12
13
18
3142
27k
2150
220n
L
8M51
17
2130
330n
3140
15k
7104
BC848B
3141
3k9
8
15
11
16
+14V
3129
8k2
3124
10k
7M51
2127
330n
2141
4u7
+5
+5
3125
10k
7103
BC848C
3126
15k
9M51
R EXT
6M51
2126
8n2
3114
4k7
2) 1k8
3130
6k8
3127
15k
2135
220n
L EXT
5M51
2136
330n
I/BG
12M51
2143
22n
3044
1k
2)
+14
6040
LL4148
2055
39p
3086
120k
6042
LL4148
2057
33n
3062
56k
3068
1k5
6041
LL4148
7041
BC848
3060
470
2056
10u
7040
BC858
3066
820k
6043
LL4148
3064
56k
2058
22n
3063
2k7
2059
3u3
3065
22k
3067
330
2060
22n
EXT1
CVBS
CVBS EXT 1/3
CVBS IF
1M50
10M50
4M50
1M50
5M50
CHASSIS GR2.1
CL06532002/016,MREF
040291

1010	I 8	3102	C 9
1042	N16	3103	C10
1043	N16	3104	C15
1102	C18	3105	A19
1103	D18	3107	D18
2011	L 9	3108	B21
2012	M11	3109	A21
2013	K11	3112	F20
2014	J11	3114	E22
2015	L10	3116	F20
2016	L11	3117	G19
2017	L19	3118	E20
2018	N19	3119	F19
2019	N12	3120	F19
2020	J 5	3121	B25
2021	J 7	3124	D25
2022	K 6	3125	D25
2023	J 6	3126	D26
2025	K 7	3127	E26
2035	H14	3129	D22
2036	G13	3130	E24
2037	H14	3131	B16
2038	O13	3132	C16
2039	M14	3140	C25
2040	N14	3141	C25
2041	N13	3142	C25
2042	L14	3143	B26
2044	I13	3144	B26
2047	J18	4010	H13
2048	O20	4012	M19
2049	I12	4014	K 8
2050	F 4	4015	K18
2055	L23	4016	L16
2056	M23	4018	L11
2057	M24	4019	K 9
2058	N25	4021	K 9
2059	N26	4100	L17
2060	N27	5005	J 6
2100	B 6	5010	J 4
2101	C 7	5035	I14
2102	B 7	5036	M14
2104	B 8	5037	G14
2105	B 9	5038	N14
2106	B 9	5039	G13
2107	B10	5041	L18
2108	D10	5042	M16
2109	B10	5100	C 6
2110	B 8	5101	B 7
2111	C 9	5102	B11
2113	C16	5105	D20
2114	C15	6005	J 7
2115	C11	6037	G14
2116	D14	6038	N14
2117	D12	6039	N18
2118	B21	6040	K24
2124	B19	6041	M24
2125	B18	6042	M24
2126	E21	6043	N25
2127	D21	6101	C 8
2129	B17	6102	C 9
2130	C24	6103	C10
2132	C18	6104	C10
2133	C18	6108	F20
2134	A24	6112	B18
2135	E26	7000	I12
2136	E24	7030	M18
2137	O20	7031	M19
2138	F19	7035	F 4
2139	F20	7040	M25
2141	D23	7041	M26
2143	F21	7100	B12
2150	C26	7101	B19
2151	C26	7102	F19
3012	K 9	7103	E25
3013	K 9	7104	C25
3014	L 9		
3015	M11		
3016	M11		
3017	L12		
3019	K18		
3020	K19		
3021	K20		
3022	I 6		
3024	J 5		
3025	J 6		
3030	L11		
3031	L10		
3036	H15		
3037	G14		
3038	N14		
3039	O14		
3040	N13		
3041	L14		
3042	M16		
3044	I21		
3046	N17		
3047	N18		
3048	M18		
3049	M18		
3050	M18		
3051	N20		
3052	N17		
3055	F 3		
3056	E 3		
3058	I14		
3060	M23		
3062	M25		
3063	N25		
3064	N26		
3065	N26		
3066	N24		
3067	N27		
3068	M27		
3086	L24		
3100	C 8		
3101	C 9		

Mono IF/sound module / Mono ZF/Tonmodul /



MONO IF/SOUND PANEL

1
2
3
4
5
6
7
A
B
C
D
M50
M51
CVBS EXT
AGC
CVBS
IDENT
CVBS IF
POS/NEG
⊥
IF
⊥
EXT 1
AFC
I/BG
L'
⊥
+14
L IF
R IF
L EXT
R EXT
L
MUTE
7000
7100
7035
3016
3048
6039
5100
5101
5102
5005
1010
1042
1043
1102
1103
5035
5036
5037
5038
5039
5041
5042
5010
3043
3104
3116
9010
9011
9012
9014
9016
9017
9018
9026
9028
9030
9031
9032
9100
9102
9106
2011
2012
2015
2018
2048
2050
2056
2059
2113
2115
2116
2117
2126
2127
2129



MONO IF/SOUND PANEL

9
8
7
6
5
4
3
A
B
C
D
M51
MUTE
L
R EXT
L EXT
R IF
L IF
+14
⊥
L'
I/BG
AFC
EXT 1
7000
7100
7102
7104
3016
5100
5101
5102
5105
5005
5041
5042
1010
1042
1043
1102
1103
6005
6101
6102
6103
6104
6108
6112
9016
9017
9018
9014
9026
9028
9030
9031
9032
9100
9101
9102
9106

Module FI/son mono


8
9
A
B
C
D
2151
3105
2125
2127
2130
2141
5105
2136
2150
2135
9101
7101
2118


2
1
A
B
C
D
3043
9010
3055
7035
2048
9011
2042
6040
3041
3061
2055
6042
6041
2056
4010
2036
2041
3040
3036
2037
6037
6038
2038
2057
3062
3066
2058
3063
3048
6039
3051
2018
3064
3065
3068
3067
2060
7041
4014
4012
7031
4020
9012
M50
2047
2049
3044
4021
3058
2044
3052
4016
4042
9014
3046
13
12
11
10
9
8
7
6
5
4
3
2
1
L'
I/BG
AFC
EXT 1
⊥
IF
⊥
POS/NEG
CVBS IF
IDENT
CVBS
AGC
CVBS EXT
PCB 03173
T28/107

M50	C2
M51	C6
1010	B4
1042	C3
1043	C3
1102	B7
1103	B7
2011	C4
2012	B4
2013	B3
2014	B3
2015	C4
2016	B3
2017	A3
2018	C1
2019	C4
2020	C4
2021	C4
2022	B4
2023	C4
2025	B4
2035	B3
2036	B2
2037	B2
2038	C1
2039	B2
2040	B2
2041	B2
2042	B2
2044	B3
2047	D1
2048	A1
2049	A3
2050	A2
2055	B1
2056	B1
2057	B1
2058	C1
2059	C1
2060	D1
2100	C5
2101	C5
2102	C5
2104	C6
2105	C5
2106	C6
2107	B6
2108	C6
2109	B6
2110	C6
2111	C5
2112	B6
2113	B5
2114	B5
2115	B6
2116	B6
2117	A6
2118	C8
2124	B8
2125	B9
2126	B7
2127	B7
2129	C7
2130	C9
2132	B8
2133	B8
2134	C8
2135	D9
2136	C8
2137	C8
2138	C7
2139	C8
2141	C9
2143	C7
2150	D9
2151	B7
3012	B3
3013	B3
3014	B4
3015	B4
3016	B4
3017	B4
3019	A3
3020	A3
3021	B4
3022	C4
3024	C4
3025	C4
3030	B3
3031	C4
3036	B3
3037	C2
3038	C2
3039	C2
3040	B2
3041	B2
3042	B3
3043	A1
3044	A3
3046	C3
3047	C3
3048	C2
3049	C2
3050	C2
3051	C2
3052	B3
3055	A2
3056	A2
3058	B3
3060	B1
3061	B1
3062	B1
3063	C1
3064	C1
3065	C1
3066	B1
3067	C1
3068	C1
3080	C7
3100	C6
3101	C5
3102	C6
3103	B6
3104	A5
3105	B8
3107	B7
3108	C8
3109	C8
3112	C8
3114	C7
3116	B5
3117	B4
3118	C8
3119	C7
3120	C7
3121	C8
3124	C9
3125	C8
3126	D8
3127	C9
3129	C7
3130	C8
3131	B7
3132	B6
3140	C9
3141	C9
3142	C9
3143	C9
3144	B7
4010	B2
4011	C3
4012	C2
4013	A4
4014	C2
4015	B3
4016	B3
4018	C3
4019	C3
4020	C2
4021	B3
4100	A3
5005	C4
5010	C4
5035	B3
5036	B2
5037	B3
5038	B1
5039	C2
5041	A4
5042	C3
5100	B5
5101	C6
5102	B6
5105	C7
6005	C4
6037	B2
6038	B2
6039	C2
6040	B1
6041	B1
6042	B1
6043	C1
6101	C6
6102	C6
6103	B6
6104	B6
6108	C7
6112	B9
7000	B3
7030	C2
7031	C2
7035	A2
7040	C1
7041	C1
7100	B6
7101	B8
7102	B4
7103	C9
7104	C9
9010	A1
9011	B1
9012	C2
9014	C3
9016	A4
9017	A4
9018	C3
9026	C4
9028	B5
9030	C5
9031	C5
9032	C5
9100	C5
9101	B8
9102	B7
9106	C6

Stereo IF/sound module / Stereo ZF/Tonmodul /


STEREO IF/SOUND MODULE
1
2
3
4
5
A
B
C
M50
7001
7010
7035
7016
5035
5036
5037
5038
5039
5042
5010
5100
5101
5104
1042
1101
1102
1103
6039
3046
3048
3015
3016
CVBS EXT
AGC
CVBS
IDENT
CVBS IF
POS/NEG
⊥
IF
⊥
EXT1
AFC
I/BG
L
⊥
+14
L IF


STEREO IF/SOUND MODULE
8
7
6
5
4
A
B
C
M51
7100
7200
7205
7220
5100
5101
5102
5103
5104
5105
1100
1102
1200
3016
3204
SDA
SCL
N.C
R
MUTU
L
N.C
R EXT
L EXT
R IF
L IF
+14
⊥

Module FI/son stéréo





M50	C2
M51	C6
1010	B3
1042	B2
1101	B4
1102	A4
1103	B4
1200	A7
2011	C2
2012	A3
2013	A2
2014	A3
2015	C3
2016	A2
2017	A3
2018	C1
2035	A2
2036	B1
2037	B2
2038	B1
2039	A1
2040	B1
2041	B1
2042	A1
2044	A2
2047	C1
2048	A1
2049	B2
2050	A1
2051	A1
2055	A1
2056	A1
2057	B1
2058	C1
2059	C1
2100	C3
2101	B3
2102	C4
2104	C4
2105	B5
2106	C5
2107	C5
2108	C4
2109	C5
2110	C4
2111	C5
2112	C5
2113	B5
2114	B5
2115	B4
2117	B5
2118	A5
2119	A5
2120	A5
2122	B4
2123	B6
2124	B6
2125	B5
2126	A5
2127	A6
2128	A6
2129	A6
2130	B6
2133	C3
2200	B6
2201	A7
2202	B6
2203	A7
2204	A7
2205	B7
2206	B8
2207	B7
2208	C7
2209	B7
2210	B8
2211	B7
2212	B7
2213	B8
2214	B8
2215	B8
2216	C8
2217	B8
2218	B8
2219	C8
2220	C7
2221	C8
2222	B8
3012	B2
3013	A2
3014	A3
3015	A3
3016	A4
3017	B3
3019	A2
3020	A2
3021	C3
3030	B3
3031	B3
3036	B2
3037	B1
3038	B1
3039	B1
3040	B1
3041	A1
3042	B2
3043	A3
3044	A2
3046	B2
3047	B2
3048	C2
3049	B2
3050	B1
3051	B1
3052	B2
3053	C3
3055	A1
3056	A1
3060	A1
3061	A1
3062	B1
3063	C1
3064	C1
3065	C1
3066	B1
3070	A6
3100	C4
3101	C5
3102	C5
3103	C5
3105	A4
3106	A4
3107	B4
3108	B4
3109	A4
3110	A4
3112	A4
3113	A4
3115	B5
3117	B5
3119	A6
3120	A6
3121	A5
3122	A5
3123	B4
3124	B4
3125	A5
3126	A6
3127	B6
3128	B6
3200	C8
3201	C8
3202	B7
3203	B7
3204	A6
3205	C6
3206	B8
3207	C8
3208	B8
3209	B8
3210	B7
3211	B6
3213	A8
3214	C8
4010	A2
4011	C3
4012	C3
4014	B2
4015	A2
4018	B3
4019	B2
4020	B2
4021	A2
4040	A2
4041	A3
4042	B1
4100	B5
4101	A6
4102	B5
4104	B6
4105	B6
4107	A4
4108	A4
4201	B8
4204	C8
4205	B7
5010	B3
5035	A2
5036	A1
5037	B2
5038	B1
5039	B1
5042	B2
5100	C4
5101	C5
5102	B5
5103	B6
5104	A5
5105	A6
6037	B1
6038	B1
6039	C1
6040	A1
6041	B1
6042	B1
6043	C1
6101	C4
6102	C4
6103	C4
6104	C5
6106	A4
6107	A4
6108	A6
6109	B6
7000	A2
7030	B1
7031	C1
7035	A1
7040	B1
7100	B5
7101	B5
7102	B5
7103	B4
7104	A6
7200	B7
7220	B8
7232	C8
9000	A1
9001	A3
9011	A1
9012	C1
9013	C2
9014	C2
9015	C2
9016	A3
9021	C3
9022	C3
9023	C3
9026	B3
9101	B4
9103	A6
9104	A6
9200	C5
9201	C6
9202	A7
9204	C8

Stereo IF/sound module / Stereo ZF/Tonmodul /


H
STEREO IF/SOUND MODULE
MODULO IF/AUDIO STEREO
MODULO SONIDO ESTEREO FI
1M51
2M50
+14
3125
1k
4100
2122
100n
3122
1k2
7103
BC858
7102
BC848
3124
2k2
3123
560
7100
TDA3856
1)
1010
OFWK 3261
IF VIDEO
IF
QSS
2,3,8,10
8M50
7M50
9M50
13M50
2100
12p
5010
0u5
2102
6p8
5101
0u36
2104
39p
2110
6p8
2105
33p
2106
1p5
2107
39p
2112
2p7
2109
27p
5102
0u34
5100
0u75
2101
27p
3102
2k2
6102
BA682
6103
BA682
3100
100k
6101
BA682
2111
4n7
3101
5k6
6104
BA682
3103
100k
3105
120
2108
4n7
2115
33u
2114
10n
2113
10u
2123
4u7
2u2
IF'
2)
7101
TDA 3857
1010
OFWG 3251
4102
5010
1u
2123
1u
2126
4n7

Module FI/son stéréo


10
11
12
13
14
15
16
17
18
19
20
21
22
12MS0
I/BG
3109 5k6
3110 5k6
+14
4108
3113 5k6
3112 5k6
3107 1k
1102 SFE6.0
6106 BA682
3108 560
1103 SFT5.5
6107 BA682
3106 560
1101 SFT5.74
5103 0u83
2125 910p
3115 330
2119 22n
2117 2u2
5104 1u2
2126 4n7
2R
R+L
3117 560
2127 820p
5105 0u83
2128 820p
2129 220p
2120 2u2
2118 2u2
2123 4u7
2124 2u2
4104
3120 5k6
3119 5k6
6108 BA682
3121 5k6
2133 22n
6109 LL4148
4101
POS/NEG
4103
3117 680
2127 1n
2123 1u
3128 1k8
2130 150u
3127 1k5
7104 BC848
2202 470n
3126 1k
3204 10k
2201 470n
2200 470n
7200 TDA8417
MATR.
IDENT.
10 MHz
DIV
V=
1200 10MHz
2404 220n
5039 33u
6037 BA682
5037 1u35
2036 4n7
3037 3k9
4010
2035 5p6
2037 4n7
5035 0u5
3058 4k7
3056 470
3055 10k
7035 BC338
2050 330u
4040
2051 100n
+12
2049 100n
2044 22n
7000 TDA2549
3013 27k
2014 22n
2013 4n7
4014
4019
3012 5k6
3014 82k
2011 47u
4018
3030 22k
2016 4n7
3031 470k
2015 680n
3017 82k
3041 220
2042 12p
5036 0u36
3016 100k
3015 100k
2012 4u7
4107
4041
2039 8p2
2041 4n7
2040 4n7
5038 0u25
3038 4k7
3040 4k7
6038 BA682
3039 4k7
2038 100n
L'
AGC
2M50
6M50

REMARKS/REMARQUES/ANMEF

PRESENT IN SETS:
PRESENT SUR LES APPAREI
ANWESEND IN GERÄTEN:
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS

1) MULTI
2) NON MULTI

REMARQUES/ANMERKUNGEN/NOTE
IN SETS:
SUR LES APPAREILS:
IN GERäTEN:
SUI MODELLI:
SOBRE MODELLOS:

ULTI


22
23
24
25
26
27
28
29
30
31
32
33
6M51
5M51
13M51
12M51
R EXT
L EXT
SDA
SCL
4201
330 3200
330 3201
56k 3202
56k 3203
7220
TDA8425
I²C
V=
2209 33u
2208 33u
2207 470n
2206 470n
R
L
SCL
SDA
+14
3205 22
4R7 3206
2212 10u
2205 100n
2211 470u
2210 100n
4205
2213 15n
2214 15n
2215 33n
2216 5n6
2217 33n
2218 5n6
+14V
1k8 3211
1k8 3210
3209 33k
3207 27k
2k7 3208
7232 BC848B
4204
2220 4u7
3213 10k
2203 5n6
IDEN
5037 1u35
3k9 3037
+12
4k7 3036
2037 4n7
+14
220 3043
7043 BC848
2043 100n
1k 3044
1k 3045
3043 100
2047 100n
+12
47k 3019
3020 27k
4021
4015
2017 100n
18k 3021
2)
+14
6040 LL4148
2055 39p
120k 3061
6042 LL4148
6041 LL4148
2057 33n
56k 3062
7040 BC858
3060 470
2056 10u
3066 820k
6043 LL4148
3064 56k
2058 22n
2k7 3063
2059 3u3
+14
8k2
4k7
220 3041
2042 12p
4020
82 3042
5042 5u6
1042 TPS5.5
1k 3052
+12
4042
18k 3049
2k7 3050
2k 3048
7030 BC858
7031 BC848
3046 680
8k2 3047
6039 1N4148
2018 470n
56k 3051
2040 4n7
+12
5038 0u25
4k7 3038
4k7 3039
2048 47u
AFC
EXT1
CVBS
CVBS EXT 1/3
CVBS IF
11M50
10M50
3M50
1M50
5M50
CHASSI
CLO


H
6M51
5M51
13M51
12M51
R EXT
L EXT
SDA
SCL
4201
3200 330
3201 330
R IF 4M51
L IF 3M51
3202 56k
3203 56k
7220 TDA8425
I²C
V=
2217 33n
2218 5n6
+14V
3211 1k8
3210 1k8
2222 100u
3209 33k
2221 4u7
L 8M51
3207 27k
3208 2k7
7232 BC848B
4204
2220 4u7
R 10M51
SDA
+14
3205 22
3206 4R7
2212 10u
2213 15n
2214 15n
2215 33n
2216 5n6
2205 100n
2211 470u
2210 100n
4205
3213 10k
3214 1k
9M51
2203 5n6
2219 47u
+14
3043 220
7043 BC848
2043 100n
3044 1k
3045 1k
IDENT
3043 100
2047 100n
2)
+14
6060 LL4148
2055 39p
3061 120k
6042 LL4148
6041 LL4148
2057 33n
3062 56k
7040 BC858
3060 470
2056 10u
3066 820k
6043 LL4148
3064 56k
2058 22n
3063 2k7
2059 3u3
+14
3070 8k2
1)
4017
2)
IDENT 4M50
3065 4k7
2) 33k
3019
3020 27k
4021
4015
2017 100n
3021 18k
4042
3049
3050 2k7
3048
7030 BC858
7031 BC848
2018 470n
3051 56k
3047
6039 1N4148
AFC
EXT1
CVBS
CVBS EXT 1/3
CVBS IF
11M50
10M50
3M50
1M50
5M50
CHASSIS GR2.1
CL06532002/014.MREF 040291
26
27
28
29
30
31
32
33
34

1010	D 6	3042	M24	6102	F 5
1010	K 6	3043	I29	6103	F 6
1042	N23	3043	J25	6104	F 7
1101	C11	3044	I28	6106	B12
1101	J11	3045	I29	6107	B12
1102	B11	3046	N25	6108	H14
1103	B11	3047	N25	6109	G14
1103	I11	3048	M25	7000	J19
1200	G19	3049	M25	7030	N26
2011	K17	3050	M26	7031	N27
2012	N19	3051	N27	7035	I18
2013	K19	3052	N24	7040	M32
2014	K19	3055	I17	7043	I29
2015	L17	3056	H17	7100	D 8
2016	L18	3058	I21	7101	K 8
2017	L27	3060	M30	7102	B 9
2018	N27	3061	L30	7102	J 9
2035	H21	3062	L31	7103	B10
2036	H21	3063	M32	7103	I10
2037	H22	3064	M33	7104	B18
2038	D20	3065	M33	7200	D19
2039	N21	3066	M31	7220	D27
2040	N21	3070	M33	7232	D33
2041	N21	3100	F 5		
2042	M22	3101	F 6		
2043	I29	3102	F 6		
2044	I20	3103	F 7		
2047	J26	3105	F 8		
2048	O22	3105	M 8		
2049	I19	3106	C11		
2050	I17	3106	J11		
2051	I18	3107	B11		
2055	K30	3108	B11		
2056	M30	3108	J11		
2057	L31	3109	A12		
2058	M31	3110	A12		
2059	M32	3112	C13		
2100	E 3	3113	B13		
2101	F 4	3115	C14		
2102	E 4	3115	K14		
2104	E 5	3117	G14		
2105	E 5	3117	N14		
2106	E 6	3119	I13		
2107	E 6	3120	H13		
2108	G 7	3121	H14		
2109	E 7	3122	B 9		
2110	E 5	3122	I 9		
2111	F 6	3123	C 9		
2112	E 7	3123	K 9		
2113	G 9	3124	C10		
2114	G 9	3124	J10		
2114	N 9	3125	A 9		
2115	G 8	3125	H 9		
2115	N 8	3126	C18		
2117	D15	3127	B18		
2117	K15	3128	A17		
2118	G15	3200	A29		
2118	N15	3201	A29		
2119	D13	3202	C25		
2119	K13	3203	C26		
2120	G15	3204	D18		
2122	B 9	3205	F26		
2122	I 9	3206	F27		
2123	G10	3207	D32		
2123	N10	3208	E32		
2124	G10	3209	D33		
2125	C14	3210	D33		
2125	J14	3211	C33		
2126	D10	3213	H33		
2126	K11	3214	H34		
2127	G14	4010	H21		
2127	N14	4014	K17		
2128	H13	4015	L26		
2129	H14	4017	M34		
2130	B17	4018	L18		
2133	I15	4019	K18		
2200	E18	4020	M24		
2201	D18	4021	L26		
2202	B18	4040	I18		
2203	H33	4041	N19		
2205	G25	4042	M25		
2206	E24	4100	B10		
2207	E24	4101	G15		
2208	D24	4102	L 8		
2209	D24	4103	J13		
2210	G26	4104	H13		
2211	G26	4107	N18		
2212	G27	4108	B13		
2213	G29	4201	A27		
2214	G29	4204	F32		
2215	G31	4205	H26		
2216	G31	5010	E 3		
2217	D31	5010	L 6		
2218	D31	5035	I21		
2219	H34	5036	M21		
2220	F33	5037	G22		
2221	D34	5038	N21		
2222	D33	5039	G20		
2404	G21	5042	N23		
3012	K18	5100	F 3		
3013	K18	5101	E 4		
3014	K18	5102	E 8		
3015	M19	5103	B14		
3016	M18	5103	J14		
3017	M20	5104	K11		
3019	K25	5104	C11		
3020	L25	5105	G14		
3021	L27	5105	O14		
3030	L18	6037	G21		
3031	L19	6038	O21		
3036	H22	6039	N26		
3037	H21	6040	K30		
3038	N22	6041	L30		
3039	O22	6042	L30		
3040	O20	6043	M32		
3041	M21	6101	F 5		



I

NICAM IF/SOUND MODULE
MODULO IF/AUDIO STEREO
MODULO SONIDO ESTEREO FI

REMARKS/REMARQUES/ANMERKUNGEN/NOTE

PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEND IN GERäTEN:
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS:

1) PAL I
2) PAL BG

1
2
3
4
5
6
7
8
9
10
A
B
C
D
E
F
G
H
I
J
K
L
M
N
O
+14
3056 470
7035 BC338
+12
3055 10k
2050 330u
1116 TH316BQM 1)2110QDAF 2)2080QDAF
2122 10n
2M51
+14
2119 470u
2198 470n
3197 330
3190 470
7195 BC848
1M51
6190 LL4148
6197 LLZ-C11
2197 47u
3195 10
+10A
11M51 +8
7190 BC858B
2195 47u
2196 10n
5M51 L EXT
6M51 R EXT
12M51 SCL
3206 330
3160 330
1191 400mA
7191 BC338
3191 39
2193 330u
3192 4R7
+5A
2194 100n
2190 100n
6191 LLZ-C5V6
2191 100u
2192 100n
+5
13M51 SDA
3208 330
3161 330
3116 470
2116 1n
3122 470
2121 0u47
2,4,5
510
1010 1)OFWF3251 2)OFWG3254
8M50 IF
7M50
9M50
5010 1u
2,3,8,10
+12
2049 100n
2044 22n
3035 4k7
5035 0u34
7000 TDA2549/C4
3044 1k
2014 22n
2013 22n
+12
3013 27k
2M50 AGC
3012 5k6
3030 22k
2011 47u
3014 470k
2015 680n
2016 4n7
3019 47k
3020 27k
3041 220
2042 12p
5036 0u36
3042 100
2120
3052 1k
2017 100n
3021 18k
5042 5u6
1042 1)6.0MHz 2)5.5MHz
+14
3016 100k
3015 100k
2012 4u7
+12
AFC
EXT1
11M50
10M50


ND MODULE
DIO STEREO
D ESTEREO FI
1116
TH316BQM
1)2110QDAF
2)2080QDAF
7120
TA8662N
VCO
90°
1125
1)6.552MHz
2)5.85MHz
7035
BC338
7195
BC848
7190
BC858B
7191
BC338
1191
400mA
3192
4R7
6190
LL414B
6197
LLZ-C11
6191
LLZ-C5V6
1010
1)OFWF3251
2)OFWG3254
7000
TDA2549/C4
7100
TDA3857
7106
BC848
3035
4k7
5035
0u34
5036
0u36
5042
5u6
1042
1)6.0MHz
2)5.5MHz
IF
EXT
SCL
SDA
+14
+12
+10A
+5A
+5
+8
AFC
EXT1
CVBS
CVBS EXT 1/3
CBVS IF
11M50
10M50
3M50
1M50
5M50

REMARKS/REMARQUES/ANMERKUNGEN/NOTE

PRESENT IN SETS:
PRESENT SUR LES APPAREILS:
ANWESEND IN GERäTEN:
PRESENTE SUI MODELLI:
PRESENTE SOBRE MODELLOS:

1) PAL I
2) PAL BG

NICAM IF/sound module / NICAM ZF/Tonmodul /


13
14
15
16
17
18
19
20
21
22
23
24
25
+10A
2129 220p
2130 220p
5129 820u
5130 820u
2137 10n
2131 10n
2138 10n
3139 39k
2139 0u47
2142 33p
2140 56p
1141 5.824MHz
2141 18p
3141 1k
3140 470
3143 330
2143 15p
VCO 5.824MHz
÷ 8
÷ 2
90°
Y=XT1-XT0
2146 15p
2147 15p
A
B
2133 100n
2134 100n
2136 100n
2135 100n
+10A
3126 39k
2128 10n
2127 0u47
+5
3144 2R7
2144 10n
2145 47u
7150 CF70123
+5A
CL
DA
DESCR.
FAW
RAM
MU EN
MU FL
C0 C1 C2 C3 C4
IM
5.284MHz
VCO 18.384MHz
÷2
÷1
7160 PCF8574P
P5
P4
P8
P.
P1
P6
P3
READ
WRITE
I²C CONTROL
A1
A2
SCL
SDA
+5A
3150 1k
3151 10k
2151 47p
5153 3u3
2153 10n
2150 100n
6151 BB405B
2152
2155 1p8-22p
2154 39p
+14
3110 1k
2110 100n
3107 1k2
7108 BC858
7106 BC848
3108 2k2
3106 560
3100 560
1100 SFT 5.74MHz
3105 560
1105 SFT 1) 6.0MHz 2) 5.5MHz
5103 1u2
2104 4n7
5101 2) 0u83
2101 2) 1n
3101 330
2107 2u2
2200 470n
2201 470n
3201 8k2
3200 10k
3202 5k1
2202 120p
2100 1u
2106 2u2
3102 680
2102 1) 820P 2) 1n
5102 0u83
7200 TDA8415
SDA
SCL
NICAM L
NICAM R
MATR.
IDEN.
V=
I²C
10 MHZ
1200 10MHz
3209 10k
3210 1k
2210 47u
2211 220n
9MS1
+14
3205 22
3070 8k2
3065 4k7
2205 100n
2214 100n
2215 47u
2212 5n6
2108

Module FI/son NICAM


I
3162
330
2162
100n
SCL
SDA
I²C CONTROL
A1
A2
+5
+5A
2160
2161
7168
TDA1543
3168
2R7
2168
100n
2169
47u
ERFL
ID
CL
DA
I²S
3171
2k7
2) 1k
2171
1) 15n
2) 39n
3172
4k7
3173
2174
2n7
2175
2n2
2170
1) 6n8
2) 18n
2173
560p
3170
15k
2) 5k6
7170
LM833N
2176
470n
11
+14
3188
10
2188
47u
2189
22n
3181
2181
3182
3183
2184
2185
2180
2183
3180
7180
LM833N
2186
10
2177
22n
3177
2) 8k2
2187
22n
2154
39p
R EXT
L EXT
L IF
3MS1
R IF
4MS1
2221
2222
2224
33n
2223
5n6
7220
TDA8425
2203
33u
2204
2207
470n
2209
3203
56k
3204
2206
2208
V=
3313
4R7
2213
150u
2215
15n
2226
2216
33n
2220
3218
100
3217
1k
2218
100u
3216
33k
2217
4u7
8MS1
3214
27k
7217
BC848B
3215
2k7
2219
10MS1
2212
5n6
CHASSIS GR2.1
CL06532002/015.MREF
040291
25
26
27
28
29
30
31
32
33
34

1010	H 3	2218	K33
1042	O 8	2219	M34
1100	I16	2220	N31
1105	I16	2221	K28
1116	B 9	2222	K30
1125	F12	2223	K31
1141	A17	2224	K31
1191	E 5	2226	N29
1200	N21	3012	M 2
2011	N 2	3013	M 2
2012	O 4	3014	M 2
2013	M 4	3015	N 4
2014	L 4	3016	N 3
2015	N 3	3019	L10
2016	N 4	3020	M10
2017	N 9	3021	N 1
2042	N 7	3030	M 3
2044	J 5	3035	J 6
2047	M11	3041	N 6
2049	J 4	3042	N 8
2050	B 8	3043	L11
2100	N14	3044	K10
2101	J18	3052	N 9
2102	N18	3055	B 8
2104	K15	3056	A 8
2106	N19	3065	O24
2107	K19	3070	N24
2108	N13	3100	I15
2109	N12	3101	K18
2110	I13	3102	N18
2116	D 9	3105	I15
2119	C 5	3106	J14
2120	B12	3107	I14
2121	D11	3108	I14
2122	C10	3109	M12
2123	G11	3110	H14
2124	F12	3116	D 9
2125	F11	3120	A12
2126	G12	3121	D11
2127	G14	3122	D10
2128	G13	3123	F11
2129	A13	3125	F12
2130	A14	3126	F14
2131	B15	3139	A16
2132	B13	3140	B17
2133	F14	3141	A18
2134	F15	3143	B18
2135	F16	3144	F17
2136	F16	3150	F22
2137	B15	3151	G22
2138	B16	3160	F 2
2139	B16	3161	G 2
2140	B17	3162	A26
2141	A18	3168	B28
2142	B17	3170	B31
2143	C19	3171	A30
2144	G17	3172	A31
2145	G17	3173	A32
2146	C18	3177	G30
2147	D18	3180	E31
2148	B11	3181	D30
2150	G22	3182	D31
2151	G23	3183	E32
2152	G23	3188	C30
2153	G24	3190	D 5
2154	G24	3191	E 7
2155	G23	3192	F 7
2160	C26	3195	D 8
2161	C26	3197	C 6
2162	B26	3200	M20
2168	C28	3201	M20
2169	C29	3202	N20
2170	A31	3203	L26
2171	A31	3204	L26
2173	B31	3205	N24
2174	A32	3206	F 2
2175	A33	3208	F 2
2176	C33	3209	N21
2177	G29	3210	O21
2180	E31	3214	L32
2181	D31	3215	L32
2183	E31	3216	K32
2184	E32	3217	K33
2185	E33	3218	J33
2186	F33	3313	M27
2187	G31	5010	I 2
2188	D30	5035	J 6
2189	D31	5036	N 6
2190	F 5	5042	N 8
2191	F 6	5101	J18
2192	F 8	5102	O18
2193	F 8	5103	J15
2194	F 4	5129	B13
2195	E 8	5130	B14
2196	E 8	5153	G24
2197	D 7	6151	G22
2198	C 6	6190	D 5
2200	K20	6191	F 5
2201	L20	6197	D 6
2202	N20	7000	K 4
2203	K25	7035	A 9
2204	K25	7100	K13
2205	O23	7106	I13
2206	L26	7108	I14
2207	L27	7120	B11
2208	L27	7150	C19
2209	L27	7160	A23
2210	O22	7168	C27
2211	N22	7170	B33
2212	O25	7180	F33
2213	N27	7190	E 5
2214	O23	7191	F 6
2215	O24	7195	D 8
2215	N29	7200	K20
2216	N31	7217	I33
2217	K34	7220	K27

NICAM IF/sound module / NICAM ZF/Tonmodul /



NICAM IF/SOUND MODULE

1
2
3
4
5
6
7
A
B
C
D
M50
M51
CVBS EXT
AGC
CVBS
IDENT
CVBS IF
N.C.
⊥
IF
⊥
EXT1
AFC
N.C.
N.C.
⊥
+14
L IF
R IF
L EXT
R EXT
N.C.
L
MUTE
R
+8
SCL
SDA



NICAM IF/SOUND MODULE

9
8
7
6
5
4
3
A
B
C
D
M51
SDA
SCL
+8
R
MUTE
L
N.C.
R EXT
L EXT
R IF
L IF
+14
⊥
N.C.

Module FI/son NICAM





M50	D2
M51	D6
1010	C2
1042	D1
1100	A1
1105	A1
1116	A3
1125	A3
1141	A5
1191	C9
1200	C3
2011	D1
2012	C3
2013	C2
2014	C2
2015	C2
2016	C2
2017	C2
2042	C1
2044	C1
2047	C2
2049	B1
2050	B1
2100	B2
2101	B2
2102	B3
2104	A2
2106	A1
2107	A1
2108	B2
2109	B1
2110	B1
2116	A2
2119	C8
2120	A4
2121	A3
2122	A3
2123	A4
2124	B3
2125	B3
2126	A3
2127	B3
2128	B3
2129	B4
2130	B4
2131	B4
2132	B4
2133	B4
2134	B4
2135	B4
2136	B4
2137	A5
2138	B5
2139	B5
2140	A4
2141	A5
2142	A4
2143	B5
2144	A5
2145	A5
2146	A5
2147	A5
2148	A4
2150	C6
2151	B6
2152	B5
2153	B6
2154	B5
2155	A6
2160	B5
2161	C5
2162	C5
2168	C7
2169	C7
2170	C8
2171	C8
2173	C8
2174	C8
2175	C8
2176	C7
2177	C7
2180	B8
2181	B8
2183	B7
2184	B7
2185	B7
2186	C7
2187	B8
2188	B8
2189	B7
2190	C9
2191	C8
2192	A5
2193	D9
2194	D9
2195	D7
2196	D7
2197	D8
2198	D8
2200	C3
2201	C3
2202	A2
2203	C5
2204	B4
2205	C3
2206	C3
2207	D4
2208	C4
2209	C4
2210	D7
2211	C4
2212	C3
2213	C3
2214	C3
2215	D3
2216	C4
2217	C6
2218	C6
2219	C5
2220	C4
2221	D4
2222	B5
2223	C4
2224	C5
2225	C4
2226	C4
3012	B2
3013	B1
3014	B2
3015	B2
3016	B2
3019	B1
3020	C1
3021	C2
3030	C2
3035	C1
3041	C1
3042	C2
3043	B2
3044	B1
3052	D2
3055	B1
3056	B1
3065	D3
3070	D4
3100	B1
3101	B2
3102	A2
3105	B1
3106	B1
3107	B1
3108	B1
3109	B1
3110	B1
3116	B3
3120	A3
3121	A4
3122	A3
3123	A3
3125	B4
3126	B3
3139	B5
3140	A4
3141	A4
3143	B5
3144	A5
3150	C6
3151	C6
3160	C5
3161	C5
3162	C5
3168	C8
3170	C8
3171	C8
3172	C8
3173	C8
3177	C7
3180	B8
3181	B8
3182	B7
3183	B7
3188	C9
3190	C8
3191	C8
3192	C9
3195	D7
3197	D8
3200	B3
3201	B2
3202	B2
3203	D5
3204	D4
3205	D3
3206	C3
3208	B3
3209	C7
3210	D6
3213	B3
3214	D5
3215	D5
3216	D5
3217	D5
3218	D5
4000	B6
5010	C3
5035	C1
5036	C1
5042	C1
5101	B2
5102	A3
5103	A2
5129	B4
5130	B4
5153	B6
6151	C6
6190	C9
6191	D9
6197	C8
7000	C2
7035	B1
7100	A2
7106	B1
7108	B1
7120	B4
7150	B5
7160	B5
7168	C7
7170	C8
7180	B7
7190	C9
7191	D9
7195	C8
7200	C3
7213	C4
7217	D5

PIP module / PIP-Modul / Module PIP


3
2
1
D
C
B
A
1155
5157
5175
5170
5190
9040
2351
9002
9003
9004
3157
9046
7126
7125
2212
1212
1201
9007
3106
9050
5118
2350
3353
3345
P017
3155
2161
2160
3202
3242
2345
7235
2232
3470
9045
2230
3221
2197
2220
3196
3440
3239
2238
5403
2402
5402
3227
2442
3446
3444
2250
7408
7755
9010
9011
9012
9013
5404
9015
9016
9025
7406
7410
9044
9043
3462
2451
9041
2459
3463
5400
2438
2439
9026
9024
9032
5406
9031
5408
5410
3460
3461
P016
2400
9027
9028
9029
9042
7380
9036
3341
9037
P57
P56
9034
2340
9038
9035
9033
9030
9039

1155 C3	2404 B3	3265 C1	3997 D1	7
1201 D2	2405 B3	3270 C1	4001 D2	77
1212 D2	2409 B3	3275 C1	4002 C3	9
2103 D1	2410 B3	3276 C1	4003 B2	9
2105 D1	2413 C3	3330 B1	4004 A1	9
2118 D1	2414 B3	3331 A1	4005 C2	9
2119 D1	2415 B3	3332 A1	4006 D1	9
2120 D1	2430 B3	3333 B1	4007 D2	9
2125 C3	2432 B3	3334 B1	4010 B1	9
2155 C3	2434 B2	3335 B1	4011 B2	9
2158 D3	2438 B3	3336 B1	4012 B2	9
2160 C2	2439 A3	3337 B1	4047 A2	9
2161 C2	2440 B3	3338 A1	4048 A2	9
2162 C3	2441 B3	3339 B1	4049 A2	9
2163 C3	2442 B2	3340 B1	4100 D1	9
2171 D2	2444 C2	3341 A1	4200 D1	9
2172 D2	2446 B2	3345 C1	4201 D1	9
2176 D3	2448 A2	3353 D1	4401 B2	9
2177 D3	2449 B1	3354 D1	4402 B2	9
2180 D2	2450 B2	3380 A3	4403 B2	9
2181 D3	2451 B2	3381 A3	4404 B1	9
2185 C2	2454 B1	3382 A3	4406 A1	90
2187 D2	2455 B2	3383 A3	4407 B1	90
2189 D2	2459 B1	3384 A3	4410 B1	90
2196 C2	2466 B2	3385 A3	4411 B1	90
2197 C3	3103 D1	3386 A2	4415 C3	90
2201 D2	3104 D1	3387 A3	5118 D1	90
2202 C2	3105 D1	3388 A2	5155 C3	90
2211 D2	3106 D2	3390 A1	5157 D3	90
2212 D2	3107 D2	3391 A1	5170 D2	90
2220 C2	3108 D2	3394 A2	5175 D2	90
2222 C2	3155 C3	3395 A1	5190 D2	90
2227 B2	3156 C3	3398 A2	5400 B3	90
2230 C1	3157 D3	3399 A1	5402 C3	90
2232 C1	3158 D3	3404 C3	5403 C3	90
2234 C1	3170 D2	3405 B3	5404 B3	90
2235 C1	3175 D2	3410 B3	5406 A2	P
2238 C2	3195 C2	3411 B3	5408 A2	P
2239 C1	3196 C2	3412 B3	5410 A1	P5
2250 C2	3200 D2	3413 B3	6300 B2	P5
2251 C1	3201 D2	3414 B3	7103 D1	
2255 C1	3202 D2	3416 B3	7105 D1	
2260 C1	3211 D2	3434 B3	7125 D3	
2270 C2	3212 D2	3435 B3	7126 D2	
2330 B1	3214 C2	3436 B2	7200 C2	
2333 B1	3220 C2	3437 B2	7210 D2	
2340 A1	3221 C3	3438 B3	7233 D1	
2345 C1	3222 D2	3440 C2	7234 D1	
2350 D1	3227 C3	3441 C2	7330 B1	
2351 D1	3228 B2	3442 B2	7333 B1	
2380 A2	3231 C1	3444 C2	7335 B1	
2381 A2	3232 C1	3446 C2	7337 B1	
2382 A2	3233 D1	3448 B2	7338 A1	
2383 A2	3234 D1	3450 A2	7350 D1	
2384 A2	3235 C1	3452 A2	7380 A2	
2385 A2	3236 D1	3454 B2	7381 A3	
2390 A1	3237 D1	3460 A1	7385 A3	
2391 A3	3238 C2	3461 A1	7387 A3	
2395 A3	3239 C2	3462 B2	7400 B3	
2397 A3	3240 C1	3463 B1	7402 B3	
2399 C1	3241 D1	3464 B1	7404 B3	
2400 A3	3242 C1	3465 A2	7406 B2	
2402 C3	3250 C1	3470 C1	7408 A2	

D1	7410 B1
D2	7755 B1
C3	9002 D2
B2	9003 D3
A1	9004 D3
C2	9007 C2
D1	9010 B1
D2	9011 B1
B1	9012 B1
B2	9013 B1
B2	9015 B3
A2	9016 B3
A2	9024 A2
A2	9025 B3
D1	9026 B3
D1	9027 A3
D1	9028 A3
B2	9029 A2
B2	9030 A3
B2	9031 A2
B1	9032 A2
A1	9033 A2
B1	9034 A2
B1	9035 A2
B1	9036 A2
C3	9037 A1
D1	9038 A1
C3	9039 A2
D3	9040 D2
D2	9041 B1
D2	9042 A2
D2	9043 B1
B3	9044 B1
C3	9045 C1
C3	9046 C3
B3	9050 C2
A2	P016 A1
A2	P017 C1
A1	P56 A2
B2	P57 A3
D1	
D1	
D3	
D2	
C2	
D2	
D1	
D1	
B1	
B1	
B1	
B1	
A1	
D1	
A2	
A3	
A3	
A3	
B3	
B3	
B3	
B2	
A2	



1155 C3	2404 B3	3265 C1	3997 D1	7410 B1
1201 D2	2405 B3	3270 C1	4001 D2	7755 B1
1212 D2	2409 B3	3275 C1	4002 C3	9002 D2
2103 D1	2410 B3	3276 C1	4003 B2	9003 D3
2105 D1	2413 C3	3330 B1	4004 A1	9004 D3
2118 D1	2414 B3	3331 A1	4005 C2	9007 C2
2119 D1	2415 B3	3332 A1	4006 D1	9010 B1
2120 D1	2430 B3	3333 B1	4007 D2	9011 B1
2125 C3	2432 B3	3334 B1	4010 B1	9012 B1
2155 C3	2434 B2	3335 B1	4011 B2	9013 B1
2158 D3	2438 B3	3336 B1	4012 B2	9015 B3
2160 C2	2439 A3	3337 B1	4047 A2	9016 B3
2161 C2	2440 B3	3338 A1	4048 A2	9024 A2
2162 C3	2441 B3	3339 B1	4049 A2	9025 B3
2163 C3	2442 B2	3340 B1	4100 D1	9026 B3
2171 D2	2444 C2	3341 A1	4200 D1	9027 A3
2172 D2	2446 B2	3345 C1	4201 D1	9028 A3
2176 D3	2448 A2	3353 D1	4401 B2	9029 A2
2177 D3	2449 B1	3354 D1	4402 B2	9030 A3
2180 D2	2450 B2	3380 A3	4403 B2	9031 A2
2181 D3	2451 B2	3381 A3	4404 B1	9032 A2
2185 C2	2454 B1	3382 A3	4406 A1	9033 A2
2187 D2	2455 B2	3383 A3	4407 B1	9034 A2
2189 D2	2459 B1	3384 A3	4410 B1	9035 A2
2196 C2	2466 B2	3385 A3	4411 B1	9036 A2
2197 C3	3103 D1	3386 A2	4415 C3	9037 A1
2201 D2	3104 D1	3387 A3	5118 D1	9038 A1
2202 C2	3105 D1	3388 A2	5155 C3	9039 A2
2211 D2	3106 D2	3390 A1	5157 D3	9040 D2
2212 D2	3107 D2	3391 A1	5170 D2	9041 B1
2220 C2	3108 D2	3394 A2	5175 D2	9042 A2
2222 C2	3155 C3	3395 A1	5190 D2	9043 B1
2227 B2	3156 C3	3398 A2	5400 B3	9044 B1
2230 C1	3157 D3	3399 A1	5402 C3	9045 C1
2232 C1	3158 D3	3404 C3	5403 C3	9046 C3
2234 C1	3170 D2	3405 B3	5404 B3	9050 C2
2235 C1	3175 D2	3410 B3	5406 A2	P016 A1
2238 C2	3195 C2	3411 B3	5408 A2	P017 C1
2239 C1	3196 C2	3412 B3	5410 A1	P56 A2
2250 C2	3200 D2	3413 B3	6300 B2	P57 A3
2251 C1	3201 D2	3414 B3	7103 D1	
2255 C1	3202 D2	3416 B3	7105 D1	
2260 C1	3211 D2	3434 B3	7125 D3	
2270 C2	3212 D2	3435 B3	7126 D2	
2330 B1	3214 C2	3436 B2	7200 C2	
2333 B1	3220 C2	3437 B2	7210 D2	
2340 A1	3221 C3	3438 B3	7233 D1	
2345 C1	3222 D2	3440 C2	7234 D1	
2350 D1	3227 C3	3441 C2	7330 B1	
2351 D1	3228 B2	3442 B2	7333 B1	
2380 A2	3231 C1	3444 C2	7335 B1	
2381 A2	3232 C1	3446 C2	7337 B1	
2382 A2	3233 D1	3448 B2	7338 A1	
2383 A2	3234 D1	3450 A2	7350 D1	
2384 A2	3235 C1	3452 A2	7380 A2	
2385 A2	3236 D1	3454 B2	7381 A3	
2390 A1	3237 D1	3460 A1	7385 A3	
2391 A3	3238 C2	3461 A1	7387 A3	
2395 A3	3239 C2	3462 B2	7400 B3	
2397 A3	3240 C1	3463 B1	7402 B3	
2399 C1	3241 D1	3464 B1	7404 B3	
2400 A3	3242 C1	3465 A2	7406 B2	
2402 C3	3250 C1	3470 C1	7408 A2	

①


②


③


④


⑤


⑥


⑦


⑧


⑨


⑩


11


12


13


⑭


⑮


⑯


⑰


⑱


⑲


⑳


㉑


㉒


23


㉔


ESV.00342
T12/030

PIP module / PIP-Modul / Module PIP



1023 PIP PANEL
K
PAL ONLY PIP
+12C
2162 100n
3155 390
2155 10n
5155 7µH2
3156 1k2
+12
1155 DL711
2158 10n
7126 TDA4510
2125 22n
2103 33p
3104
2118 680p
2119 150p
4100
5118 10µH3
2120 1n2
+12C
2161 2µ2
2160 1µ
PAL
G
8.86MHz
1201 8MHz
2202 2-22p
4005
2220 330n
2222 47n
3222
3220
3221
2196 100n
3200
3202
PAL 0V
NTSC 12V5
SECAM 12V5
2202 2-22p
1201 8,8MHZ
3201 10k
2201 1n
7200 BC848B
PAL 0V7
NTSC 0V
SECAM 0V
3212
PAL 12V5
NTSC 0V
SECAM 12V5
PAL 0V
NTSC 0V7
SECAM 0V
2212 2-22p
1212 7,2MHz
3211 10k
2211 1n
7210 BC848B
3105
2103 33p
3103
3104
2105 120p
2118 680p
2119 150p
PAL 0V
NTSC 2V3
SECAM 12V5
PAL 2V3
NTSC 0V
SECAM 12V5
5118 10µH3
2120 1n2
7105 BC848B
PAL 0V
NTSC 0V7
SECAM 0V
3106 10k
3107 10k
3108 10k
7103 BC848B
PAL 0V7
NTSC 0V
SECAM 0V
2125 22n
851
3155 390
2155 10n
5155 7µH2
3156 1k2
1155 DL711
861
5157 9µH4
2158 10n
2V6
2160 1µ
2161 2µ2
2162 100n
7125 TDA4554
10V2 13
6V2 14
8V2 12
3V5 15
SECAM
PAL
NTSC
16 8V5
27
28
25
26
TV
IDENT
BX
H
V
G
8.86MHz
+12C
3234 360
3233
7234 BC848B
8V8
7233 BC858B
9V3
CVBS
10 P17 3V3
2V6
1V
4200 RES
4201
3236
3237
3241
3 P17 F.BL
5 P17
+5
3470
8 P17
+13
7 P17
9 P17
3341 22
+12A
2340 47µ
3345 22
+12B
2345 47µ
3353 5E6
13V
7350 BC818-40
12V3
+12C
3354
2351 100µ
2350 330µ
3242 1k
PAL 0V
NTSC 6V1
SECAM 0V
PAL 0V5
NTSC 0V
SECAM 0V
PAL 5V1
NTSC 0V
SECAM 0V
20 6V
21 7V8
22 4V5
2185 22n
2187 22n
2189 1n
841
5190 10µH3
100p
19
18 8V4
17 3V2
2196 100n
3220
3221
3222
2220 330n
2222 47n


PAL
B–Y
R–Y
SECAM
PAL
NTSC
SECAM
REF
BK
H
V
G
5157
9µH4
3157
3158
75
330
2158
10n
2196
100n
2187
22n
2197
270p
3196
1k
5170
10µH3
5175
10µH3
841
861
3170
1k1
3175
620
2171
68p
2172
22p
2176
22p
2177
68p
2180
180p
2181
180p
+12C
3404
430
7400
BC858B
8V9
8V2
2V4
2405
10n
3405
360
2404
220p
+5
5400
12µH
2432
100n
2400
Res
+5H
5402
12µH
2434
100n
2402
Res
7406
SDA9087
5V4
3410
390
7402
BC858B
3V1
3411
470
2409
220p
2410
10n
3V2
3440
390
3441
51
2442
1µ
3V8
2V7
3442
91
3413
RES
3412
750
7404
BC858B
9V9
9V2
1V2
5404
33µH
3416
1k8
3414
470
2415
220p
2414
10n
2V8
Y
VSSA
4415
5403
100µH
2413
100p
2430
100n
–2V6
CL
A
D
M
VCO
0V9
1V
0V5
3435
RES
3434
47k
3437
100
3436
47k
0V
2V6
2V4
1V2
1V3
1V1
0V5
4V7
0V5
3227
7k5
3228
4k7
2227
330p
2441
220p
2440
100p
3231
6k8
3232
22
2230
1µ
2232
22µ
3235
1k2
2234
100n
2235
6µ8
3238
33k
2238
2n7
3239
4k7
7755
TDA2579A
8V4
7V4
2V8
4V4
2V5
3240
RES
2255
120p
7V1
2260
100n
0V
TV
IDENT
50Hz
15625Hz
+12B
3265
100k
13V
3V7
0V
3270
10k
2270
100n
3275
10k
3276
1k
1V2
11
13
① ③ ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩
11
12
13
14
15
16
17
18
19
20
21
22


22
23
24
25
26
27
28
29
30
31
32
33
F.BL
PIP
6
6P17
12
+12
+12
3335
270
3338
3k3
3336
4k3
12V5
7335
BC548B
7337
BC548B
5V4
F.BL
4010
1V4
3V9
4V
3337
1k2
3340
2k
+13
5V4
7338
BC848
4V8
3461
2k2
3460
820
+12A
2390
100n
7380
TEA5114
14
+5
+5
5406
12μH
5408
12μH
+5Va
2446
100n
2448
100n
D
3448
3k9
2V8
4
7408
SDA9088
5V4
28
5V4
3
0V
9
25
0V9
19
1V
20
0V5
21
0V9
22
13
DE-
MUX
U/V
INTERP
R
G
B
Y
-U
-V
D
A
5
0V
R
14
470
3454
6
0V
G
15
470
3452
7
0V
B
16
470
3450
8
0V
2V9
220k
2444
+5
+5
3435
RES
3434
47k
20
0V
3437
100
3436
47k
D
21
2V6
2V4
23
1V2
24
1V3
25
1V1
26
0V5
27
13
24
4V2
1
18
1V5
2
0V
10
4V2
11
0V
12
-1V4
13
1V5
16
3V7
17
3V9
14
15
G
G
I²C
10
20
21
16
+5H
2441
220p
2439
22n
3438
51k
2440
100p
2438
22n
+12B
22
23
24
4405
Res
+5b
2454
RES
2451
RES
3462
51k
2455
39p
2450
8n2
3444
100
3446
100
4k7
3239
+12B
13V
10
2239
100n
16
9V
3250
910
+12B
2250
270n
2251
1n
11
12
0V
3214
1k
17
1V2
9
10
9045
Res
3463
7k5
4k7
3464
6300
7V9
4403
4004
2399
1n
4407
7410
SDA9086/2
2V2
5
3V7
3
4V2
2
1V8
8
VCO
1
-2V7
4
5V4
6
7
2466
100n
+5b
5410
12μH
2449
100n
2459
100μ
D
D
D
D
+5
VPIP
4P17
4
VPIP
2P17
1P17
SDA
SCL
2
1
SDA
SCL
3V6
1
3V6
3
2381
220n
15
0V6
3V6
4
3V6
5
2383
220n
12
0V
8
9
0V6
3V6
6
3V6
7
2385
220n
10
0V
2
16
3V
13
3V
11
3V
17
18
19
2384
220n
2382
220n
2380
220n
D


K
26
27
28
29
30
31
32
33
34
35
A
B
C
D
E
F
G
H
I
J
K
L
M
N
O
F.BL
PIP
17
+12
+12
+13
3335
270
3338
3k3
5V4
7338
BC848
4V8
3336
4k3
12V5
7335
BC548B
7337
BC548B
5V4
F.BL
4010
1V4
4V
3V9
3337
1k2
3340
2k
3461
2k2
3460
820
+12A
2390
100n
7380
TEA5114
14
3448
3k9
2V8
4
3V6
1
16
3V
3390
150
P16
R
4
R
3391
180
(17)
3V6
2381
220n
3
15
0V6
5
0V
R
(14)
3454
470
D
3
3
3V6
4
13
3V
3394
150
G
2
2
G
3395
180
(18)
3V6
2383
220n
5
6
0V
G
(15)
3452
470
RGB
Y
-U
-V
12
9
0V6
F.BL
5
5
F.BL
0V
8
3V6
6
11
3V
3398
150
B
1
1
B
3399
180
(19)
3V6
2385
220n
7
10
7
0V
B
(16)
3450
470
A
I²C
8
0V
0V
2
16
3V7
17
3V9
14
15
2V9
220k
2444
+5b
2454
RES
2451
RES
3444
100
3446
100
3462
51k
2455
39p
2450
8n2
2384
220n
B
1P56
B
2382
220n
G
2P56
G
3P56
2380
220n
R
4P56
R
F.BL
5P56
F.BL
9045
Res
3463
7k5
3464
4k7
6300
7V9
4403
4004
4407
3V7
3
4V2
2
1V8
8
2399
1n
VCO
D
4
5V4
6
7
VPIP
SDA
SCL
2449
100n
2459
100µ
+5
D
D
D
4P17
2P17
1P17
4
2
1
VPIP
SDA
SCL
ESV.00324
T-26/048

1155	B10
1155	G10
1201	E9
1201	F3
1212	H3
2103	B4
2103	F3
2105	F5
2118	B5
2118	F5
2119	B6
2119	F6
2120	C6
2120	G6
2125	B6
2125	G8
2155	A8
2155	G8
2158	A11
2158	H11
2160	D7
2160	H7
2161	D6
2161	H7
2162	A8
2162	H8
2171	H12
2172	H13
2176	H13
2177	H14
2180	H15
2181	H15
2185	M7
2187	E12
2187	M7
2189	M8
2196	E11
2196	M11
2197	E13
2197	M12
2201	F1
2202	F2
2202	F9
2211	H2
2212	H2
2220	E9
2220	M9
2222	F9
2222	N9
2227	J20
2230	K17
2232	K19
2234	K20
2235	K20
2238	K21
2239	K24
2250	L24
2251	L24
2255	L17
2260	M16
2270	N19
2340	M3
2345	N3
2350	O3
2351	N5
2380	K32
2381	E32
2382	J32
2383	F32
2384	J32
2385	H32
2390	C33
2399	M28
2400	C20
2402	C21
2404	C19
2405	C18
2409	F18
2410	F19
2413	I 17
2414	H19
2415	H17
2430	I 19
2432	C19
2434	C20
2438	J23
2439	J23
2440	J22
2441	J22
2442	G19
2444	I 27
2446	D24
2448	D24
2449	O26
2450	J26
2451	I 26
2454	I 26
2455	J26
2459	O26
2466	O25
3103	F4
3104	B5
3104	F4
3105	F5
3106	H6
3107	H6
3108	I 6
3155	A8
3155	G8
3156	A8
3156	H8
3157	A12
3157	G12
3158	A11
3158	G11
3170	G12
3175	G14
3196	E14
3196	M12
3200	F1
3201	F1
3202	F1
3211	H1
3212	G2
3214	M24
3220	E10
3220	M10
3221	F10
3221	N10
3222	F9
3222	N9
3227	J19
3228	J20
3231	K18
3232	K18
3233	J3
3234	J3
3235	K20
3236	L3
3237	L3
3238	K21
3239	K22
3240	L16
3241	L4
3242	O6
3250	L24
3265	M17
3270	N19
3275	N21
3276	N21
3335	A26
3336	B27
3337	C26
3338	A27
3340	C27
3341	M3
3345	M3
3353	N3
3354	N3
3390	D34
3391	E34
3394	F34
3395	F34
3398	G34
3399	H34
3404	A18
3405	C18
3410	E18
3411	F17
3412	G17
3413	G17
3414	H17
3416	H16
3434	F22
3435	F22
3436	G22
3437	G22
3438	J23
3440	F19
3441	G18
3442	G19
3444	I 28
3446	J28
3448	D27
3450	H28
3452	F28
3454	E28
3460	C31
3461	B31
3462	J26
3463	K27
3464	L27
3470	L4
4004	M27
4005	F9
4010	B26
4100	C5
4200	K4
4201	K4
4403	M27
4405	I 25
4407	M26
4415	I 16
5118	C6
5118	G5
5155	A9
5155	G9
5157	A11
5157	G11
5170	G13
5175	G13
5190	N9
5400	B19
5402	B20
5403	I 16
5404	G16
5406	C24
5408	C24
5410	O25
6300	L28
7103	H4
7105	H5
7125	H7
7126	B7
7200	F2
7210	H2
7233	K4
7234	K3
7335	B26
7337	B27
7338	B29
7350	N4
7380	D32
7400	B18
7402	E18
7404	H17
7406	C19
7408	D23
7410	M25
7755	K16
9045	K26

Electrical settings

Setting conditions.

All electrical settings should be made under the following conditions:

- supply voltage: 220 - 240 V ± 10%; 50 Hz ± 5%
- warming-up time ≈ 10 minutes
- the voltages and oscillograms have been measured with regard to tuner earth.
- measuring probe: Ri > 10 MΩ; Ci < 2.5 pF.

1. Settings on the carrier board

1.1 +148V/+95V supply voltage

Connect a voltmeter over C2631.
Using R3635, set the supply voltage to +148V ± 0.5V for 25" and 28" units or to 95V ± 0.5V for 21" units.

1.2 Focusing

This is set using the focusing potentiometer (on the top of the line output transformer).

1.3 Vg2 setting

Connect a pattern generator and supply a blanking frame signal (black picture). Switch the unit to the service default mode (see section 9).
Connect an oscilloscope to the emitters of transistors 7304 and 7364 on the picture tube module. Set the oscilloscope to frame frequency. Measure the DC voltage level of the measuring pulses (see Fig. 7.2). Using the Vg2 potentiometer on the line output transformer, set the measuring pulse with the lowest DC voltage level to:

* +153V ± 5V for 25" and 28" blackline units (protected high-voltage cable)
* +130V ± 5V for 28" non-blackline units
* +118V ± 5V for 25" non-blackline units
* +120V ± 5V for 21" units.

1.4 Horizontal synchronization

Connect pin 5-IC7470 to pin 9-IC7470.
Supply an aerial signal and tune the set.
Adjust potentiometer 3457 until the picture is straight.
Remove the interconnection.

1.5 Horizontal centring

Set using potentiometer 3461.

1.6 Picture width

Set using potentiometer 3525.

1.7 Vertical centring

Set using potentiometer 3516.

1.8 Picture height

Set using potentiometer 3504.

1.9 East/West correction

Set using potentiometer 3521. This setting is only for 25" and 28" units.

1.10 Chroma bandpass filte

a. Setting for PAL/SECAM

Connect a signal generat
pin 20 of the euroconnec
frequency to 4.286 MHz/
to EXT1. Connect pin 27-
(+12V). Connect an oscill
Set 5301 to maximum am
Remove the interconnecti

b. Setting for PAL sets (TD

Connect a signal generat
pin 20 of the euroconnec
frequency to 4.43 MHz.
Connect an oscilloscope
Set 5301 to maximum am

1.11 Chroma auxiliary oscil

Connect a pattern genera
colour bar pattern. Conne
(TDA4510) or pin 17-IC7
Set 2313 so that the colo
practically stopped. Rem

1.12 SECAM demodulators (TDA4650)

Connect a pattern genera
black pattern. Connect a
pin 1-IC7306. Set 5304 t
Connect the oscilloscope
to minimum amplitude.

1.13 White balance

Connect a pattern genera
picture. Switch on the se
and select "WHITE BALA
Set the values of "GREE
required white balance is

1.14 Peak white limit

Switch on the service me
select "WHITE BALANCE
Set "WHITE LIMIT" to the

- 23 for blackline units
- 53 for non-blackline u
- 53 for 21" units.

1.15 Cut-off points of the

Connect a pattern gener
picture. Switch on the se
"CUT OFF". Switch on "D
Set "RED", "GREEN" and
respective guns give no

1.16 Options

Switch on the service me
or "OPTION 2".
Switch the options "ON"
whether the following op

- "PIP" on a PIP set
- "2ND SCART" on a se
- "TELETEXT" on a tele
- "AUTO STORE" for th
  in the installation men
- "SVHS" for the Y/C cc
- "MULTI SYSTEM" for
- "HYPERBAND" for a t
  to the frequency band
- "UHF ONLY" for a tun
  to the UHF band
- "NICAM TWIN" for ste
  receive NICAM sound

e

5%

=.

±
r 21"

n the

king
the

cy.
g
eter
ing

nly

1.10 Chroma bandpass filter

a. Setting for PAL/SECAM sets (TDA4650)
Connect a signal generator (e.g. PM 5326) to pin 20 of the euroconnector (EXT1) and set its frequency to 4.286 MHz/0.2 Vpp. Switch the unit to EXT1. Connect pin 27-IC7306 to pin 13-IC7306 (+12V). Connect an oscilloscope to pin 15-IC7306. Set 5301 to maximum amplitude.
Remove the interconnection.

b. Setting for PAL sets (TDA4510)
Connect a signal generator (e.g. PM 5326) to pin 20 of the euroconnector (EXT1) and set its frequency to 4.43 MHz. Connect the unit to EXT1. Connect an oscilloscope to pin 9-IC7305.
Set 5301 to maximum amplitude.

1.11 Chroma auxiliary oscillator

Connect a pattern generator and supply a PAL colour bar pattern. Connect pin 11-IC7305 (TDA4510) or pin 17-IC7306 (TDA4650) to earth. Set 2313 so that the colour on the screen has practically stopped. Remove the interconnection.

1.12 SECAM demodulators for PAL/SECAM sets (TDA4650)

Connect a pattern generator and supply a SECAM black pattern. Connect an oscilloscope to pin 1-IC7306. Set 5304 to minimum amplitude. Connect the oscilloscope to pin 3-IC7306. Set 3312 to minimum amplitude.

1.13 White balance

Connect a pattern generator and select a white picture. Switch on the service menu (see section 9) and select "WHITE BALANCE".
Set the values of "GREEN" and "BLUE" so that the required white balance is achieved.

1.14 Peak white limit

Switch on the service menu (see section 9) and select "WHITE BALANCE".
Set "WHITE LIMIT" to the value:
- 23 for blackline units
- 53 for non-blackline units
- 53 for 21" units.

1.15 Cut-off points of the picture tube

Connect a pattern generator and select a black picture. Switch on the service menu and select "CUT OFF". Switch on "DISABLE" ("ON").
Set "RED", "GREEN" and "BLUE" until the respective guns give no more light on the screen.

1.16 Options

Switch on the service menu and select "OPTION 1" or "OPTION 2".
Switch the options "ON" and "OFF" according to whether the following options are present:
- "PIP" on a PIP set
- "2ND SCART" on a set with two euroconnectors
- "TELETEXT" on a teletext set
- "AUTO STORE" for the automatic tuning facility in the installation menu
- "SVHS" for the Y/C connector in mono sets
- "MULTI SYSTEM" for multisystem sets
- "HYPERBAND" for a tuner which can be tuned to the frequency band of 300 MHz to 450 MHz
- "UHF ONLY" for a tuner which can only be tuned to the UHF band
- "NICAM TWIN" for stereo sets which can also receive NICAM sound.

2. Settings on the IF/sound module

2.1 AFC and the picture demodulator

a. Setting for multisystem units
Connect a signal generator (e.g. PM 5326) via a capacitor of 5p6 to pin 17 of the tuner and set its frequency to 33.4 MHz for mono sets or to 33.95 MHz for stereo sets. Modulate (AM) the signal with, for example, 1kHz.
Tune mono sets to VHF1 band at a tuning voltage of approximately 5V at pin 11 of the tuner. The "search" (selection B of the manual installation menu) can be stopped by selecting menu selection C "programme".
Set stereo sets to a tuning frequency of 45 MHz.
Select system France.
AFC: using 5036 set the voltage at pin 15-IC7000 to 6V (DC).
Picture demodulator: set 5035 to a maximum (undistorted) signal at pin 22-IC7000.
Then set the frequency of the signal generator to 38.9 MHz. Select system Europe on the set.
AFC: using 5038 set the voltage at pin 15-IC7000 to 6V (DC).
Picture demodulator: set 5037 to a maximum (undistorted) signal at pin 22-IC7000.
Adjacent channel suppression (mono sets):
Then set the frequency of the signal generator to 33.4 MHz. Place pin 9-IC7000 at a fixed voltage of +1V using a laboratory supply. Tune the set to the UHF band and select system France.
Set 5005 to a minimum signal at pin 22-IC7000.

b. Setting for single-system units
Connect a signal generator (e.g. PM 5326) via a capacitor of 5p6 to pin 17 of the tuner and set its frequency to 38.9 MHz. Modulate (AM) the signal with, for example, 1kHz.
AFC: using 5036 set the voltage at pin 15-IC7000 to 6V (DC).
Picture demodulator: set 5035 to a maximum (undistorted) signal at pin 22-IC7000.

2.2 RF-AGC

If the picture from a strong local transmitter is distorted, adjust 3016 until the picture is not distorted.

2.3 MF-AGC (Multisystem units)

Connect a pattern generator and supply a SECAM-L colour bar signal. Connect an oscilloscope to pin 22-IC7000. Set the amplitude of the video signal with 3048 to 1.7 Vpp for stereo units or to 1.8 Vpp for mono units.

2.4 AM-IF sound filter (Multisystem units)

Connect a signal generator (e.g. PM 5326) via a capacitor of 5p6 to pin 17 of the tuner and set its frequency to 30.9 MHz. Modulate (AM) the signal with 1kHz, for example. Tune the unit to UHF band and select system France. Connect an oscilloscope to pin 9-IC7100 and set 5100 to minimum amplitude.
Place pin 3-IC7100 on a fixed voltage of +2V using a laboratory supply.
Set the frequency of the generator to 32.4 MHz and set 5101 and 5102 to maximum amplitude.

e IF/sound module

ture demodulator
system units
enerator (e.g. PM 5326) via a
pin 17 of the tuner and set its
MHz for mono sets or to
reo sets. Modulate (AM) the
mple, 1kHz.
VHF1 band at a tuning voltage
V at pin 11 of the tuner. The
B of the manual installation
ped by selecting menu selection

a tuning frequency of 45 MHz.
nce.
et the voltage at pin 15-IC7000

tor: set 5035 to a maximum
l at pin 22-IC7000.
ency of the signal generator to
system Europe on the set.
et the voltage at pin 15-IC7000

tor: set 5037 to a maximum
l at pin 22-IC7000.
suppression (mono sets):
ency of the signal generator to
in 9-IC7000 at a fixed voltage of
atory supply. Tune the set to the
ect system France.
mum signal at pin 22-IC7000.

system units
enerator (e.g. PM 5326) via a
pin 17 of the tuner and set its
MHz. Modulate (AM) the signal
1kHz.
et the voltage at pin 15-IC7000

tor: set 5035 to a maximum
l at pin 22-IC7000.

a strong local transmitter is
16 until the picture is not

stem units)
generator and supply a
ar signal. Connect an
22-IC7000. Set the amplitude of
ith 3048 to 1.7 Vpp for stereo
for mono units.

er (Multisystem units)
enerator (e.g. PM 5326) via a
pin 17 of the tuner and set its
MHz. Modulate (AM) the signal
mple. Tune the unit to UHF band
France. Connect an oscilloscope
d set 5100 to minimum

on a fixed voltage of +2V using
y.
of the generator to 32.4 MHz
5102 to maximum amplitude.

2.5 IF sound demodulator (stereo and NICAM units)
Connect a signal generator (e.g. PM 5326) via a capacitor of 5p6 to pin 17 of the tuner and set its frequency to 38.9 MHz. Modulate (AM) the signal with 1kHz, for example. Connect an oscilloscope to pin 17-IC7100 (TDA3856) or pin 16-IC7101 (TDA3856) and set 5104 to minimum amplitude.

2.6 5.5 MHz or 6.0 MHz FM sound demodulator
Connect a pattern generator and supply a PAL signal with FM mono sound. Set 5105 (mono and stereo units) or 5102 (NICAM units) to maximum sound reproduction.

2.7 5.742 MHz FM sound demodulator (stereo and NICAM units)
Connect a pattern generator and supply a PAL BG signal with two-language sound. Select language II on the unit with the remote control.
Set 5103 (stereo units) or 5101 (NICAM units) to maximum sound reproduction.

2.8 Stereo matrix (stereo and NICAM units)
Connect a pattern generator and supply a PAL BG signal with stereo sound. Select only the right-hand channel sound. Set the balance of the unit completely to the left.
Set 3204 (stereo units) or 3200 (NICAM units) to minimum sound reproduction.

2.9 NICAM demodulator (NICAM units)
Connect a pattern generator and supply a PAL signal with NICAM sound. Connect the X-input of the oscilloscope to pin 19-IC7120. Connect the Y-input of the oscilloscope to pin 20-IC7120. Set the oscilloscope to the X-Y position. Set the sensitivity of the oscilloscope to 1V/div AC. Set the X and Y position so that the cross pattern is in the centre of the oscilloscope picture.
Set 2124 on a straight cross pattern (see fig. 7.3).

2.10 "Sample" clock oscillator (NICAM units)
Connect a pattern generator and supply a PAL signal with NICAM sound. Connect an oscilloscope to pin 9-IC7150. Set the sensitivity of the oscilloscope to 1V/div and the time base to 2µs/div.
Set 2155 so that a symmetrical block wave is visible.

3. Setting on the teletext

Connect pin 22-IC7830 to eart
frequency counter to pin 17-IC
6000 MHz ± 30kHz.
Remove the interconnection.

4. Settings on the PIP mo

Setting conditions
Before making each setting, e
picture with the prescribed sig
screen and that the unit has re
temperature (after ≈ 10 min.).

4.1 Horizontal synchronization
Do not supply an aerial or gen
Connect pin 28-IC7125 to pin 1
TDA4554 is present (PAL sele
5-IC7755 to earth.
Measure the frequency at pin
3239 set it to 15.625 Hz ± 25
Remove the interconnection.

4.2 Chroma bandpass filter
a. Setting for PIP modules wit
Connect a signal generator (e.
10 of P17 and set its frequenc
Vpp.
Connect pin 27-IC7125 to 13-I
oscilloscope to pin 15-IC7125.
Set 5118 to maximum amplitu
Remove the interconnection.
b. Setting for PIP modules with
Connect a signal generator (e.
10 of P17 and set its frequenc
4.43 MHz/0.2Vpp.
Connect an oscilloscope to pin
Set 5118 to maximum amplitu

4.3 PAL chroma auxiliary oscil
Connect a pattern generator a
colour bar pattern. Connect pi
(TDA4554) or pin 11-IC7126 (T
Set 2202 so that the colour of
practically still.
Remove the interconnection.

4.4 NTSC chroma auxiliary osc modules with TDA4554
Connect a pattern generator a
M colour bar pattern. Connect
earth. Set 2202 so that the col
is practically still.
Remove the interconnection.

3. Setting on the teletext decoder

Connect pin 22-IC7830 to earth. Connect a frequency counter to pin 17-IC7830 and set 5803 to 6000 MHz ± 30kHz.
Remove the interconnection.

4. Settings on the PIP module

Setting *conditions*
Before making each setting, ensure that a PIP picture with the prescribed signal is visible on the screen and that the unit has reached its operating temperature (after ≈ 10 min.).

4.1 Horizontal synchronization

Do not supply an aerial or generator signal.
Connect pin 28-IC7125 to pin 13-IC7125 if TDA4554 is present (PAL selection). Connect pin 5-IC7755 to earth.
Measure the frequency at pin 17-IC7755 and using 3239 set it to 15.625 Hz ± 25 Hz.
Remove the interconnection.

4.2 Chroma bandpass filter

a. Setting for PIP modules with TDA4554
Connect a signal generator (e.g. PM 5326) to pin 10 of P17 and set its frequency to 4.286 MHz/0.2 Vpp.
Connect pin 27-IC7125 to 13-IC7125. Connect an oscilloscope to pin 15-IC7125.
Set 5118 to maximum amplitude.
Remove the interconnection.

b. Setting for PIP modules with TDA4510
Connect a signal generator (e.g. PM 5326) to pin 10 of P17 and set its frequency to 4.43 MHz/0.2Vpp.
Connect an oscilloscope to pin 9-IC7126.
Set 5118 to maximum amplitude.

4.3 PAL chroma auxiliary oscillator

Connect a pattern generator and supply a PAL colour bar pattern. Connect pin 17-IC7125 (TDA4554) or pin 11-IC7126 (TDA4510) to earth.
Set 2202 so that the colour of the PIP picture is practically still.
Remove the interconnection.

4.4 NTSC chroma auxiliary oscillator for PIP modules with TDA4554

Connect a pattern generator and supply an NTSC M colour bar pattern. Connect pin 17-IC7125 to earth. Set 2202 so that the colour of the PIP picture is practically still.
Remove the interconnection.

4.5 Delay line

Connect a pattern generator and supply a PAL colour bar signal. Connect the X-input of the oscilloscope to pin 1-IC7125 (TDA4554) or pin 1-IC7126 (TDA4510). Connect the Y-input of the oscilloscope to pin 3-IC7125 (TDA4554) or pin 2-IC7126 (TDA4510). Set the oscilloscope to the X-Y position.
Set 5155 and 5157 so that the vectors lie in one line (points which are furthest from the origin).
Set the pattern generator to the "DEM" mode.
Set R3157 so that the vectors lie on top of one another in the origin.

4.6 SECAM identification for PIP modules with TDA4554

Connect a pattern generator and supply a SECAM colour bar signal.
Connect pin 27-IC7125 to pin 13-IC7125.
Connect an oscilloscope to pin 21-IC7125.
Set 5190 to minimum DC level.
Remove the interconnection.

4.7 SECAM demodulators for PIP modules with TDA4554

Connect a pattern generator and supply a SECAM signal without contents (black). Connect pin 27-IC7125 to pin 13-IC7125. Connect an oscilloscope to pin 1-IC7125. Using 5175, set the DC level during the scan equal to the DC level during the flyback.
In the same way set 5170, but now measure at pin 3-IC7125.
Remove the interconnection.



Fig. 7.1

PRS 06772
T~26/034



Fig. 7.2

MDA.01468
T28/826

MAIN PANEL


INSTALL
+
−
P+
P−
SK14
3312
7306
2313
8.86MHz
5304
7305
5301
1001
IF/SOUND
MODULE
1003
TXT
M17
M18
3635
+148
+95
5625
SOPS TRANSFORMER
3525
TV
3457
TV
3521
TV
3461
TV
1000
TUNER
5545
L.O.T
3516
TV
3504
TV


TXT
78
NIC
50
50
STE
MON

Fig. 7.3

PIP MODULE


5155
3157
5157
5175
7406
7126
7125
P56
7408
5170
3239
2202
2212
7380
5190
7410
7755
5118
P16
P17

TXT MODULE


7830
5803
7820
7810
7800
T7
T6

NICAM IF/SOUND MODULE


5103
5102
7100
5101
3200
2124
7120
2155
7150
3016
5036
7000
7160
7180
7168
7170
5035
7200
7213
M50
M51

STEREO IF/SOUND MODULE


3016
5104
3204
5105
5036
5035
7000
5039
7100
7101
5103
7200
5037
3048
7220
5100
5101
5102
M50
M51

MONO IF/SOUND MODULE


5036
5035
7101
7100
5039
3016
5100
5037
5102
7000
5105
3048
5005
5101
M50
M51

MDA 02965
T28/107

Fig. 7.3

Repair tips

1. Servicing of SMDs (Surface Mounted Devices)

1.1 General cautions on handling and storage

a. Oxidation on the terminals of SMDs results in poor soldering. Do not handle SMDs with bare hands.

b. Avoid using storage places that are sensitive to oxidation such as places with sulphur or chlorine gas, direct sunlight, high temperatures or a high degree of humidity.
The capacitance or resistance value of the SMDs may be affected by this.

c. Rough handling of circuit boards containing SMDs may cause damage to the components as well as the circuit boards. Circuit boards containing SMDs should never be bent or flexed. Different circuit board materials expand and contract at different rates when heated or cooled and the components and/or solder connections may be damaged due to the stress. Never rub or scrape chip components as this may cause the value of the component to change. Similarly, do not slide the circuit board across any surface.

1.2 Removal of SMDs

a. Heat the solder (for 2-3 seconds) at each terminal of the chip. By means of litz wire and a slight horizontal force, small components can be removed with the soldering iron. They can also be removed with a solder sucker (see Fig. 8.1A) or:

b. While holding the SMD with a pair of tweezers, take it off gently using the soldering iron's heat applied to each terminal (see Fig. 8.1B).

c. Remove the excess solder on the solder lands by means of litz wire or a solder sucker (see Fig. 8.1C).

Caution on removal:

a. When handling the soldering iron, use suitable pressure and be careful.

b. When removing the chip, do not use undue force with the pair of tweezers.

c. The soldering iron to be used (approx. 30 W) should preferably be equipped with a thermal control (soldering temperature: 225 to 250°C).

d. The chip, once removed, must never be reused.

1.3 Attachment of SMDs

a. Locate the SMD on the solder lands by means of tweezers and solder the component on one side. Ensure that the component is positioned correctly on the solder lands (see Fig. 8.2A).

b. Next complete the soldering of the terminals of the component (see Fig. 8.2B).

Caution when attaching SMDs:

a. When soldering the SMD terminals, do not touch them directly with the soldering iron. The soldering should be done as quickly as possible; care must be taken to avoid damage to the terminals of the SMDs themselves.

b. Keep the SMD's body in contact with the printed board when soldering.

c. The soldering iron to be used (approx. 30 W) should preferably be equipped with a thermal control (soldering temperature: 225 to 250°C).

d. Soldering should not be done outside the solder land.

e. Soldering flux (of rosin) may be used, but should not be acidic.

f. After soldering, let the SMD cool down gradually at room temperature.

g. The quantity of solder must be proportional to the size of the solder land. If the quantity is too great, the SMD might crack or the solder lands might be torn loose from the printed board (see Fig. 8.3).


DISMOUNTING
VACUUM PISTON
4822 395 10159
SOLDERING IRON
e.g. WELLER SOLDER TIP PT-H7
OR
A
SOLDERING IRON
SOLDER WICK
4822 321 40042
e.g. A PAIR OF TWEEZERS
B
HEATING
HEATING
SOLDERING IRON
C
SOLDER WICK
CLEANING
43 767 A11

Fig. 8.1


MOUNTING
e.g. A PAIR OF TWEEZERS
A
SOLDER
Ø 0.5 - 0.8 mm
SOLDERING IRON
PRESSURE
SOLDERING TIME
< 3 sec/side
SOLDER
Ø 0.5 - 0.8 mm
B
PRESSURE
SOLDERING IRON
43 768 A11

Fig. 8.2


EXAMPLES
RIGHT
SOLDERING IRON
NO!
43 769 A11

Fig. 8.3

2. Replacing the EEPROM IC7710

If the EEPROM has to be replaced during a repair, the microprocessor will load the EEPROM with a number of default values for the white balance, peak white limit and cut-off point settings. However, all these values should be checked and adjusted, if necessary.
All options should also be set, the programs installed and personal preference set.

3. Table of fault messages

Fault indication	Description	Possible fault
OSD: ER PIP	I²C fault PIP module	* +5 on PIP module * IC7406
OSD: ER TXT	I²C fault TXT module	* +5 on teletext module * IC7800
OSD: ER NICAM	I²C fault IC7160 (NICAM units)	* +5 on MF/sound module * IC7160, C2160, C2161, C2221, C2222 * IC7213
OSD: ER 8415	I²C fault IC7200 (stereo and NICAM units)	* +14 on MF/sound module * IC7200 * IC7220
OSD: ER 8425	I²C fault IC7213 (NICAM units) I²C fault IC7220 (Stereo units)	* IC7213/IC7220
OSD: ER EEPROM	I²C fault IC7710	* ICC7710
OSD: ER TUNER	I²C fault tuner (stereo and NICAM units)	* Tuner * TS7003
OSD: ER CHROMA	I²C fault IC7309	* supply IC7309 (+9) * IC7309
Flashing LED	Internal fault in µP	* IC7708
OSD: ER BUS	I²C bus blocked	* C2714, C2715

Directions for use

1. Service default mode

The GR2.1 is equipped with a service default mode. The service default mode is a fixed defined mode in which the unit can be placed.

1.1 Mode definition

The definition of the fixed mode in the service default mode is as follows:
- all sound and picture controls are in the central position (with the exception of the volume which is set to low)
- stereo units are tuned to 475.25 MHz
- mono units are tuned to programme 0
- system:
  - * PAL BG, PAL/SECAM BG or PAL I for single system units
  - * SECAM L for multisystem units.

1.2 Switching on and off

The service default mode is switched on by briefly short-circuiting the pins M33 and M34 (SERVICE) behind the INSTALL key on the carrier panel when switching the unit on with the mains switch. In order to indicate that the unit is in the service default mode, an "S" appears on the screen.
The service default mode can only be switched off by switching the unit to standby. If the unit is switched off and then on again using the mains switch or mains plug, the service default mode remains switched on.

1.3 Operation and extra facilities

In addition to the fact that the unit can be operated normally, in the service default mode two extra functions are available:
- Autostore
  When operating the install key on the local control panel, the unit is tuned to the next transmitter frequency. This frequency is also stored under the selected programme number. Therefore the installation menu cannot be accessed in the service default mode!
- Service menu
  The service menu is activated by first pressing the ⊿ key and then at the same time the P+ key on the local control panel. The service menu now appears on the screen.
  The service menu offers the facility to set various options and make a number of picture tube settings. The various components in the service menu are selected using the coloured keys on the remote control. The various components themselves are adjusted using the + and - keys on the remote control.
  The values and options set are immediately stored in the EEPROM.

Note 1:
If the service menu does not appear on the screen and the autostore function does not react, then the "LOCK" function is probably activated.
If the autostore function only does not react, the hotel mode is activated.

Note 2:
If a multisystem unit in the service default mode is to be used with the PAL/SECAM BG system, the "MULTI SYSTEM" option can be temporarily switched off.

2. Hotel mode

In the hotel mode the volume control is limited to a maximum to be set beforehand and the installation menu cannot be called up.

2.1 Switching the hotel mode on and off

Select programme number 38.
First press ⊿ + and keep this depressed while pressing P –.

Survey of menus

MAIN MENU STEREO


MENU ON/OFF
MAIN MENU
A PICTURE
B SOUND
C SPECIAL FEATURES
D CLOCK
PICTURE
A BRIGHTNESS
B COLOUR
C CONTRAST
SOUND
A BALANCE
B TREBLE
C BASS
D SOUND MODE
E SPATIAL SOUND
SPECIAL FEATURES
A LOCK
B DISPLAY PROG. NR
C PERS. PREFERENCE
D PIP SIZE
CLOCK
A SET CLOCK
B SWITCH-ON TIME
C PROGRAMME NUMBER
D ON/OFF
E SLEEPTIMER
MENU ON/OFF
MENU ON/OFF
MENU ON/OFF
MENU ON/OFF
PRS.06884
T-10 105

MAIN MENU MONO


MENU ON/OFF
MAIN MENU
A PICTURE
B SPECIAL FEATURES
PICTURE
A BRIGHTNESS
B COLOUR
C CONTRAST
SPECIAL FEATURES
A LOCK
B DISPLAY PROG. NR
C PERS. PREFERENCE
D PIP SIZE
MENU ON/OFF
MENU ON/OFF
PRS.06886
T-08 105

INSTALLATION MENU


INSTALL.
INSTALLATION
A LANGUAGE
B MANUAL STORE
C AUTO STORE
D SORT
MENU ON/OFF
A· ENGLISH/ENGLISH
B DEUTSCH/SUOMI
C FRANCAIS/DANSK
D ITALIANO/SVENSKA
E >>
A NEDERLANDS/NORSK
B PORTUGUES/ESPANOL
C >>
MENU ON/OFF
MANUAL STORE
A SYSTEM
B SEARCH
C PROGRAMME NUMBER
D STORE
MENU ON/OFF
SORT
A FROM
B TO
C STORE
MENU ON/OFF
PRS.06885
T-08 105

SERVICE MENU


-/P+
SERVICE
A OPTION 1
B OPTION 2
C WHITE BALANCE
D CUT-OFF
MENU ON/OFF
OPTION 1
A PIP
B 2ND SCART
C TELETEXT
D AUTO STORE
E SVHS
MENU ON/OFF
OPTION 2
A MULTY SYSTEM
B HYPERBAND
C UHF ONLY
D NICAMTWIN
MENU ON/OFF
WHITE BALANCE
A GREEN
B BLUE
C WHITE LIMIT
MENU ON/OFF
CUT-OFF
A RED
B GREEN
C BLUE
D DISABLE
MENU ON/OFF
PRS 06888
T-08 104

Spare parts lists / Stückliste / Liste

Carrier panel

Mechanical parts

4822 404 31174	bracket EURO MOD.
4822 492 70871	spring (wire)
4822 492 70143	spring fix. TS7625
4822 256 91766	LED holder
4822 276 50354	keyboard 5-fold
4822 466 30395	shielding IC7708
4822 256 30274	fuse holder
4822 320 20126	focus cable

●—

10	4822 265 30389	2p male
11	4822 265 30389	2p male
12	4822 265 30351	5p male
13	4822 265 30378	4p male
14	4822 290 40295	7p male
15	4822 265 40421	6p male
16	4822 264 40207	3p male
17	4822 267 50591	6p male gold
18	4822 264 50148	8p male gold
19	4822 264 40239	3p male
22	4822 267 40666	3p male
23	4822 264 40207	3p male
24	4822 264 40207	3p male
27	4822 265 30351	5p male
28	4822 265 30877	3p male
29	4822 265 41086	9p male,
35	4822 267 20387	SVHS-connector
39	4822 267 31014	headphone socket
47	4822 267 30631	dual cinch connector
49	4822 267 60243	EURO-connector

)—

4822 290 60626	2p female
4822 290 40285	3p female
4822 267 50824	4p female
4822 265 30275	5p female
4822 267 30546	6p female
4822 265 40252	7p female
4822 267 51084	9p female
4822 267 50637	10p female

various

1000	4822 210 10405	UV917E/IEC
1000	4822 212 23695	U943/IEC
1000	4822 210 50124	UV916E/IEC
1000	4822 210 10366	U944/IEC
1002	4822 526 10405	ferrite bead for D6640,D6641
1003	4822 212 23667	infra red receiver
1004	4822 526 10538	ferrite bead for D6546
1240	4822 071 51602	fuse T1,6A
1242	4822 071 51602	fuse T1,6A
1300	4822 242 70304	crystal 8,867 238 MHz
1534	4822 071 53151	fuse T315mA
1559	4822 071 51002	fuse T1A
1580	4822 071 51602	fuse T1,6A
1600	4822 070 32002	fuse T2A
1702	4822 242 80238	crystal 4,194 MHz
1702	4822 242 80221	crystal 4,194 304 MHz

⊣⊢

2001	4822 124 40195	150µF 20% 16V
2002	5322 122 32838	82nF 10% 63V
2002	4822 122 31797	22nF 10% 63V
2003	4822 122 31784	4,7nF 10% 50V
2003	4822 122 32893	100nF 80% 50V
2004	4822 122 33205	12pF 10% 63V
2008	4822 122 31765	100pF 5% 50V
2231	4822 124 41525	100µF 20% 25V
2232	4822 122 32863	22nF 80% 50V
2233	4822 122 32863	22nF 80% 50V
2234	4822 122 32863	22nF 80% 50V
2235	4822 122 32863	22nF 80% 50V
2236	4822 122 31784	4,7nF 10% 50V
2237	4822 122 32893	100nF 80% 50V
2238	4822 122 32597	6,8nF 10% 63V
2238	4822 122 31784	4,7nF 10% 50V
2239	4822 122 32893	100nF 80% 50V
2240	4822 124 40214	1000µF 20% 25V
2241	4822 122 32893	100nF 80% 50V
2242	4822 124 40214	1000µF 20% 25V
2243	4822 122 32863	22nF 80% 50V
2245	4822 122 32863	22nF 80% 50V
2246	4822 124 41596	22µF 20% 50V
2246	4822 124 41506	47µF 20% 16V
2248	4822 124 40849	330µF 20% 16V
2249	4822 122 32863	22nF 80% 50V
2250	4822 121 42472	10nF 10% 50V
2251	4822 121 42472	10nF 10% 50V
2252	4822 121 51252	470nF 5% 63V
2254	4822 121 51252	470nF 5% 63V
2255	4822 121 51252	470nF 5% 63V
2256	4822 122 32142	270pF 5% 63V
2257	4822 122 32142	270pF 5% 63V
2260	4822 122 32566	3,9nF 10% 63V
2261	4822 122 32566	3,9nF 10% 63V
2262	4822 122 32142	270pF 5% 63V
2263	4822 122 32142	270pF 5% 63V
2264	4822 121 51252	470nF 5% 63V
2265	4822 121 51252	470nF 5% 63V
2300	4822 122 32482	22pF 5% 63V
2301	4822 122 31773	560pF 5% 50V
2303	4822 122 32142	270pF 5% 63V
2304	4822 122 33498	2,7nF 10% 63V
2304	4822 122 31773	560pF 5% 50V
2305	4822 122 32444	33pF 5% 50V
2306	4822 122 31965	220pF 5% 63V
2307	4822 122 31965	220pF 5% 63V
2308	4822 122 32442	10nF 50V
2309	4822 122 32442	10nF 50V
2310	4822 122 32442	10nF 50V
2311	4822 122 33496	100nF 10% 63V
2312	4822 122 32442	10nF 50V
2313	4822 125 50045	20pF
2314	5322 121 42661	330nF 5% 63V
2315	4822 122 32504	15pF 5% 50V
2315	4822 122 33205	12pF 10% 63V
2316	4822 122 31825	27pF 10% 50V
2317	4822 122 33466	82pF 2%
2318	4822 122 32875	100pF 5% 50V
2319	4822 122 31825	27pF 10% 50V
2320	4822 122 32444	33pF 5% 50V
2320	4822 122 31839	82pF 10% 50V
2321	4822 122 31797	22nF 10% 63V
2322	4822 122 31797	22nF 10% 63V
2323	4822 122 32542	47nF 10% 63V
2325	4822 122 32542	47nF 10% 63V
2326	4822 051 10008	0Ω 5% 0,25W
2326	4822 122 33496	100nF 10% 63V
2327	4822 122 32442	10nF 50V
2328	4822 121 41856	22nF 5% 250V
2328	4822 121 42408	220nF 5% 63V
2329	4822 121 42408	220nF 5% 63V
2329	4822 121 41856	22nF 5% 250V
2330	4822 122 31765	100pF 5% 50V
2331	4822 122 31765	100pF 5% 50V
2332	5322 122 31842	330pF 5% 63V
2333	4822 121 42408	220nF 5% 63V
2334	4822 122 31965	220pF 5% 63V
2335	4822 122 31965	220pF 5% 63V
2336	4822 122 31797	22nF 10% 63V
2337	4822 122 31797	22nF 10% 63V
2338	4822 122 31797	22nF 10% 63V
2339	4822 122 33496	100nF 10% 63V
2340	4822 122 31797	22nF 10% 63V
2341	4822 122 31797	22nF 10% 63V
2342	4822 122 33496	100nF 10% 63V
2343	4822 122 33496	100nF 10% 63V
2344	4822 122 33496	100nF 10% 63V
2345	4822 122 31797	22nF 10% 63V
2346	4822 122 31765	100pF 5% 50V
2349	5322 122 31647	1nF 10% 63V
2350	4822 122 31797	22nF 10% 63V
2351	4822 122 31797	22nF 10% 63V
2352	5322 122 31647	1nF 10% 63V
2353	4822 122 33496	100nF 10% 63V
2354	4822 124 40242	1µF 20% 63V
2355	4822 124 40849	330µF 20% 16V
2356	4822 122 31797	22nF 10% 63V
2357	4822 122 31797	22nF 10% 63V
2358	4822 122 31797	22nF 10% 63V
2359	4822 122 31765	100pF 5% 50V
2360	4822 122 33496	100nF 10% 63V
2361	4822 122 33496	100nF 10% 63V
2362	4822 122 33496	100nF 10% 63V
2363	4822 122 31972	39pF 5% 50V
2365	4822 124 40242	1µF 20% 63V
2366	4822 124 41566	3,3µF 20% 50V
2367	4822 124 40435	10µF 20% 50V
2367	4822 124 41596	22µF 20% 50V
2368	4822 122 33205	12pF 10% 63V
2368	4822 122 32504	15pF 5% 50V
2370	4822 121 42408	220nF 5% 63V
2371	4822 122 31825	27pF 10% 50V
2372	4822 122 31825	27pF 10% 50V
2373	4822 122 31825	27pF 10% 50V
2374	4822 122 31772	47pF 5% 50V
2375	4822 122 31765	100pF 5% 50V
2376	4822 122 31765	100pF 5% 50V
2380	4822 122 31766	120pF 5% 50V
2381	4822 122 31766	120pF 5% 50V
2384	4822 122 31765	100pF 5% 50V
2384	4822 051 10008	0Ω 5% 0,25W
2385	4822 122 31765	100pF 5% 50V
2451	4822 122 32442	10nF 50V
2451	4822 122 33496	100nF 10% 63V
2456	4822 124 40242	1µF 20% 63V
2457	4822 122 33496	100nF 10% 63V
2458	4822 121 42937	2,7nF 1% 250V
2459	4822 122 33496	100nF 10% 63V
2460	5322 122 31647	1nF 10% 63V
2460	4822 122 31784	4,7nF 10% 50V
2460	4822 122 32442	10nF 50V
2461	5322 122 31647	1nF 10% 63V
2464	4822 122 33496	100nF 10% 63V
2465	4822 124 40849	330µF 20% 16V
2466	4822 124 41577	4,7µF 20% 50V
2467	4822 122 33496	100nF 10% 63V
2468	4822 124 40242	1µF 20% 63V
2469	4822 124 41596	22µF 20% 50V
2470	4822 122 31772	47pF 5% 50V
2471	5322 121 42661	330nF 5% 63V
2473	5322 121 42661	330nF 5% 63V
2475	4822 122 31797	22nF 10% 63V
2500	4822 122 31965	220pF 5% 63V
2500	4822 122 31727	470pF 5% 63V
2502	4822 124 41596	22µF 20% 50V
2505	4822 122 32542	47nF 10% 63V
2506	4822 124 41747	680µF 20%
2506	4822 124 41334	470µF 20% 35V

Carrier panel (continued)

2507	4822 122 31797	22nF 10% 63V
2509	4822 124 41576	2,2µF 20% 50V
2520	5322 124 41299	68µF 20% 25V
2521	4822 122 32891	68nF 10% 63V
2522	5322 121 42661	330nF 5% 63V
2524	4822 124 21208	4,7µF 20% 50V
2524	4822 124 42167	4,7µF 20% 50V
2526	4822 121 42472	10nF 10% 50V
2526	4822 122 31759	18nF 10%
2528	5322 121 42025	0,22µF 10% 250V
2531	4822 121 43396	120nF 5% 63V
2531	4822 121 42408	220nF 5% 63V
2532	4822 124 40242	1µF 20% 63V
2532	4822 124 41577	4,7µF 20% 50V
2533	4822 124 40242	1µF 20% 63V
2538	4822 121 51256	39nF 10% 50V
2539	4822 124 41525	100µF 20% 25V
2545	4822 126 10202	1,5nF 10% 2kV
2545	4822 122 33707	1,2nF 10% 2kV
2546	5322 121 42523	8,2nF 5% 2kV
2546	5322 121 41603	10nF 5% 2kV
2546	4822 121 43065	7,5nF 5% 2kV
2547	4822 121 40488	22nF 10% 400V
2547	5322 121 44151	33nF 10% 400V
2549	4822 121 42073	390 nF 10% 400V
2549	4822 121 42074	470 nF 10% 400V
2550	4822 121 51527	390nF 5% 250V
2550	4822 121 43148	470nF 10% 2000V
2551	4822 124 41831	1µF 20% 160V
2559	4822 124 41525	100µF 20% 25V
2560	4822 121 51408	33nF 10% 250V
2563	4822 122 10175	2,2nF 10% 50V
2570	4822 124 40764	22µF 100 V
2574	4822 122 10175	2,2nF 10% 50V
2580	4822 124 40214	1000µF 20% 25V
2585	4822 124 40435	10µF 20% 50V
2588	4822 122 31644	2,2nF 10% 63V
2590	5322 121 42498	680nF 5% 63V
2590	5322 121 42498	680nF 5% 63V
2600	4822 124 41531	470nF 10% 250VAC
2605	4822 124 23492	220µF 50% 385V
2605	4822 124 42104	68µF 20% 385V
2607	4822 122 33922	1nF 20% 400V
2611	5322 124 41299	68µF 20% 25V
2617	4822 121 43047	1µF 10% 63V
2620	5322 121 42465	68nF 5% 63V
2625	4822 122 40593	1nF 10% 1kV
2626	4822 122 40594	470pF 10% 1kV
2629	4822 122 31784	4,7nF 10% 50V
2630	4822 124 23418	47µF 200V
2630	4822 124 22349	100µF 160V
2631	4822 124 22349	100µF 160V
2631	4822 124 23418	47µF 200V
2632	4822 126 11382	1nF 10% 1kV
2636	4822 122 31644	2,2nF 10% 63V
2640	4822 124 40214	1000µF 20% 25V
2641	4822 124 40214	1000µF 20% 25V
2646	4822 124 42153	15µF 20% 50V
2649	4822 122 33496	100nF 10% 63V
2650	4822 122 33496	100nF 10% 63V
2652	5322 122 32331	1nF 10% 100V
2653	5322 122 32331	1nF 10% 100V
2658	5322 122 32838	82nF 10% 63V
2660	4822 124 40201	1000µF 20% 16V
2661	4822 124 41506	47µF 20% 16V
2662	4822 122 30107	270pF 2% 100V
2662	5322 122 32056	220pF 2% 100V
2663	5322 122 32344	82pF 2% 100V
2663	4822 122 31081	100pF 2% 100V
2664	4822 124 41576	2,2µF 20% 50V
2670	4822 122 31766	120pF 5% 50V
2671	4822 121 42408	220nF 5% 63V
2675	5322 124 41468	1000µF 20% 40V
2675	4822 124 21215	680µF 20% 40V
2676	5322 122 32331	1nF 10% 100V
2701	4822 122 31765	100pF 5% 50V
2702	4822 122 32442	10nF 50V
2703	4822 121 51252	470nF 5% 63V
2704	4822 122 32542	47nF 10% 63V
2705	4822 122 31766	120pF 5% 50V
2706	5322 124 41299	68µF 20% 25V
2707	4822 124 40242	1µF 20% 63V
2708	4822 122 31766	120pF 5% 50V
2709	4822 122 32083	8,2pF 5% 50V
2710	4822 122 32083	8,2pF 5% 50V
2711	4822 122 31825	27pF 10% 50V
2712	4822 122 31825	27pF 10% 50V
2713	4822 124 41525	100µF 20% 25V
2714	4822 122 31766	120pF 5% 50V
2715	4822 122 31766	120pF 5% 50V
2716	4822 122 33496	100nF 10% 63V
2717	4822 122 31644	2,2nF 10% 63V
2718	4822 122 33496	100nF 10% 63V
2719	4822 124 40242	1µF 20% 63V
2719	5322 121 42386	100nF 5% 63V
2721	4822 122 32442	10nF 50V
2722	4822 121 42007	100nF 10% 100V
2722	4822 122 32893	100nF 80% 50V
2781	4822 122 33496	100nF 10% 63V
2800	4822 124 41506	47µF 20% 16V
2805	4822 122 31772	47pF 5% 50V
2810	4822 122 31784	4,7nF 10% 50V
2875	4822 122 32893	100nF 80% 50V

3001	4822 052 10279	27Ω 5% 0,33W
3002	4822 051 10223	22k 2% 0,25W
3003	4822 051 20222	2k2 5% 0,1W
3004	4822 051 10472	4k7 2% 0,25W
3005	4822 051 10102	1k 2% 0,25W
3006	4822 051 10472	4k7 2% 0,25W
3007	4822 051 10102	1k 2% 0,25W
3008	4822 051 10472	4k7 2% 0,25W
3009	4822 051 10102	1k 2% 0,25W
3010	4822 051 10102	1k 2% 0,25W
3218	4822 116 52228	680Ω 5% 0,5W
3219	4822 116 52228	680Ω 5% 0,5W
3220	4822 051 10392	3k9 2% 0,25W
3221	4822 116 52204	1k 5% 0,5W
3222	4822 116 52234	100k 5% 0,5W
3224	4822 116 52256	2k2 5% 0,5W
3225	4822 051 10272	2k7 2% 0,25W
3226	4822 051 10333	33k 2% 0,25W
3227	4822 051 10333	33k 2% 0,25W
3228	4822 051 10151	150Ω 2% 0,25W
3229	4822 051 10562	5k6 2% 0,25W
3230	4822 116 52257	22k 5% 0,5W
3231	4822 051 10472	4k7 2% 0,25W
3232	4822 051 10101	100Ω 2% 0,25W
3232	4822 051 10008	0Ω 5% 0,25W
3233	4822 051 10103	10k 2% 0,25W
3234	4822 051 10223	22k 2% 0,25W
3235	4822 051 10223	22k 2% 0,25W
3236	4822 051 10562	5k6 2% 0,25W
3236	4822 051 10122	1k2 2% 0,25W
3237	4822 051 10562	5k6 2% 0,25W
3237	4822 051 10122	1k2 2% 0,25W
3238	4822 051 10122	1k2 2% 0,25W
3239	4822 116 52207	1k2 5% 0,5W
3240	4822 052 10828	8Ω2 5% 0,33W
3241	4822 052 10828	8Ω2 5% 0,33W
3242	4822 051 10333	33k 2% 0,25W
3243	4822 051 10333	33k 2% 0,25W
3244	4822 051 10103	10k 2% 0,25W
3245	4822 051 10103	10k 2% 0,25W
3246	4822 050 23301	330Ω 1% 0,6W
3247	4822 116 52175	100Ω 5% 0,5W
3248	4822 050 23301	330Ω 1% 0,6W
3249	4822 116 52193	39Ω 5% 0,5W
3249	4822 116 52175	100Ω 5% 0,5W
3250	4822 116 52204	1k 5% 0,5W
3251	4822 116 52204	1k 5% 0,5W
3253	4822 116 52211	150Ω 5% 0,5W
3254	4822 116 52211	150Ω 5% 0,5W
3255	4822 116 52204	1k 5% 0,5W
3256	4822 116 52204	1k 5% 0,5W
3257	4822 051 10334	330k 2% 0,25W
3258	4822 051 10334	330k 2% 0,25W
3259	4822 051 10334	330k 2% 0,25W
3260	4822 051 10334	330k 2% 0,25W
3261	4822 116 80747	75Ω 5% 0,125W
3262	4822 116 80747	75Ω 5% 0,125W
3263	4822 051 10008	0Ω 5% 0,25W
3263	4822 051 10562	5k6 2% 0,25W
3264	4822 051 10008	0Ω 5% 0,25W
3264	4822 051 10562	5k6 2% 0,25W
3265	4822 050 21008	1Ω 1% 0,6W
3266	4822 050 21008	1Ω 1% 0,6W
3300	4822 051 10562	5k6 2% 0,25W
3301	4822 051 10272	2k7 2% 0,25W
3302	4822 051 20222	2k2 5% 0,1W
3303	4822 051 10332	3k3 2% 0,25W
3303	4822 051 10122	1k2 2% 0,25W
3304	4822 051 10182	1k8 2% 0,25W
3305	4822 051 10431	430Ω 2% 0,25W
3306	4822 051 10103	10k 2% 0,25W
3307	4822 051 10681	680Ω 2% 0,25W
3308	4822 051 10331	330Ω 2% 0,25W
3309	4822 051 10331	330Ω 2% 0,25W
3310	4822 116 52286	5k1 5% 0,5W
3311	4822 051 10391	390Ω 2% 0,25W
3312	4822 100 11677	470Ω 30% lin 0,2W
3313	4822 051 10103	10k 2% 0,25W
3313	4822 051 10332	3k3 2% 0,25W
3314	4822 051 10103	10k 2% 0,25W
3315	4822 051 10911	910Ω 2% 0,25W
3316	4822 051 10105	1M 5% 0,25W
3317	4822 051 20222	2k2 5% 0,1W
3318	4822 051 10472	4k7 2% 0,25W
3323	4822 116 52272	330k 5% 0,5W
3325	4822 051 10271	270Ω 2% 0,25W
3326	4822 051 10271	270Ω 2% 0,25W
3327	4822 050 11202	1k2 1% 0,4W
3328	4822 051 10473	47k 2% 0,25W
3330	4822 051 10109	10Ω 2% 0,25W
3331	4822 051 10109	10Ω 2% 0,25W
3332	4822 050 23901	390Ω 1% 0,6W
3334	4822 050 21809	18Ω 1% 0,6W
3335	4822 116 52184	18Ω 5% 0,5W
3336	4822 052 10189	18Ω 5% 0,33W
3336	4822 052 10279	27Ω 5% 0,33W
3337	4822 052 10189	18Ω 5% 0,33W
3337	4822 052 10279	27Ω 5% 0,33W
3338	4822 116 52204	1k 5% 0,5W
3339	4822 051 10152	1k5 2% 0,25W
3340	4822 116 52204	1k 5% 0,5W
3341	4822 051 10103	10k 2% 0,25W
3342	4822 051 10102	1k 2% 0,25W
3343	4822 051 10104	100k 2% 0,25W
3344	4822 051 10182	1k8 2% 0,25W
3347	4822 116 52219	330Ω 5% 0,5W
3348	4822 116 52219	330Ω 5% 0,5W
3349	4822 116 52219	330Ω 5% 0,5W
3350	4822 116 52204	1k 5% 0,5W
3351	4822 116 52263	2k7 5% 0,5W
3352	4822 116 52263	2k7 5% 0,5W
3353	4822 116 52263	2k7 5% 0,5W

Carrier panel (continued)

3354	4822 051 10221	220Ω 2% 0,25W
3357	4822 051 10102	1k 2% 0,25W
3358	4822 051 10331	330Ω 2% 0,25W
3359	4822 051 10331	330Ω 2% 0,25W
3360	4822 051 10102	1k 2% 0,25W
3361	4822 051 10102	1k 2% 0,25W
3362	4822 051 10472	4k7 2% 0,25W
3365	4822 116 52245	150k 5% 0,5W
3365	4822 116 52301	75k 5% 0,5W
3366	4822 051 20183	18k 5% 0,1W
3367	4822 116 52175	100Ω 5% 0,5W
3368	4822 116 52175	100Ω 5% 0,5W
3369	4822 116 52175	100Ω 5% 0,5W
3370	4822 051 10332	3k3 2% 0,25W
3371	4822 051 10332	3k3 2% 0,25W
3372	4822 051 10472	4k7 2% 0,25W
3373	4822 051 10102	1k 2% 0,25W
3374	4822 050 26803	68k 1% 0,6W
3375	4822 051 10331	330Ω 2% 0,25W
3376	4822 051 10331	330Ω 2% 0,25W
3380	4822 051 10101	100Ω 2% 0,25W
3381	4822 051 10101	100Ω 2% 0,25W
3394	4822 051 10104	100k 2% 0,25W
3395	4822 051 10683	68k 2% 0,25W
3450	4822 116 52238	12k 5% 0,5W
3451	4822 116 52175	100Ω 5% 0,5W
3452	4822 116 52175	100Ω 5% 0,5W
3455	4822 051 10102	1k 2% 0,25W
3456	4822 051 10682	6k8 2% 0,25W
3457	4822 100 11676	10k 30% lin 0,2W
3458	4822 051 10303	30k 2% 0,25W
3459	4822 051 10823	82k 2% 0,25W
3460	4822 051 10333	33k 2% 0,25W
3461	4822 100 11682	47k 30% lin 0,2W
3463	4822 051 20183	18k 5% 0,1W
3464	4822 051 10123	12k 2% 0,25W
3465	4822 051 10394	390k 2% 0,25W
3466	4822 051 10152	1k5 2% 0,25W
3467	4822 116 80692	2M2 5% 0,2W
3467	4822 050 21205	1M2 1% 0,6W
3468	4822 051 10682	6k8 2% 0,25W
3469	4822 051 10229	22Ω 2% 0,25W
3470	4822 116 52269	3k3 5% 0,5W
3471	4822 050 19109	91Ω 1% 0,4W
3473	4822 116 52265	270k 5% 0,5W
3474	4822 051 10392	3k9 2% 0,25W
3483	4822 051 10479	47Ω 2% 0,25W
3485	4822 051 20222	2k2 5% 0,1W
3501	4822 051 10759	75Ω 2% 0,25W
3501	4822 051 10101	100Ω 2% 0,25W
3502	4822 050 28201	820Ω 1% 0,6W
3503	4822 052 10108	1Ω 5% 0,33W
3504	4822 100 11684	100Ω 10% 0,1W
3505	4822 051 10471	470Ω 2% 0,25W
3506	4822 116 52245	150k 5% 0,5W
3507	4822 116 52233	10k 5% 0,5W
3507	4822 116 52238	12k 5% 0,5W
3508	4822 051 10228	2Ω2 5% 0,25W
3509	4822 051 10228	2Ω2 5% 0,25W
3510	4822 051 10228	2Ω2 5% 0,25W
3511	4822 051 10228	2Ω2 5% 0,25W
3512	4822 051 10109	10Ω 2% 0,25W
3513	4822 050 25601	560Ω 1% 0,6W
3514	4822 051 10392	3k9 2% 0,25W
3515	4822 051 10228	2Ω2 5% 0,25W
3516	4822 100 11678	22k 30% lin 0,2W
3517	4822 051 10228	2Ω2 5% 0,25W
3518	4822 051 10101	100Ω 2% 0,25W
3519	4822 051 10228	2Ω2 5% 0,25W
3520	4822 116 52211	150Ω 5% 0,5W
3521	4822 100 11679	4,7k 30% lin 0,2W
3522	4822 051 10152	1k5 2% 0,25W
3523	4822 051 10228	2Ω2 5% 0,25W

3524	4822 051 10683	68k 2% 0,25W
3525	4822 100 11678	22k 30% lin 0,2W
3525	4822 100 11676	10k 30% lin 0,2W
3526	4822 051 10823	82k 2% 0,25W
3526	4822 051 10104	100k 2% 0,25W
3527	4822 051 10125	1M2 5% 0,25W
3527	4822 051 10333	33k 2% 0,25W
3528	4822 051 20222	2k2 5% 0,1W
3528	4822 051 10681	680Ω 2% 0,25W
3529	4822 051 10228	2Ω2 5% 0,25W
3530	4822 051 10102	1k 2% 0,25W
3530	4822 051 10008	0Ω 5% 0,25W
3531	4822 051 10104	100k 2% 0,25W
3531	4822 051 10008	0Ω 5% 0,25W
3532	4822 051 10103	10k 2% 0,25W
3532	4822 051 10153	15k 2% 0,25W
3533	4822 051 10822	8k2 2% 0,25W
3534	4822 052 10828	8Ω2 5% 0,33W
3535	4822 116 52231	820Ω 5% 0,5W
3535	4822 116 52243	1k5 5% 0,5W
3536	4822 051 10822	8k2 2% 0,25W
3538	4822 116 52251	18k 5% 0,5W
3539	4822 053 20684	680k 5% 0,25W
3539	4822 053 20434	430k 5% 0,25W
3540	4822 051 10399	39Ω 2% 0,25W
3542	4822 050 28201	820Ω 1% 0,6W
3543	4822 051 10101	100Ω 2% 0,25W
3545	4822 116 52256	2k2 5% 0,5W
3545	4822 111 70178	120Ω 5% 5W
3545	4822 116 82999	330Ω 5% 5W
3546	4822 050 15608	5Ω6 1% 0,4W
3549	4822 116 52251	18k 5% 0,5W
3550	4822 052 10153	15k 5% 0,33W
3550	4822 116 52251	18k 5% 0,5W
3551	4822 050 25601	560Ω 1% 0,6W
3552	4822 050 25601	560Ω 1% 0,6W
3553	4822 052 10561	560Ω 5% 0,33W
3560	4822 116 52254	20k 5% 0,5W
3560	4822 116 52247	16k 5% 0,5W
3560	4822 051 10333	33k 2% 0,25W
3570	4822 052 10688	6Ω8 5 0,33W
3582	4822 050 25601	560Ω 1% 0,6W
3585	4822 052 10159	15Ω 5% 0,33W
3588	4822 052 10561	560Ω 5% 0,33W
3589	4822 050 24701	470Ω 1% 0,6W
3590	4822 116 52234	100k 5% 0,5W
3591	4822 051 10474	470k 2% 0,25W
3592	4822 051 10681	680Ω 2% 0,25W
3603	4822 053 21915	9M1 5% 0,5W
3605	4822 052 10102	1k 5% 0,33W
3606	4822 052 10102	1k 5% 0,33W
3610	4822 052 10159	15Ω 5% 0,33W
3610	4822 052 10688	6Ω8 5 0,33W
3617	4822 116 52213	180Ω 5% 0,5W
3619	4822 116 52182	15Ω 5% 0,5W
3620	4822 053 12121	120Ω 5% 3W
3622	4822 053 11479	47Ω 5% 2W
3624	4822 116 52272	330k 5% 0,5W
3625	4822 116 52292	560k 5% 0,5W
3626	4822 053 12361	360Ω 5% 3W
3626	4822 113 80565	180Ω 5% 5W
3627	4822 053 12361	360Ω 5% 3W
3628	4822 051 10334	330k 2% 0,25W
3629	4822 051 10682	6k8 2% 0,25W
3631	4822 050 22204	220k 1% 0,6W
3631	4822 050 21204	120k 1% 0,6W
3634	4822 116 52269	3k3 5% 0,5W
3634	4822 116 52263	2k7 5% 0,5W
3635	4822 100 11681	1k 30% 0,1W
3636	4822 051 10224	220k 2% 0,25W
3637	4822 051 10101	100Ω 2% 0,25W
3647	4822 050 23603	36k 1% 0,6W
3647	4822 050 23303	33k 1% 0,6W

3648	4822 051 10273	27k 2% 0,25W
3649	4822 050 23309	33Ω 1% 0,6W
3658	4822 052 10688	6Ω8 5 0,33W
3659	4822 051 10181	180Ω 2% 0,25W
3660	4822 051 10101	100Ω 2% 0,25W
3661	4822 051 10361	360Ω 2% 0,25W
3662	4822 051 10221	220Ω 2% 0,25W
3663	4822 051 10472	4k7 2% 0,25W
3664	4822 051 10272	2k7 2% 0,25W
3665	4822 051 10103	10k 2% 0,25W
3666	4822 051 10102	1k 2% 0,25W
3667	4822 051 10361	360Ω 2% 0,25W
3668	4822 051 10102	1k 2% 0,25W
3669	4822 051 10102	1k 2% 0,25W
3670	4822 051 10303	30k 2% 0,25W
3671	4822 116 52204	1k 5% 0,5W
3672	4822 051 10103	10k 2% 0,25W
3673	4822 051 10472	4k7 2% 0,25W
3674	4822 051 10112	1k1 2% 0,25W
3675	4822 116 52239	120k 5% 0,5W
3676	4822 051 10103	10k 2% 0,25W
3701	4822 051 10273	27k 2% 0,25W
3702	4822 051 10153	15k 2% 0,25W
3704	4822 051 10103	10k 2% 0,25W
3705	4822 051 10102	1k 2% 0,25W
3706	4822 051 10472	4k7 2% 0,25W
3707	4822 051 10223	22k 2% 0,25W
3708	4822 051 10334	330k 2% 0,25W
3710	4822 051 10008	0Ω 5% 0,25W
3710	4822 051 10243	24k 2% 0,25W
3711	4822 116 52244	15k 5% 0,5W
3711	4822 116 80176	1Ω 5% 0,5W
3712	4822 051 10223	22k 2% 0,25W
3712	4822 051 10008	0Ω 5% 0,25W
3713	4822 051 10223	22k 2% 0,25W
3713	4822 051 10008	0Ω 5% 0,25W
3714	4822 051 10155	1M5 5% 0,25W
3716	4822 051 10103	10k 2% 0,25W
3717	4822 051 10103	10k 2% 0,25W
3718	4822 116 52215	220Ω 5% 0,5W
3719	4822 116 52215	220Ω 5% 0,5W
3720	4822 116 52215	220Ω 5% 0,5W
3721	4822 051 10103	10k 2% 0,25W
3722	4822 051 10103	10k 2% 0,25W
3723	4822 051 10103	10k 2% 0,25W
3724	4822 051 10103	10k 2% 0,25W
3725	4822 051 10103	10k 2% 0,25W
3726	4822 051 10103	10k 2% 0,25W
3727	4822 116 52175	100Ω 5% 0,5W
3728	4822 116 52175	100Ω 5% 0,5W
3729	4822 051 10911	910Ω 2% 0,25W
3730	4822 051 10221	220Ω 2% 0,25W
3731	4822 051 10103	10k 2% 0,25W
3732	4822 053 11103	10k 5% 2W
3732	4822 053 11332	3k3 5% 2W
3733	4822 116 52283	4k7 5% 0,5W
3733	4822 050 23902	3k9 1% 0,6W
3734	4822 116 52283	4k7 5% 0,5W
3734	4822 050 23902	3k9 1% 0,6W
3735	4822 051 10104	100k 2% 0,25W
3736	4822 116 52175	100Ω 5% 0,5W
3737	4822 116 52284	47k 5% 0,5W
3737	4822 116 52204	1k 5% 0,5W
3741	4822 051 10123	12k 2% 0,25W
3742	4822 051 10332	3k3 2% 0,25W
3743	4822 051 10472	4k7 2% 0,25W
3747	4822 051 10273	27k 2% 0,25W
3748	4822 051 10273	27k 2% 0,25W
3749	4822 051 10273	27k 2% 0,25W
3750	4822 051 10273	27k 2% 0,25W
3751	4822 051 10153	15k 2% 0,25W
3752	4822 051 10153	15k 2% 0,25W
3753	4822 051 10153	15k 2% 0,25W

Carrier panel (continued)

3754	4822 051 10153	15k 2% 0,25W
3755	4822 051 10008	0Ω 5% 0,25W
3755	4822 051 10101	100Ω 2% 0,25W
3756	4822 051 10101	100Ω 2% 0,25W
3757	4822 051 20222	2k2 5% 0,1W
3758	4822 051 10392	3k9 2% 0,25W
3759	4822 116 52175	100Ω 5% 0,5W
3768	4822 116 52235	1M 5% 0,5W
3770	4822 051 10473	47k 2% 0,25W
3771	4822 116 52251	18k 5% 0,5W
3772	4822 051 10392	3k9 2% 0,25W
3774	4822 051 10103	10k 2% 0,25W
3775	4822 051 10101	100Ω 2% 0,25W
3776	4822 051 10562	5k6 2% 0,25W
3777	4822 116 52264	27k 5% 0,5W
3778	4822 051 10563	56k 2% 0,25W
3779	4822 116 52233	10k 5% 0,5W
3780	4822 051 10103	10k 2% 0,25W
3781	4822 051 10472	4k7 2% 0,25W
3850	4822 116 52189	30Ω 5% 0,5W
3851	4822 116 80747	75Ω 5% 0,125W
3852	4822 116 80747	75Ω 5% 0,125W
3853	4822 116 80747	75Ω 5% 0,125W
3854	4822 116 80747	75Ω 5% 0,125W
3855	4822 116 52201	75Ω 5% 0,5W
3856	4822 051 10101	100Ω 2% 0,25W
3857	4822 051 10331	330Ω 2% 0,25W
3858	4822 051 10331	330Ω 2% 0,25W
3859	4822 051 10331	330Ω 2% 0,25W
3860	4822 116 80176	1Ω 5% 0,5W
3861	4822 051 10562	5k6 2% 0,25W
3866	4822 051 10103	10k 2% 0,25W
3867	4822 116 80747	75Ω 5% 0,125W
3868	4822 116 80747	75Ω 5% 0,125W
3869	4822 116 52175	100Ω 5% 0,5W
3871	4822 116 52175	100Ω 5% 0,5W
3874	4822 050 21008	1Ω 1% 0,6W
3875	4822 051 10102	1k 2% 0,25W
3880	4822 116 52204	1k 5% 0,5W
3881	4822 116 52224	470Ω 5% 0,5W
3882	4822 116 52224	470Ω 5% 0,5W
3883	4822 051 10104	100k 2% 0,25W
3884	4822 050 21004	100k 1% 0,6W
3885	4822 051 10223	22k 2% 0,25W
3886	4822 051 10472	4k7 2% 0,25W
3887	4822 116 52289	5k6 5% 0,5W
3888	4822 116 52207	1k2 5% 0,5W
3890	4822 051 10103	10k 2% 0,25W
4221	4822 051 10008	0Ω 5% 0,25W
4222	4822 051 10008	0Ω 5% 0,25W
4223	4822 051 10008	0Ω 5% 0,25W
4224	4822 051 10008	0Ω 5% 0,25W
4233	4822 051 10008	0Ω 5% 0,25W
4237	4822 051 10008	0Ω 5% 0,25W
4239	4822 051 10008	0Ω 5% 0,25W
4300	4822 051 10008	0Ω 5% 0,25W
4301	4822 051 10008	0Ω 5% 0,25W
4302	4822 051 10008	0Ω 5% 0,25W
4303	4822 051 10008	0Ω 5% 0,25W
4304	4822 051 10008	0Ω 5% 0,25W
4305	4822 051 10008	0Ω 5% 0,25W
4306	4822 051 10008	0Ω 5% 0,25W
4307	4822 051 10008	0Ω 5% 0,25W
4308	4822 051 10008	0Ω 5% 0,25W
4310	4822 051 10008	0Ω 5% 0,25W
4312	4822 051 10008	0Ω 5% 0,25W
4314	4822 051 10008	0Ω 5% 0,25W
4315	4822 051 10008	0Ω 5% 0,25W
4316	4822 051 10008	0Ω 5% 0,25W
4317	4822 051 10008	0Ω 5% 0,25W
4318	4822 051 10008	0Ω 5% 0,25W
4319	4822 051 10152	1k5 2% 0,25W
4320	4822 051 10008	0Ω 5% 0,25W
4321	4822 051 10008	0Ω 5% 0,25W
4322	4822 051 10008	0Ω 5% 0,25W
4323	4822 051 10008	0Ω 5% 0,25W
4324	4822 051 10008	0Ω 5% 0,25W
4325	4822 051 10008	0Ω 5% 0,25W
4326	4822 051 10008	0Ω 5% 0,25W
4329	4822 051 10008	0Ω 5% 0,25W
4450	4822 051 10008	0Ω 5% 0,25W
4451	4822 051 10008	0Ω 5% 0,25W
4452	4822 051 10008	0Ω 5% 0,25W
4500	4822 051 10008	0Ω 5% 0,25W
4501	4822 051 10008	0Ω 5% 0,25W
4502	4822 051 10008	0Ω 5% 0,25W
4503	4822 051 10008	0Ω 5% 0,25W
4504	4822 051 10008	0Ω 5% 0,25W
4505	4822 051 10008	0Ω 5% 0,25W
4506	4822 051 10008	0Ω 5% 0,25W
4507	4822 051 10008	0Ω 5% 0,25W
4602	4822 051 10008	0Ω 5% 0,25W
4603	4822 051 10008	0Ω 5% 0,25W
4604	4822 051 10008	0Ω 5% 0,25W
4605	4822 051 10008	0Ω 5% 0,25W
4700	4822 051 10008	0Ω 5% 0,25W
4701	4822 051 10008	0Ω 5% 0,25W
4704	4822 051 10008	0Ω 5% 0,25W
4706	4822 051 10008	0Ω 5% 0,25W
4707	4822 051 10008	0Ω 5% 0,25W
4708	4822 051 10008	0Ω 5% 0,25W
4709	4822 051 10008	0Ω 5% 0,25W
4710	4822 051 10008	0Ω 5% 0,25W
4711	4822 051 10008	0Ω 5% 0,25W
4712	4822 051 10008	0Ω 5% 0,25W
4713	4822 051 10008	0Ω 5% 0,25W
4714	4822 051 10008	0Ω 5% 0,25W
4715	4822 051 10008	0Ω 5% 0,25W
4716	4822 051 10008	0Ω 5% 0,25W
4718	4822 051 10008	0Ω 5% 0,25W
4720	4822 051 10008	0Ω 5% 0,25W
4721	4822 051 10008	0Ω 5% 0,25W
4723	4822 051 10008	0Ω 5% 0,25W
4850	4822 051 10008	0Ω 5% 0,25W
4851	4822 051 10008	0Ω 5% 0,25W
4852	4822 051 10008	0Ω 5% 0,25W
4853	4822 051 10008	0Ω 5% 0,25W
4854	4822 051 10008	0Ω 5% 0,25W
4855	4822 051 10008	0Ω 5% 0,25W
4856	4822 051 10008	0Ω 5% 0,25W
4857	4822 051 10008	0Ω 5% 0,25W
4858	4822 051 10008	0Ω 5% 0,25W
4859	4822 051 10008	0Ω 5% 0,25W
4862	4822 051 10008	0Ω 5% 0,25W
4863	4822 051 10008	0Ω 5% 0,25W
4865	4822 051 10008	0Ω 5% 0,25W
4866	4822 051 10008	0Ω 5% 0,25W
4867	4822 051 10008	0Ω 5% 0,25W

5240	4822 158 10551	27µH
5242	4822 158 10551	27µH
5301	4822 157 63075	7,95µH 8%
5303	4822 157 53906	47µH
5303	5322 157 51687	39µH 10%
5304	4822 157 63074	7,6µH
5306	4822 320 40081	470 NSEC
5530	4822 152 20559	390µH 10%
5534	4822 158 10728	coil 25"/28"
5534	4822 157 62771	coil 21"
5541	4822 157 63078	line driver
5545	4822 140 10417	L.O.T. 25"/28" non BL.L.
5545	4822 140 10414	L.O.T. 25"/28" BL.L.
5545	4822 140 10418	L.O.T. 21"
5549	4822 157 53069	coil balance
5554	4822 157 63079	AT4042/97 25"/28"
5554	4822 157 63161	AT4042/90G 21"
5582	5322 157 52539	15µH
5588	4822 157 52505	33µH 10%
5605	4822 157 53995	100µH 10%
5606	4822 157 53995	100µH 10%
5619	4822 156 21125	3,9µH 10% 25"/28"
5619	4822 157 51235	4µH 7 10% 21"
5621	4822 157 60412	150µH 10% 25"/28"
5621	4822 157 53903	180µH 10% 21"
5625	4822 148 81159	S.O.P.S. trafo 21"
5625	4822 148 81168	S.O.P.S. trafo 25"/28"
5630	4822 157 60387	1µH
5631	4822 158 10551	27µH
5632	4822 158 10551	27µH
5661	4822 152 20678	33µH 10%
5701	4822 157 52843	56µH 5%
5703	4822 157 52279	33µH 10%
5801	4822 157 53001	27µH 10%

6245	4822 130 30621	1N4148
6246	4822 130 81139	LLZ-C3V3
6247	4822 130 81139	LLZ-C3V3
6248	4822 130 80446	LL4148
6249	4822 130 80446	LL4148
6300	4822 130 80446	LL4148
6302	4822 130 34382	BZX79-C8V2
6303	4822 130 34382	BZX79-C8V2
6310	4822 130 80954	LLZ-C5V6
6315	4822 130 80446	LL4148
6316	4822 130 30621	1N4148
6317	4822 130 30621	1N4148
6318	4822 130 80446	LL4148
6367	4822 130 80884	LLZ-C5V1
6464	4822 130 81015	LLZ-C10
6465	4822 130 61219	BZX79-F10
6465	4822 130 80239	BZX79-F8V2
6465	4822 130 34281	BZX79-F15
6503	4822 130 42489	BYD33G
6504	4822 130 80446	LL4148
6518	4822 130 80446	LL4148
6519	4822 130 80446	LL4148
6546	4822 130 41275	BY228/20
6547	4822 130 41602	BYW95C/20
6548	4822 130 30621	1N4148
6549	4822 130 42488	BYD33D
6551	4822 130 42489	BYD33G
6560	4822 130 80446	LL4148
6561	4822 130 34383	BZX79-C47
6563	4822 130 80915	BYD74C
6570	4822 130 42488	BYD33D
6571	4822 130 42488	BYD33D
6580	4822 130 82512	BYV29F-400
6580	4822 130 32961	BYV28-200
6585	4822 130 42488	BYD33D
6590	4822 130 81141	LLZ-C43
6591	4822 130 30621	1N4148
6592	4822 130 80928	BZX79-C30
6610	4822 130 80446	LL4148
6611	4822 130 34268	LLZ-F16
6612	4822 130 30621	1N4148
6617	4822 130 31456	BZV85-C5V1
6621	4822 130 42488	BYD33D
6622	4822 130 30621	1N4148
6630	4822 130 33531	BY229F-600
6630	4822 130 81175	BYD74G
6640	4822 130 80914	BYD74B
6641	4822 130 80914	BYD74B
6646	4822 130 42488	BYD33D

Carrier panel (continued)

6648	4822 130 34488	BZX79-F12
6648	4822 130 61219	BZX79-F10
6649	4822 130 30621	1N4148
6660	4822 130 30621	1N4148
6661	4822 130 42488	BYD33D
6662	4822 130 80905	LLZ-F5V1
6663	4822 130 34281	BZX79-F15
6664	4822 130 61219	BZX79-F10
6664	4822 130 30862	BZX79-F9V1
6665	4822 130 80883	LLZ-C4V7
6666	4822 130 80887	LLZ-C36
6666	4822 130 81141	LLZ-C43
6669	4822 130 80446	LL4148
6670	4822 130 20245	SF0Ω5D43
6675	4822 130 80914	BYD74B
6675	4822 130 42488	BYD33D
6705	4822 130 80905	LLZ-F5V1
6707	4822 209 72895	TLUV5320
6708	4822 130 81145	LLZ-F2V4
6709	4822 130 82037	HZT33

7000	5322 130 42012	BC858A
7001	5322 130 42012	BC858A
7002	5322 130 42012	BC858A
7003	4822 130 42133	BC817
7240	4822 209 73253	TDA2613/N1
7240	4822 209 73853	TDA1521/N4
7243	5322 130 42012	BC858
7244	4822 130 42513	BC858C
7245	5322 130 42136	BC848C
7246	5322 130 42136	BC848C
7247	5322 130 42136	BC848C
7248	4822 130 61207	BC848
7249	4822 130 61207	BC848
7301	4822 130 61207	BC848
7302	5322 130 42012	BC858
7303	4822 130 61207	BC848
7305	4822 209 70019	TDA4510/V2/S8
7306	4822 209 63109	TDA4650/V3
7307	4822 209 63108	TDA4660/V2
7308	4822 209 71512	TDA4565/V6
7309	4822 209 63733	TDA4680/V5
7310	4822 130 61207	BC848
7311	5322 209 10576	4053B
7312	5322 209 10576	4053B
7341	4822 130 61207	BC848
7370	4822 130 61207	BC848
7371	4822 130 61207	BC848
7372	4822 130 61207	BC848
7373	4822 130 61207	BC848
7374	4822 130 61207	BC848
7455	5322 130 42012	BC858
7470	4822 209 63297	TDA2579B/N1
7500	4822 130 41344	BC337-40
7502	4822 130 60775	2SD1266P
7503	4822 130 61236	BD234
7504	4822 130 61207	BC848
7505	5322 130 42012	BC858
7530	4822 130 61207	BC848
7533	4822 130 60111	2SA1359
7534	4822 130 44283	BC636
7540	4822 130 41344	BC337-40
7545	4822 130 61265	BU508AF
7546	4822 130 62677	BUT11AF/1
7591	5322 130 42012	BC858
7600	4822 209 63735	TDA8385/N2
7614	4822 209 63732	CNR50
7625	4822 130 43919	BUT12AF
7661	5322 130 44921	BD943
7663	4822 130 42513	BC858C
7671	4822 130 61207	BC848

7672	4822 130 61207	BC848
7701	5322 130 42012	BC858A
7702	4822 130 61207	BC848
7703	4822 130 61207	BC848
7704	4822 130 61207	BC848
7705	4822 130 61207	BC848
7706	4822 130 61207	BC848
7707	4822 130 61207	BC848
7708	4822 209 63872	TMP47C1237N-U105 GR2VSL1
7708	4822 209 63947	TMP47C1237N-U107 GR2VSL2
7708	4822 209 63861	TMP47C1637N-U208 GR2FSL2
7708	4822 209 63875	TMP47C1637N-U211 GR2FSL1
7709	4822 130 61207	BC848
7710	4822 209 62098	ST24C02CP
7711	4822 130 61207	BC848
7712	4822 130 61207	BC848
7805	4822 130 61207	BC848
7810	4822 130 61207	BC848

Mains module

	4822 212 23664	mains mod.

10	4822 265 30389	2P MALE
32	4822 265 30389	2P MALE
33	4822 265 30877	3P MALE

2601	4822 121 40487	100n 400V

3601	4822 116 40211	PTC/NTC
3607	4822 050 23901	390Ω

5600	4822 157 63073	filter

6602	4822 130 31933	1N5061
6603	4822 130 31933	1N5061
6604	4822 130 31933	1N5061
6605	4822 130 31933	1N5061

CRT modules

	4822 212 23675	CRT MOD. 25"/28" BL.L.
	4822 212 23676	CRT MOD. 25"/28" NON BL.L.
	4822 212 23678	CRT MOD. 21"

19	4822 265 30378	4P MALE
20	4822 290 40295	7P MALE
21	4822 255 70261	CRT SOCKET 25"/28"
21	4822 255 70251	CRT SOCKET 21"

2301	4822 122 31961	68pF 5% 63V
2301	4822 122 31825	27pF 10% 50V
2301	4822 122 32482	22pF 5% 63V
2331	4822 122 31774	56pF 5% 50V
2331	4822 122 31825	27pF 10% 50V
2331	4822 122 32482	22pF 5% 63V
2361	4822 122 31774	56pF 5% 50V
2361	4822 122 32482	22pF 5% 63V
2361	4822 122 31825	27pF 10% 50V
2391	4822 121 43878	27pF 2% 500V
2392	4822 124 40246	4,7µF 20% 63V
2392	4822 124 41577	4,7µF 20% 50V
2411	4822 124 40849	330µF 20% 16V
2412	4822 122 33496	100nF 10% 63V
2421	4822 122 31772	47pF 5% 50V
2431	4822 121 41689	100nF 10% 250V
2432	4822 124 41506	47µF 20% 16V
2433	5322 121 50885	33nF 5% 1kV
2434	5322 122 32334	220pF 10% 100V

3301	4822 051 10131	130Ω 2% 0,25W
3302	4822 051 10152	1k5 2% 0,25W
3302	4822 051 10162	1k6 2% 0,25W
3302	4822 051 10362	3k6 2% 0,25W
3303	4822 051 10272	2k7 2% 0,25W
3304	4822 116 52239	120k 5% 0,5W
3305	4822 116 52283	4k7 5% 0,5W
3306	4822 116 52283	4k7 5% 0,5W
3307	4822 116 52283	4k7 5% 0,5W
3308	4822 051 10479	47Ω 2% 0,25W
3308	4822 051 10118	1Ω1 5% 0,25W
3310	4822 116 52219	330Ω 5% 0,5W
3311	4822 053 12123	12k 5% 3W
3311	4822 053 12153	15k 5% 3W
3312	4822 052 10271	270Ω 5% 0,33W
3313	4822 052 10271	270Ω 5% 0,33W
3314	4822 050 21502	1k5 1% 0,6W
3315	4822 051 10124	120k 2% 0,25W
3316	4822 051 10124	120k 2% 0,25W
3331	4822 051 10131	130Ω 2% 0,25W
3332	4822 051 10152	1k5 2% 0,25W
3332	4822 051 10162	1k6 2% 0,25W
3332	4822 051 10362	3k6 2% 0,25W
3333	4822 051 10272	2k7 2% 0,25W
3334	4822 116 52239	120k 5% 0,5W
3335	4822 116 52283	4k7 5% 0,5W
3336	4822 116 52283	4k7 5% 0,5W
3337	4822 116 52283	4k7 5% 0,5W
3339	4822 051 10479	47Ω 2% 0,25W
3339	4822 051 10118	1Ω1 5% 0,25W
3340	4822 116 52219	330Ω 5% 0,5W
3341	4822 053 12153	15k 5% 3W
3342	4822 052 10271	270Ω 5% 0,33W
3343	4822 052 10271	270Ω 5% 0,33W
3344	4822 050 21502	1k5 1% 0,6W

3345	4822 051 10681	680Ω 2% 0,25W
3361	4822 116 52208	130Ω 5% 0,5W
3361	4822 051 10131	130Ω 2% 0,25W
3362	4822 051 10152	1k5 2% 0,25W
3362	4822 051 10162	1k6 2% 0,25W
3362	4822 051 10362	3k6 2% 0,25W
3363	4822 051 10272	2k7 2% 0,25W
3364	4822 116 52239	120k 5% 0,5W
3365	4822 116 52283	4k7 5% 0,5W
3366	4822 116 52283	4k7 5% 0,5W
3367	4822 116 52283	4k7 5% 0,5W
3368	4822 051 10479	47Ω 2% 0,25W
3369	4822 051 10479	47Ω 2% 0,25W
3369	4822 051 10118	1Ω1 5% 0,25W
3370	4822 116 52219	330Ω 5% 0,5W
3371	4822 053 12103	10k 5% 3W
3371	4822 053 12153	15k 5% 3W
3372	4822 052 10271	270Ω 5% 0,33W
3373	4822 052 10271	270Ω 5% 0,33W
3374	4822 050 21502	1k5 1% 0,6W
3391	4822 051 10104	100k 2% 0,25W
3392	4822 051 10104	100k 2% 0,25W
3393	4822 116 52234	100k 5% 0,5W
3393	4822 050 28203	82k 1% 0,6W
3394	4822 051 10333	33k 2% 0,25W
3394	4822 116 52267	30k 5% 0,5W
3395	4822 051 10683	68k 2% 0,25W
3396	4822 051 10124	120k 2% 0,25W
3397	4822 051 10124	120k 2% 0,25W
3411	4822 051 10182	1k8 2% 0,25W
3411	4822 116 52243	1k5 5% 0,5W
3412	4822 116 52224	470Ω 5% 0,5W
3413	4822 116 52218	300Ω 5% 0,5W
3413	4822 051 10221	220Ω 2% 0,25W
3414	4822 051 10519	51Ω 2% 0,25W
3414	4822 051 10479	47Ω 2% 0,25W
3415	4822 116 52218	300Ω 5% 0,5W
3415	4822 051 10221	220Ω 2% 0,25W
3421	4822 051 10104	100k 2% 0,25W
3422	4822 051 10682	6k8 2% 0,25W
3422	4822 050 26802	6k8 1% 0,6W
3423	4822 051 10474	470k 2% 0,25W
3423	4822 116 52285	470k 5% 0,5W
3431	4822 052 10181	180Ω 5% 0,33W
3432	4822 052 10399	39Ω 5% 0,33W
3433	4822 052 10108	1Ω 5% 0,33W
3434	4822 050 21502	1k5 1% 0,6W
3435	4822 050 21502	1k5 1% 0,6W
3436	4822 050 21805	1M8 1% 0,6W
4000	4822 051 10008	0Ω 5% 0,25W
4001	4822 051 10008	0Ω 5% 0,25W
4002	4822 051 10008	0Ω 5% 0,25W
4003	4822 051 10008	0Ω 5% 0,25W
4005	4822 051 10008	0Ω 5% 0,25W
4006	4822 051 10008	0Ω 5% 0,25W
4007	4822 051 10008	0Ω 5% 0,25W
4008	4822 051 10008	0Ω 5% 0,25W
4009	4822 051 10008	0Ω 5% 0,25W
4010	4822 051 10008	0Ω 5% 0,25W
4011	4822 051 10008	0Ω 5% 0,25W
4012	4822 051 10008	0Ω 5% 0,25W

5401	4822 156 20915	33µH
5401	4822 158 10563	82µH 7,5%

6301	4822 130 80877	BAV103
6331	4822 130 80877	BAV103
6345	4822 130 81015	BZV55-F10
6361	4822 130 80877	BAV103
6411	4822 130 80879	BZV55-C3V0
6421	4822 130 80446	LL4148

7301	4822 130 41773	BF869
7301	4822 130 41782	BF422
7303	4822 130 61207	BC848
7304	4822 130 41782	BF422
7304	4822 130 41782	BF422
7305	4822 130 41646	BF423
7332	4822 130 41773	BF869
7332	4822 130 41782	BF422
7333	4822 130 61207	BC848
7334	4822 130 41782	BF422
7335	4822 130 41646	BF423
7345	5322 130 42012	BC858A
7362	4822 130 41773	BF869
7362	4822 130 41782	BF422
7363	4822 130 61207	BC848
7364	4822 130 41782	BF422
7365	4822 130 41646	BF423
7391	4822 130 41646	BF423
7411	4822 130 40938	BC548
7421	5322 130 41983	BC858B

Euro module

1006	4822 212 23666	EURO MODULE

23	4822 265 40442	10P MALE
26	4822 265 40442	10P MALE
30	4822 265 41086	9P MALE
32	4822 267 40666	3P MALE
48	4822 267 60247	EURO CONNECTOR

2800	4822 121 51252	470nF 5% 63V
2801	4822 121 51252	470nF 5% 63V
2802	4822 121 51252	470nF 5% 63V
2803	4822 121 51252	470nF 5% 63V
2804	4822 122 33496	100nF 10% 63V
2805	4822 122 33496	100nF 10% 63V
2806	4822 122 33496	100nF 10% 63V
2807	4822 124 41506	47µF 20% 16V
2810	4822 122 32142	270pF 5% 63V
2811	4822 122 32142	270pF 5% 63V
2812	4822 122 33496	100nF 10% 63V
2813	4822 122 32542	47nF 10% 63V
2814	4822 122 31759	18nF
2815	4822 122 33496	100nF 10% 63V
2816	4822 122 33496	100nF 10% 63V
2817	4822 122 33496	100nF 10% 63V
2818	4822 122 33496	100nF 10% 63V
2819	4822 124 41525	100µF 20% 25V
2820	5322 121 42386	100nF 5% 63V
2821	4822 124 40433	47µF 20% 25V
2822	4822 124 40435	10µF 20% 50V
2823	4822 122 33496	100nF 10% 63V
2831	4822 124 40272	33µF 20% 16V
2833	4822 122 33496	100nF 10% 63V
2834	4822 122 33496	100nF 10% 63V

3800	4822 116 52189	30Ω 5% 0,5W
3801	4822 116 80747	75Ω 5% 0,125W
3802	4822 116 52211	150Ω 5% 0,5W
3803	4822 116 52211	150Ω 5% 0,5W
3804	4822 116 52204	1k 5% 0,5W
3805	4822 116 52204	1k 5% 0,5W
3806	4822 051 10334	330k 2% 0,25W
3807	4822 051 10334	330k 2% 0,25W
3808	4822 051 10334	330k 2% 0,25W
3809	4822 051 10334	330k 2% 0,25W
3810	4822 051 10622	6k2 2% 0,25W
3811	4822 051 10182	1k8 2% 0,25W
3812	4822 051 10331	330Ω 2% 0,25W
3813	4822 116 52201	75Ω 5% 0,5W
3814	4822 051 10152	1k5 2% 0,25W
3815	4822 051 10472	4k7 2% 0,25W
3816	4822 116 52296	6k8 5% 0,5W
3819	4822 051 10331	330Ω 2% 0,25W
3820	4822 051 10331	330Ω 2% 0,25W
3821	4822 051 10331	330Ω 2% 0,25W
3822	4822 051 10331	330Ω 2% 0,25W
3823	4822 051 10561	560Ω 2% 0,25W
3824	4822 051 10151	150Ω 2% 0,25W
3825	4822 051 10223	22k 2% 0,25W
3826	4822 051 10102	1k 2% 0,25W
3827	4822 051 10339	33Ω 2% 0,25W
3828	4822 051 10562	5k6 2% 0,25W
3829	4822 051 10821	820Ω 2% 0,25W
3830	4822 051 10683	68k 2% 0,25W
3831	4822 051 10123	12k 2% 0,25W
3833	4822 051 10279	27Ω 2% 0,25W
3834	4822 051 10279	27Ω 2% 0,25W
3835	4822 051 10221	220Ω 2% 0,25W
3836	4822 051 10102	1k 2% 0,25W
3837	4822 052 10278	2Ω7 5% 0,33W
3838	4822 116 80747	75Ω 5% 0,125W
4851	4822 051 10008	0Ω 5% 0,25W
4852	4822 051 10008	0Ω 5% 0,25W
4854	4822 051 10008	0Ω 5% 0,25W
4855	4822 051 10008	0Ω 5% 0,25W
4856	4822 051 10008	0Ω 5% 0,25W
4858	4822 051 10008	0Ω 5% 0,25W

5800	4822 157 51462	10µH

6800	4822 130 80954	LLZ-C5V6
6801	4822 130 80446	LL4148
6802	4822 130 80446	LL4148
6803	4822 130 30621	1N4148

7800	5322 130 44921	BD943
7801	5322 209 10576	4053B
7802	5322 209 10576	4053B
7820	4822 130 61207	BC848
7821	5322 130 42136	BC848C
7822	5322 130 42012	BC858
7823	4822 130 61207	BC848
7824	4822 130 61207	BC848

Mono IF/sound module

	4822 212 23688	IF MOD. MULTI
	4822 212 23689	IF MOD. PAL/SECAM BG
	4822 212 23694	IF MOD. PAL I

various

1010	4822 242 72212	OFWG3950
1010	4822 242 72374	OFWG1961
1010	4822 242 70936	OFWJ1952
1042	4822 242 72211	TPS 5,5MHz
1043	4822 153 30025	6MHz
1102	4822 242 70714	SFT5,5MA
1103	4822 242 71841	SFT6,0MA

2011	4822 124 40435	10µF 20% 50V
2012	4822 124 41577	4,7µF 20% 50V
2013	4822 122 31784	4,7nF 10% 50V
2014	4822 122 31784	4,7nF 10% 50V
2014	4822 122 31797	22nF 10% 63V
2015	5322 121 42498	680nF 5% 63V
2016	4822 122 31784	4,7nF 10% 50V
2017	4822 122 33496	100nF 10% 63V
2018	4822 121 51252	470nF 5% 63V
2019	4822 122 31784	4,7nF 10% 50V
2020	4822 122 33205	12pF 10% 63V
2021	4822 122 33205	12pF 10% 63V
2022	4822 122 33472	22pF 2%
2025	4822 122 31784	4,7nF 10% 50V
2035	4822 122 32507	6,8pF 5% 50V
2036	4822 122 31766	120pF 5% 50V
2037	4822 122 31766	120pF 5% 50V
2038	4822 122 31784	4,7nF 10% 50V
2039	4822 122 32504	15pF 5% 50V
2040	4822 122 31784	4,7nF 10% 50V
2041	4822 122 31784	4,7nF 10% 50V
2042	4822 122 33205	12pF 10% 63V
2044	4822 122 31797	22nF 10% 63V
2047	4822 122 33496	100nF 10% 63V
2048	4822 124 41506	47µF 20% 16V
2049	4822 122 33496	100nF 10% 63V
2050	4822 124 40849	330µF 20% 16V
2055	4822 122 31972	39pF 5% 50V
2056	4822 124 40435	10µF 20% 50V
2057	4822 122 31981	33nF ±0,5pF 50V
2058	4822 122 31797	22nF 10% 63V
2059	4822 124 41566	3,3µF 20% 50V
2060	4822 122 31797	22nF 10% 63V
2100	4822 122 33205	12pF 10% 63V
2101	4822 122 33473	27pF 2%
2102	4822 122 32507	6,8pF 5% 50V
2104	4822 122 33474	47pF 2%
2105	4822 122 33465	39pF 2%
2106	4822 122 31792	1,5pF 10% 50V
2107	4822 122 33465	39pF 2%
2108	4822 122 31784	4,7nF 10% 50V
2109	4822 122 33473	27pF 2%
2110	5322 126 10514	0,47pF 5% 63V
2111	4822 122 31784	4,7nF 10% 50V
2113	4822 124 41596	22µF 20% 50V
2114	4822 122 31784	4,7nF 10% 50V
2115	4822 124 41577	4,7µF 20% 50V
2116	4822 124 40435	10µF 20% 50V
2117	4822 124 41576	2,2µF 20% 50V
2118	4822 124 40432	1500µF 20% 25V
2124	4822 122 32442	10nF 50V
2125	4822 124 40195	150µF 20% 16V
2126	4822 121 43898	8,2nF 10% 50V
2127	5322 121 42661	330nF 5% 63V
2129	5322 121 42661	330nF 5% 63V
2130	5322 121 42661	330nF 5% 63V
2132	4822 122 31797	22nF 10% 63V

Mono IF/sound module (continued)

⊣⊢

2133	4822 122 31797	22nF 10% 63V
2134	4822 124 41596	22µF 20% 50V
2135	4822 121 42408	220nF 5% 63V
2136	5322 121 42661	330nF 5% 63V
2137	4822 126 11381	820pF 2%
2137	4822 122 31746	1000pF 5% 50V
2141	4822 124 41577	4,7µF 20% 50V
2143	4822 122 31797	22nF 10% 63V
2150	4822 121 42408	220nF 5% 63V
2151	4822 124 40195	150µF 20% 16V

-▭-

3012	4822 051 10562	5k6 2% 0,25W
3013	4822 051 10273	27k 2% 0,25W
3014	4822 051 10823	82k 2% 0,25W
3015	4822 051 10104	100k 2% 0,25W
3015	4822 051 10473	47k 2% 0,25W
3016	4822 100 11163	100k 30% LIN 0,1W
3017	4822 051 10823	82k 2% 0,25W
3019	4822 051 10473	47k 2% 0,25W
3020	4822 051 10223	22k 2% 0,25W
3020	4822 051 10273	27k 2% 0,25W
3021	4822 051 10273	27k 2% 0,25W
3021	4822 051 20183	18k 5% 0,1W
3022	4822 051 10151	150Ω 2% 0,25W
3022	4822 051 10008	0Ω 5% 0,25W
3024	4822 051 20222	2k2 5% 0,1W
3025	4822 051 10562	5k6 2% 0,25W
3030	4822 051 10223	22k 2% 0,25W
3031	4822 051 10474	470k 2% 0,25W
3036	4822 051 10472	4k7 2% 0,25W
3037	4822 051 10392	3k9 2% 0,25W
3038	4822 051 10472	4k7 2% 0,25W
3039	4822 051 10392	3k9 2% 0,25W
3040	4822 051 10472	4k7 2% 0,25W
3041	4822 051 10221	220Ω 2% 0,25W
3042	4822 051 10101	100Ω 2% 0,25W
3042	4822 051 10221	220Ω 2% 0,25W
3043	4822 116 52175	100Ω 5% 0,5W
3044	4822 051 10102	1k 2% 0,25W
3044	4822 051 10271	270Ω 2% 0,25W
3046	4822 051 10681	680Ω 2% 0,25W
3047	4822 051 10822	8k2 2% 0,25W
3048	4822 100 11683	2k 30% LIN 0,2W
3049	4822 051 20183	18k 5% 0,1W
3050	4822 051 10272	2k7 2% 0,25W
3051	4822 051 10563	56k 2% 0,25W
3052	4822 051 10471	470Ω 2% 0,25W
3052	4822 051 10561	560Ω 2% 0,25W
3055	4822 051 10103	10k 2% 0,25W
3056	4822 051 10471	470Ω 2% 0,25W
3058	4822 051 10682	6k8 2% 0,25W
3060	4822 051 10471	470Ω 2% 0,25W
3061	4822 051 10124	120k 2% 0,25W
3062	4822 051 10563	56k 2% 0,25W
3063	4822 051 10272	2k7 2% 0,25W
3064	4822 051 10563	56k 2% 0,25W
3065	4822 051 10223	22k 2% 0,25W
3066	4822 051 10824	820k 2% 0,25W
3067	4822 051 10331	330Ω 2% 0,25W
3068	4822 051 10152	1k5 2% 0,25W
3080	4822 051 10102	1k 2% 0,25W
3080	4822 051 20222	2k2 5% 0,1W
3080	4822 051 10332	3k3 2% 0,25W
3100	4822 051 10104	100k 2% 0,25W
3101	4822 051 10562	5k6 2% 0,25W
3102	4822 051 20222	2k2 5% 0,1W
3103	4822 051 10104	100k 2% 0,25W
3104	4822 051 10479	47Ω 2% 0,25W
3105	4822 053 11271	270Ω 5% 2W
3107	4822 051 10151	150Ω 2% 0,25W
3108	4822 051 10333	33k 2% 0,25W

-▭-

3109	4822 051 10223	22k 2% 0,25W
3112	4822 051 10472	4k7 2% 0,25W
3114	4822 051 10472	4k7 2% 0,25W
3114	4822 051 10182	1k8 2% 0,25W
3116	4822 116 52263	2k7 5% 0,5W
3117	4822 051 10104	100k 2% 0,25W
3118	4822 051 10472	4k7 2% 0,25W
3118	4822 051 20222	2k2 5% 0,1W
3119	4822 051 10472	4k7 2% 0,25W
3120	4822 051 10472	4k7 2% 0,25W
3121	4822 051 10104	100k 2% 0,25W
3124	4822 051 10103	10k 2% 0,25W
3125	4822 051 10103	10k 2% 0,25W
3126	4822 051 10153	15k 2% 0,25W
3127	4822 051 10153	15k 2% 0,25W
3129	4822 051 10822	8k2 2% 0,25W
3130	4822 051 10682	6k8 2% 0,25W
3131	4822 051 10102	1k 2% 0,25W
3132	4822 051 10392	3k9 2% 0,25W
3140	4822 051 10153	15k 2% 0,25W
3141	4822 051 10392	3k9 2% 0,25W
3142	4822 051 10273	27k 2% 0,25W
3143	4822 051 10182	1k8 2% 0,25W
3144	4822 051 10182	1k8 2% 0,25W
4010	4822 051 10008	0Ω 5% 0,25W
4011	4822 051 10008	0Ω 5% 0,25W
4012	4822 051 10008	0Ω 5% 0,25W
4013	4822 051 10008	0Ω 5% 0,25W
4014	4822 051 10008	0Ω 5% 0,25W
4015	4822 051 10008	0Ω 5% 0,25W
4016	4822 051 10008	0Ω 5% 0,25W
4018	4822 051 10008	0Ω 5% 0,25W
4019	4822 051 10008	0Ω 5% 0,25W
4020	4822 051 10008	0Ω 5% 0,25W
4021	4822 051 10008	0Ω 5% 0,25W
4100	4822 051 10008	0Ω 5% 0,25W

-⌒⌒-

5005	4822 157 53539	0,27µH 5%
5010	4822 157 63081	0,56µH 20%
5035	4822 157 53534	0,34µH 5%
5036	4822 157 53609	0,36µH 5%
5037	4822 157 53537	1,35µH 5%
5038	4822 157 63076	1,2µH 5%
5039	4822 157 52983	22µH
5041	4822 157 52983	22µH
5041	4822 157 53001	27µH 10%
5042	4822 157 53634	5,6µH 10%
5042	4822 152 20677	10µH
5100	4822 157 53538	0,75µH 5%
5101	4822 157 53535	0,36µH 5%
5102	4822 157 53536	0,34µH 5%
5105	4822 157 52511	0,83µH

-▶|-

6005	4822 130 80888	BA682
6037	4822 130 80888	BA682
6038	4822 130 80888	BA682
6039	4822 130 30621	1N4148
6040	4822 130 80446	BAS32L
6041	4822 130 80446	BAS32L
6042	4822 130 80446	BAS32L
6043	4822 130 80446	BAS32L
6101	4822 130 80888	BA682
6102	4822 130 80888	BA682
6103	4822 130 80888	BA682
6104	4822 130 80888	BA682
6108	4822 130 80888	BA682
6112	4822 130 80884	LLZ-C5V1

7000	4822 209 72812	TDA2549/C4
7030	5322 130 42012	BC858
7031	4822 130 61207	BC848
7035	4822 130 44121	BC338
7040	5322 130 42012	BC858A
7041	4822 130 61207	BC848
7100	4822 209 63105	TDA3843/V2
7101	4822 209 63217	TDA3827/V2
7102	4822 130 61207	BC848
7103	5322 130 42136	BC848C
7104	5322 130 41982	BC848B

10.9 CHASSIS GR2.1

Stereo IF/sound module

	4822 212 23663	IF MOD. MULTI
	4822 212 23687	IF MOD. NON MULTI

various

1010	4822 242 80205	OFWK3261
1010	4822 242 72554	OFWG3254
1042	4822 242 72211	TPS 5,5MW
1101	4822 242 70485	SFT5,74MA
1102	4822 242 71713	SFE6,0MBF
1103	4822 242 70714	SFT5,5MA
1200	4822 242 80208	10 MHz

-||-

2011	4822 124 41506	47μF 20% 16V
2012	4822 124 41577	4,7μF 20% 50V
2013	4822 122 31784	4,7nF 10% 50V
2014	4822 122 31797	22nF 10% 63V
2015	5322 121 42498	680nF 5% 63V
2016	4822 122 31784	4,7nF 10% 50V
2017	4822 122 33496	100nF 10% 63V
2018	4822 121 51252	470nF 5% 63V
2035	4822 122 32506	5,6pF 5% 50V
2035	4822 051 10472	4k7 2% 0,25W
2036	4822 122 31784	4,7nF 10% 50V
2037	4822 122 31784	4,7nF 10% 50V
2038	4822 122 33496	100nF 10% 63V
2039	4822 122 32083	8,2pF 5% 50V
2039	4822 051 10682	6k8 2% 0,25W
2040	4822 122 31784	4,7nF 10% 50V
2041	4822 122 31784	4,7nF 10% 50V
2042	4822 122 33205	12pF 10% 63V
2044	4822 122 31797	22nF 10% 63V
2047	4822 122 33496	100nF 10% 63V
2048	4822 124 41506	47μF 20% 16V
2049	4822 122 33496	100nF 10% 63V
2050	4822 124 40849	330μF 20% 16V
2051	4822 122 33496	100nF 10% 63V
2055	4822 122 31972	39pF 5% 50V
2056	4822 124 40435	10μF 20% 50V
2057	4822 122 31981	33nF 5% 50V
2058	4822 122 31797	22nF 10% 63V
2059	4822 124 41407	0,47μF 20% 63V
2100	4822 122 33205	12pF 10% 63V
2101	4822 122 33473	27pF 2%
2102	4822 122 32507	6,8pF 5% 50V
2104	4822 122 33465	39pF 2%
2105	4822 126 11379	33pF 2%
2106	4822 122 31792	1,5pF 10% 50V
2107	4822 122 33465	39pF 2%
2108	4822 122 31784	4,7nF 10% 50V
2109	4822 122 33473	27pF 2%
2110	4822 122 32507	6,8pF 5% 50V
2111	4822 122 31784	4,7nF 10% 50V
2112	4822 122 32505	2,7pF 5% 50V
2113	4822 124 40435	10μF 20% 50V
2114	4822 122 32442	10nF 50V
2115	4822 124 41509	33μF 20% 35V
2117	4822 124 41576	2,2μF 20% 50V
2118	4822 124 41576	2,2μF 20% 50V
2119	4822 122 31797	22nF 10% 63V
2120	4822 124 41576	2,2μF 20% 50V
2122	4822 122 33496	100nF 10% 63V
2123	4822 124 41577	4,7μF 20% 50V
2123	4822 124 40242	1μF 20% 63V
2124	4822 124 41576	2,2μF 20% 50V
2125	4822 122 10527	910pF 2% NPO 50V
2126	4822 122 31784	4,7nF 10% 50V
2127	4822 126 11381	820pF 2% NPO
2127	4822 122 31746	1000pF 5% 50V
2128	4822 126 11381	820pF 2% NPO
2129	4822 122 33476	220pF 2% 50V

-||-

2130	4822 124 40195	150μF 20% 16V
2133	4822 122 31797	22nF 10% 63V
2200	4822 121 51252	470nF 5% 63V
2201	4822 121 51252	470nF 5% 63V
2202	4822 121 51252	470nF 5% 63V
2203	4822 122 31916	5,6nF 10% 63V
2204	4822 121 42408	220nF 5% 63V
2204	4822 121 42408	220nF 5% 63V
2205	4822 122 32893	100nF 80% 50V
2206	4822 121 51252	470nF 5% 63V
2207	4822 121 51252	470nF 5% 63V
2208	4822 124 41509	33μF 20% 35V
2209	4822 124 41509	33μF 20% 35V
2210	4822 122 32893	100nF 80% 50V
2211	4822 124 40198	470μF 20% 16V
2212	4822 124 40435	10μF 20% 50V
2213	4822 122 31782	15000pF 10% 50V
2214	4822 122 31782	15000pF 10% 50V
2215	4822 122 31981	33nF ±0,5pF 50V
2216	4822 122 31916	5,6nF 10% 63V
2217	4822 122 31981	33nF ±0,5pF 50V
2218	4822 122 31916	5,6nF 10% 63V
2219	4822 124 41577	4,7μF 20% 50V
2220	4822 124 41577	4,7μF 20% 50V
2221	4822 124 41577	4,7μF 20% 50V
2222	4822 124 41643	100μF 20% 16V

-▭-

3012	4822 051 10562	5k6 2% 0,25W
3013	4822 051 10273	27k 2% 0,25W
3014	4822 051 10823	82k 2% 0,25W
3015	4822 116 52234	100k 5% 0,5W
3016	4822 100 11163	100k 30% LIN 0,1W
3017	4822 051 10823	82k 2% 0,25W
3019	4822 051 10473	47k 2% 0,25W
3020	4822 051 10273	27k 2% 0,25W
3021	4822 051 20183	18k 5% 0,1W
3030	4822 051 10223	22k 2% 0,25W
3031	4822 051 10474	470k 2% 0,25W
3036	4822 051 10472	4k7 2% 0,25W
3037	4822 051 10392	3k9 2% 0,25W
3038	4822 051 10472	4k7 2% 0,25W
3039	4822 051 10472	4k7 2% 0,25W
3040	4822 051 10472	4k7 2% 0,25W
3041	4822 051 10221	220Ω 2% 0,25W
3042	4822 051 10151	150Ω 2% 0,25W
3042	4822 116 90536	120Ω 1% 0,125W
3043	4822 116 52175	100Ω 5% 0,5W
3044	4822 051 10102	1k 2% 0,25W
3044	4822 051 10271	270Ω 2% 0,25W
3046	4822 116 52228	680Ω 5% 0,5W
3047	4822 051 10822	8k2 2% 0,25W
3048	4822 100 11683	2k 30% LIN 0,2W
3049	4822 051 20183	18k 5% 0,1W
3050	4822 051 10272	2k7 2% 0,25W
3051	4822 051 10563	56k 2% 0,25W
3052	4822 051 10102	1k 2% 0,25W
3055	4822 051 10103	10k 2% 0,25W
3056	4822 051 10471	470Ω 2% 0,25W
3060	4822 051 10471	470Ω 2% 0,25W
3061	4822 051 10124	120k 2% 0,25W
3062	4822 051 10563	56k 2% 0,25W
3063	4822 051 10272	2k7 2% 0,25W
3064	4822 051 10224	220k 2% 0,25W
3065	4822 051 10472	4k7 2% 0,25W
3065	4822 051 10124	120k 2% 0,25W
3066	4822 051 10824	820k 2% 0,25W
3070	4822 051 10822	8k2 2% 0,25W
3100	4822 051 10104	100k 2% 0,25W
3101	4822 051 10562	5k6 2% 0,25W
3102	4822 051 20222	2k2 5% 0,1W
3103	4822 051 10104	100k 2% 0,25W

-▭-

3105	4822 053 11121	120Ω 5% 2W
3106	4822 051 10561	560Ω 2% 0,25W
3107	4822 051 10102	1k 2% 0,25W
3108	4822 051 10561	560Ω 2% 0,25W
3109	4822 051 10562	5k6 2% 0,25W
3110	4822 051 10562	5k6 2% 0,25W
3112	4822 051 10562	5k6 2% 0,25W
3113	4822 051 10562	5k6 2% 0,25W
3115	4822 051 10331	330Ω 2% 0,25W
3117	4822 051 10561	560Ω 2% 0,25W
3117	4822 051 10681	680Ω 2% 0,25W
3119	4822 051 10562	5k6 2% 0,25W
3120	4822 051 10562	5k6 2% 0,25W
3121	4822 051 10562	5k6 2% 0,25W
3122	4822 051 10122	1k2 2% 0,25W
3123	4822 051 10561	560Ω 2% 0,25W
3124	4822 051 20222	2k2 5% 0,1W
3125	4822 051 10102	1k 2% 0,25W
3126	4822 051 10102	1k 2% 0,25W
3127	4822 051 10152	1k5 2% 0,25W
3128	4822 051 10182	1k8 2% 0,25W
3200	4822 051 10331	330Ω 2% 0,25W
3201	4822 051 10331	330Ω 2% 0,25W
3202	4822 051 10563	56k 2% 0,25W
3203	4822 051 10563	56k 2% 0,25W
3204	4822 100 11676	10k 30% LIN 0,2W
3205	4822 052 10229	22Ω 5% 0,33W
3206	4822 051 10478	4Ω7 5% 0,25W
3207	4822 051 10273	27k 2% 0,25W
3208	4822 051 10272	2k7 2% 0,25W
3209	4822 051 10333	33k 2% 0,25W
3210	4822 116 52204	1k 5% 0,5W
3211	4822 051 10101	100Ω 2% 0,25W
3213	4822 116 52233	10k 5% 0,5W
3214	4822 051 10102	1k 2% 0,25W
4010	4822 051 10008	0Ω 5% 0,25W
4011	4822 051 10008	0Ω 5% 0,25W
4012	4822 051 10008	0Ω 5% 0,25W
4014	4822 051 10008	0Ω 5% 0,25W
4015	4822 051 10008	0Ω 5% 0,25W
4018	4822 051 10008	0Ω 5% 0,25W
4019	4822 051 10008	0Ω 5% 0,25W
4020	4822 051 10008	0Ω 5% 0,25W
4021	4822 051 10008	0Ω 5% 0,25W
4040	4822 051 10008	0Ω 5% 0,25W
4041	4822 051 10008	0Ω 5% 0,25W
4042	4822 051 10008	0Ω 5% 0,25W
4100	4822 051 10008	0Ω 5% 0,25W
4101	4822 051 10008	0Ω 5% 0,25W
4102	4822 051 10008	0Ω 5% 0,25W
4103	4822 051 10008	0Ω 5% 0,25W
4104	4822 051 10008	0Ω 5% 0,25W
4105	4822 051 10008	0Ω 5% 0,25W
4107	4822 051 10008	0Ω 5% 0,25W
4108	4822 051 10008	0Ω 5% 0,25W
4201	4822 051 10008	0Ω 5% 0,25W
4204	4822 051 10008	0Ω 5% 0,25W
4205	4822 051 10008	0Ω 5% 0,25W

-⌒⌒⌒-

5010	4822 157 63081	0,56μH 20%
5010	4822 157 53302	1μH 20%
5035	4822 157 53534	0,34μH 5%
5036	4822 157 53609	0,36μH 5%
5037	4822 157 53537	1,35μH 5%
5038	4822 157 63076	1,2μH 5%
5039	4822 152 20678	33μH 10%
5042	4822 157 62767	8,2μH 10%
5042	4822 157 53634	5,6μH 10%
5100	4822 157 53538	0,75μH 5%
5101	4822 157 53535	0,36μH 5%
5102	4822 157 53536	0,34μH 5%

Stereo IF/sound module (cont.)

5103	4822 157 52511	0,83µH
5104	4822 157 63077	0,25µH 5%
5105	4822 157 52511	0,83µH

6037	4822 130 80888	BA682
6038	4822 130 80888	BA682
6039	4822 130 30621	1N4148
6040	4822 130 80446	BAS32L
6041	4822 130 80446	BAS32L
6042	4822 130 80446	BAS32L
6043	4822 130 80446	BAS32L
6101	4822 130 80888	BA682
6102	4822 130 80888	BA682
6103	4822 130 80888	BA682
6104	4822 130 80888	BA682
6106	4822 130 80888	BA682
6107	4822 130 80888	BA682
6108	4822 130 80888	BA682
6109	4822 130 80446	LL4148

7000	4822 209 72812	TDA2549/C4
7030	5322 130 42012	BC858
7031	4822 130 61207	BC848
7035	4822 130 44121	BC338
7040	5322 130 42012	BC858A
7100	4822 209 63059	TDA3856/V3
7101	4822 209 63784	TDA3857/V3
7102	4822 130 61207	BC848
7103	5322 130 42012	BC858
7104	4822 130 61207	BC848
7200	4822 209 63294	TDA8417/V1
7220	4822 209 63734	TDA8425/V7
7232	5322 130 41982	BC848B

NICAM IF/sound module

	4822 212 23692	IF MOD. PAL BG
	4822 212 23691	IF MOD. PAL I

various

1010	4822 242 72554	OFWG3254
1010	4822 242 72553	OFWJ3251
1042	4822 242 72211	TPS 5,5MHz
1042	4822 153 30025	6MHz
1100	4822 242 70485	~~SFT5,74MA~~
1105	4822 242 70714	SFT5,5MA
1105	4822 242 71713	SFE6,0MBF
1116	4822 242 72301	TH316BQM-2080QDAF
1116	4822 242 72303	TH316BQM-2110QDAF
1125	4822 242 72302	5,850 MHz
1125	~~4822 242 72347~~	6,552 MHz
1141	4822 242 72304	5,824 MHz
1191	4822 253 10064	FUSE 0,4A
1200	4822 242 80208	10 MHz

2011	4822 124 41506	47µF 20% 16V
2012	4822 124 41577	4,7µF 20% 50V
2013	4822 122 31797	22nF 10% 63V
2014	4822 122 31797	22nF 10% 63V
2015	5322 121 42498	680nF 5% 63V
2016	4822 122 31784	4,7nF 10% 50V
2017	4822 122 33496	100nF 10% 63V
2042	4822 122 33205	12pF 10% 63V
2044	4822 122 31797	22nF 10% 63V
2047	4822 122 33496	100nF 10% 63V
2049	4822 122 33496	100nF 10% 63V
2050	4822 124 40849	330µF 20% 16V
2100	4822 124 40242	1µF 20% 63V
2101	4822 122 31746	1000pF 5% 50V
2102	4822 122 31746	1000pF 5% 50V
2102	4822 122 32765	820pF 10% 63V
2104	4822 122 31784	4,7nF 10% 50V
2106	4822 124 41576	2,2µF 20% 50V
2107	4822 124 41576	2,2µF 20% 50V
2108	4822 122 32862	10nF 80% 50V
2109	4822 124 41509	33µF 20% 35V
2110	4822 122 32893	100nF 80% 50V
2116	5322 122 31647	1nF 10% 63V
2119	4822 124 40198	470µF 20% 16V
2120	4822 124 41407	0,47µF 20% 63V
2121	4822 124 41407	0,47µF 20% 63V
2122	4822 122 32862	10nF 80% 50V
2123	4822 122 31774	56pF 5% 50V
2124	4822 125 50045	20pF
2125	4822 122 33205	12pF 10% 63V
2126	4822 122 31769	18pF 5% 50V
2127	4822 124 41407	0,47µF 20% 63V
2128	4822 122 32862	10nF 80% 50V
2129	4822 122 31965	220pF 5% 63V
2130	4822 122 31965	220pF 5% 63V
2131	4822 122 32862	10nF 80% 50V
2132	4822 122 32862	10nF 80% 50V
2133	4822 122 32893	100nF 80% 50V
2134	4822 122 32893	100nF 80% 50V
2135	4822 122 32893	100nF 80% 50V
2136	4822 122 32893	100nF 80% 50V
2137	4822 122 32862	10nF 80% 50V
2138	4822 122 32862	10nF 80% 50V
2139	4822 124 41407	0,47µF 20% 63V
2140	4822 122 31774	56pF 5% 50V
2141	4822 122 31769	18pF 5% 50V
2142	4822 122 32444	33pF 5% 50V
2143	4822 122 32504	15pF 5% 50V
2144	4822 122 32862	10nF 80% 50V
2145	4822 124 41506	47µF 20% 16V
2146	4822 122 32504	15pF 5% 50V
2147	4822 122 32504	15pF 5% 50V
2148	4822 122 33496	100nF 10% 63V
2150	4822 122 32893	100nF 80% 50V
2151	4822 122 31772	47pF 5% 50V
2153	4822 122 32862	10nF 80% 50V
2154	4822 122 31972	39pF 5% 50V
2155	4822 125 50045	20pF
2162	4822 122 32893	100nF 80% 50V
2168	4822 122 33496	100nF 10% 63V
2169	4822 124 41506	47µF 20% 16V
2170	4822 122 31759	18nF
2170	4822 122 32597	6,8nF 10% 63V
2171	4822 122 33608	39nF 10% 63V
2171	4822 122 31782	15000pF 10% 50V
2173	4822 122 31773	560pF 5% 50V
2174	4822 122 33498	2,7nF 10% 63V
2175	4822 122 32999	2,2N 5% NPO
2176	4822 121 51252	470nF 5% 63V
2177	4822 122 32863	22nF 80% 50V
2180	4822 122 31759	18nF
2180	4822 122 32597	6,8nF 10% 63V
2181	4822 122 33608	39nF 10% 63V
2181	4822 122 31782	15000pF 10% 50V
2183	4822 122 31773	560pF 5% 50V
2184	4822 122 33498	2,7nF 10% 63V
2185	4822 122 32999	2,2N 5% NPO
2186	4822 121 51252	470nF 5% 63V
2187	4822 122 32863	22nF 80% 50V
2188	4822 124 41506	47µF 20% 16V
2189	4822 122 32863	22nF 80% 50V
2190	4822 122 32893	100nF 80% 50V
2191	4822 124 41643	100µF 20% 16V
2192	4822 122 32893	100nF 80% 50V
2193	4822 124 40849	330µF 20% 16V
2194	4822 122 32893	100nF 80% 50V
2195	4822 124 41506	47µF 20% 16V
2196	4822 122 32862	10nF 80% 50V
2197	4822 124 41506	47µF 20% 16V
2198	4822 121 51252	470nF 5% 63V
2200	4822 121 51252	470nF 5% 63V
2201	4822 121 51252	470nF 5% 63V
2202	4822 122 31766	120pF 5% 50V
2203	4822 124 41509	33µF 20% 35V
2204	4822 124 41509	33µF 20% 35V
2205	4822 122 32893	100nF 80% 50V
2207	4822 121 51252	470nF 5% 63V
2209	4822 121 51252	470nF 5% 63V
2210	4822 124 41577	4,7µF 20% 50V
2211	4822 121 42408	220nF 5% 63V
2212	4822 122 31916	5,6nF 10% 63V
2213	4822 124 40195	150µF 20% 16V
2214	4822 122 32893	100nF 80% 50V
2215	4822 124 41506	47µF 20% 16V
2216	4822 122 31981	33nF ±0,5pF 50V
2217	4822 124 41577	4,7µF 20% 50V
2218	4822 124 41643	100µF 20% 16V
2219	4822 124 41577	4,7µF 20% 50V
2220	4822 122 31916	5,6nF 10% 63V
2223	4822 122 31916	5,6nF 10% 63V
2224	4822 122 31981	33nF ±0,5pF 50V
2225	4822 122 31782	15000pF 10% 50V
2226	4822 122 31782	15000pF 10% 50V

3012	4822 051 10562	5k6 2% 0,25W
3013	4822 051 10273	27k 2% 0,25W
3014	4822 051 10823	82k 2% 0,25W
3015	4822 051 10104	100k 2% 0,25W
3016	4822 100 11163	100k 30% LIN 0,1W
3019	4822 051 10473	47k 2% 0,25W
3020	4822 051 10273	27k 2% 0,25W
3021	4822 051 20183	18k 5% 0,1W

NICAM IF/sound module (continued)

-||-

3030	4822 051 10223	22k 2% 0,25W
3035	4822 051 10472	4k7 2% 0,25W
3041	4822 051 10221	220Ω 2% 0,25W
3042	4822 116 90536	120Ω 1% 0,125W
3042	4822 051 10101	100Ω 2% 0,25W
3043	4822 050 21001	100Ω 1% 0,6W
3044	4822 051 10102	1k 2% 0,25W
3052	4822 051 10102	1k 2% 0,25W
3055	4822 051 10103	10k 2% 0,25W
3056	4822 051 10471	470Ω 2% 0,25W
3065	4822 051 10472	4k7 2% 0,25W
3070	4822 051 10822	8k2 2% 0,25W
3100	4822 051 10561	560Ω 2% 0,25W
3101	4822 051 10331	330Ω 2% 0,25W
3102	4822 051 10681	680Ω 2% 0,25W
3105	4822 051 10561	560Ω 2% 0,25W
3106	4822 051 10561	560Ω 2% 0,25W
3107	4822 051 10122	1k2 2% 0,25W
3108	4822 051 20222	2k2 5% 0,1W
3109	4822 053 11121	120Ω 5% 2W
3110	4822 051 10102	1k 2% 0,25W
3116	4822 051 10471	470Ω 2% 0,25W
3120	4822 051 10154	150k 2% 0,25W
3121	4822 051 10224	220k 2% 0,25W
3122	4822 051 10471	470Ω 2% 0,25W
3123	4822 051 10511	510Ω 2% 0,25W
3125	4822 051 10102	1k 2% 0,25W
3126	4822 051 10393	39k 2% 0,25W
3139	4822 051 10393	39k 2% 0,25W
3140	4822 051 10471	470Ω 2% 0,25W
3141	4822 051 10102	1k 2% 0,25W
3143	4822 051 10331	330Ω 2% 0,25W
3144	4822 052 10278	2Ω7 5% 0,33W
3150	4822 051 10102	1k 2% 0,25W
3151	4822 051 10103	10k 2% 0,25W
3160	4822 051 10331	330Ω 2% 0,25W
3161	4822 051 10331	330Ω 2% 0,25W
3162	4822 051 10331	330Ω 2% 0,25W
3168	4822 052 10278	2Ω7 5% 0,33W
3170	4822 051 10562	5k6 2% 0,25W
3170	4822 051 10153	15k 2% 0,25W
3171	4822 051 10102	1k 2% 0,25W
3171	4822 051 10272	2k7 2% 0,25W
3172	4822 051 10472	4k7 2% 0,25W
3173	4822 051 10472	4k7 2% 0,25W
3177	4822 051 10822	8k2 2% 0,25W
3177	4822 051 10472	4k7 2% 0,25W
3180	4822 051 10562	5k6 2% 0,25W
3180	4822 051 10153	15k 2% 0,25W
3181	4822 051 10102	1k 2% 0,25W
3181	4822 051 10272	2k7 2% 0,25W
3182	4822 051 10472	4k7 2% 0,25W
3183	4822 051 10472	4k7 2% 0,25W
3188	4822 052 10109	10Ω 5% 0,33W
3190	4822 051 10471	470Ω 2% 0,25W
3191	4822 052 10399	39Ω 5% 0,33W
3192	4822 052 10478	4Ω7 5% 0,33W
3195	4822 052 10109	10Ω 5% 0,33W
3197	4822 051 10331	330Ω 2% 0,25W
3200	4822 100 11676	10k 30% LIN 0,2W
3201	4822 051 10822	8k2 2% 0,25W
3202	4822 051 10512	5k1 2% 0,25W
3203	4822 051 10563	56k 2% 0,25W
3204	4822 051 10563	56k 2% 0,25W
3205	4822 052 10229	22Ω 5% 0,33W
3206	4822 051 10331	330Ω 2% 0,25W
3208	4822 051 10331	330Ω 2% 0,25W
3209	4822 051 10103	10k 2% 0,25W
3210	4822 051 10102	1k 2% 0,25W
3213	4822 051 10478	4Ω7 5% 0,25W
3214	4822 051 10273	27k 2% 0,25W
3215	4822 051 10272	2k7 2% 0,25W
3216	4822 051 10333	33k 2% 0,25W

-||-

3217	4822 051 10102	1k 2% 0,25W
3218	4822 051 10101	100Ω 2% 0,25W
4000	4822 051 10393	39k 2% 0,25W
4000	4822 051 10392	3k9 2% 0,25W
4199	4822 051 10008	0Ω 5% 0,25W

⏦

5010	4822 157 53302	1μH
5035	4822 157 53534	0,34μH 5%
5036	4822 157 53609	0,36μH 5%
5042	4822 157 53634	5,6μH 10%
5101	4822 157 52511	0,83μH
5102	4822 157 52511	0,83μH
5103	4822 157 63077	0,25μH 5%
5129	4822 157 51238	0,820μH
5130	4822 157 51238	0,820μH
5153	4822 157 53575	3,3μH

▶|

6151	5322 130 34953	BB405B
6190	4822 130 80446	LL4148
6191	4822 130 80954	LLZ-C5V6
6197	4822 130 81027	LLZ-C11

⊗ ▭

7000	4822 209 72812	TDA2549/C4
7035	4822 130 44121	BC338
7100	4822 209 63784	TDA3857/V3
7106	4822 130 61207	BC848
7108	5322 130 42012	BC858
7120	4822 209 73558	TA8662N
7150	4822 209 61114	CF70123
7160	5322 209 10883	PCF8574P
7168	4822 209 73236	TDA1543/N2
7170	4822 209 83163	LM833N
7180	4822 209 83163	LM833N
7190	5322 130 41983	BC858B
7191	4822 130 44121	BC338
7195	4822 130 61207	BC848
7200	4822 209 61026	TDA8415/V1
7213	4822 209 63734	TDA8425/V7
7217	5322 130 41982	BC848B

Teletext module

	4822 212 23697	TXT MOD. EUROPE
	4822 212 23698	TXT MOD. SCAN

●-)—

21	4822 267 40469	6P MALE GOLD
22	4822 265 40471	8P MALE GOLD

various

1801	4822 242 73552	14,875 MHz
1802	4822 242 71508	6 MHz

-||-

2792	4822 122 33496	100nF 10% 63V
2793	4822 122 32542	47nF 10% 63V
2794	4822 122 31769	18pF 5% 50V
2795	4822 122 31769	18pF 5% 50V
2796	4822 122 31769	18pF 5% 50V
2797	4822 122 31769	18pF 5% 50V
2799	4822 122 31965	220pF 5% 63V
2800	4822 124 40178	100μF 20% 10V
2801	4822 122 32442	10nF 50V
2804	4822 122 31766	120pF 5% 50V
2805	4822 122 31766	120pF 5% 50V
2810	4822 122 33496	100nF 10% 63V
2811	4822 122 33496	100nF 10% 63V
2812	4822 122 33496	100nF 10% 63V
2813	4822 122 32442	10nF 50V
2814	4822 122 31773	560pF 5% 50V
2815	4822 122 33496	100nF 10% 63V
2816	4822 122 31825	27pF 10% 50V
2817	4822 122 32504	15pF 5% 50V
2818	5322 122 31647	1nF 10% 63V
2819	4822 122 31727	470pF 5% 63V
2820	4822 122 31797	22nF 10% 63V
2821	4822 122 32142	270pF 5% 63V
2822	4822 122 31765	100pF 5% 50V
2823	4822 122 31727	470pF 5% 63V
2824	4822 122 32891	68nF 10% 63V
2825	4822 124 41525	100μF 20% 25V
2826	4822 122 32504	15pF 5% 50V
2827	4822 122 32542	47nF 10% 63V
2828	4822 122 32542	47nF 10% 63V
2829	4822 124 41506	47μF 20% 16V
2830	4822 122 32542	47nF 10% 63V
2832	4822 124 41576	2,2μF 20% 50V
2833	4822 124 41576	2,2μF 20% 50V
2834	4822 124 40178	100μF 20% 10V
2836	4822 122 31766	120pF 5% 50V
2845	4822 124 40178	100μF 20% 10V
2846	4822 124 41554	220μF 20% 10V
2849	4822 124 21212	15μF 20% 35V
3795	4822 051 10392	3k9 2% 0,25W
3796	4822 051 10121	120Ω 2% 0,25W
3797	4822 116 52176	10Ω 5% 0,5W
3798	4822 051 10121	120Ω 2% 0,25W
3800	4822 051 10103	10k 2% 0,25W
3802	4822 051 10101	100Ω 2% 0,25W
3803	4822 051 10101	100Ω 2% 0,25W
3804	4822 051 10101	100Ω 2% 0,25W
3805	4822 051 10122	1k2 2% 0,25W
3807	4822 051 10562	5k6 2% 0,25W
3808	4822 051 10103	10k 2% 0,25W
3809	4822 051 10272	2k7 2% 0,25W
3810	4822 051 10333	33k 2% 0,25W
3811	4822 051 10223	22k 2% 0,25W
3812	4822 051 10332	3k3 2% 0,25W
3813	4822 051 10271	270Ω 2% 0,25W
3814	4822 116 52204	1k 5% 0,5W
3815	4822 051 10152	1k5 2% 0,25W

Teletext module (continued)

3816	4822 051 10683	68k 2% 0,25W
3817	4822 051 10122	1k2 2% 0,25W
3818	4822 051 10122	1k2 2% 0,25W
3819	4822 051 10122	1k2 2% 0,25W
3820	4822 051 10122	1k2 2% 0,25W
3821	4822 051 10122	1k2 2% 0,25W
3822	4822 051 10122	1k2 2% 0,25W
3823	4822 051 10122	1k2 2% 0,25W
3824	4822 051 10332	3k3 2% 0,25W
3825	4822 051 10332	3k3 2% 0,25W
3826	4822 052 10159	15Ω 5% 0,33W
3827	4822 051 10332	3k3 2% 0,25W
3828	4822 051 10122	1k2 2% 0,25W
3829	4822 116 52211	150Ω 5% 0,5W
3830	4822 050 28209	82Ω 1% 0,6W
3831	4822 051 10681	680Ω 2% 0,25W
3832	4822 051 10102	1k 2% 0,25W
3833	4822 051 10102	1k 2% 0,25W
3834	4822 051 10681	680Ω 2% 0,25W
3835	4822 051 10561	560Ω 2% 0,25W
3836	4822 051 10473	47k 2% 0,25W
3837	4822 051 10102	1k 2% 0,25W
3838	4822 051 10273	27k 2% 0,25W
3839	4822 051 10122	1k2 2% 0,25W
3840	4822 051 10122	1k2 2% 0,25W
3841	4822 051 10122	1k2 2% 0,25W
3842	4822 051 10122	1k2 2% 0,25W
3843	4822 051 10122	1k2 2% 0,25W
3845	4822 052 10689	68Ω 5% 0,33W
3846	4822 052 10689	68Ω 5% 0,33W
3847	4822 051 10829	82Ω 2% 0,25W
3848	4822 051 10181	180Ω 2% 0,25W
3849	4822 051 10102	1k 2% 0,25W
3900	4822 051 10008	0Ω 5% 0,25W
3901	4822 051 10008	0Ω 5% 0,25W
3904	4822 051 10008	0Ω 5% 0,25W
3906	4822 051 10008	0Ω 5% 0,25W
3908	4822 051 10008	0Ω 5% 0,25W
3910	4822 051 10008	0Ω 5% 0,25W
3913	4822 051 10008	0Ω 5% 0,25W
3914	4822 051 10008	0Ω 5% 0,25W
3915	4822 051 10008	0Ω 5% 0,25W
3917	4822 051 10008	0Ω 5% 0,25W
3918	4822 051 10008	0Ω 5% 0,25W
3919	4822 051 10008	0Ω 5% 0,25W
3920	4822 051 10008	0Ω 5% 0,25W
3921	4822 051 10008	0Ω 5% 0,25W
3922	4822 051 10008	0Ω 5% 0,25W

5800	4822 156 20966	47 µH
5801	4822 157 52849	22µH 10%
5803	4822 157 52825	60µH
5814	4822 157 53608	10µH
5816	4822 157 52224	15µH
5834	4822 157 53001	27µH 10%
5847	4822 157 51157	3,3µH

6809	4822 130 80446	LL4148
6810	4822 130 80446	LL4148
6811	4822 130 80446	LL4148
6812	4822 130 80446	LL4148
6813	4822 130 80906	LLZ-C7V5
6814	4822 130 80446	LL4148
6820	4822 130 80446	LL4148
6847	4822 130 42489	BYD33G
6848	4822 130 80905	LLZ-F5V1

7800	4822 209 63857	PCF84C81/074
7801	4822 130 61207	BC848
7802	4822 130 61207	BC848
7803	5322 130 41982	BC848B
7810	4822 209 72681	KM6264AL-15
7811	5322 130 41982	BC848B
7812	5322 130 60159	BC846B
7820	4822 209 73879	SAA5243P/E/M3
7830	4822 209 63645	SAA5231/V7
7831	4822 130 40962	BC558A
7832	4822 130 40937	BC548B
7846	5322 130 44921	BD943
7849	5322 130 42012	BC858

PIP module

	4822 265 40503	5P female gold plated
	4822 265 40472	10P female gold plated
	4822 265 30828	5P male

Various parts

1155	4822 320 40051	DELAY LINE DL711
1201	4822 242 70304	crystal 8,867 238 MHz
1212	4822 242 70736	crystal 7,159 090 MHz

2103	4822 122 32444	33pF 5% 50V
2105	4822 122 31766	120pF 5% 50V
2118	4822 122 31775	680pF 5% 50V
2119	4822 122 31808	150pF 10% 50V
2120	4822 122 31807	1200pF 5% 50V
2125	4822 122 32863	22nF 80% 50V
2155	4822 122 32862	10nF 80% 50V
2158	4822 122 32862	10nF 80% 50V
2160	4822 124 40242	1µF 20% 63V
2161	4822 124 41576	2,2µF 20% 50V
2162	4822 122 32893	100nF 80% 50V
2171	4822 122 31961	68pF 5% 63V
2172	4822 126 11175	22pF 5% 50V
2176	4822 126 11175	22pF 5% 50V
2177	4822 122 31961	68pF 5% 63V
2180	4822 122 31768	180pF 5% 50V
2181	4822 122 31768	180pF 5% 50V
2185	4822 122 32863	22nF 80% 50V
2187	4822 122 32863	22nF 80% 50V
2189	4822 122 31746	1000pF 5% 50V
2196	4822 122 32893	100nF 80% 50V
2197	4822 122 31385	22pF 5% 50V
2201	4822 122 31746	1000pF 5% 50V
2202	4822 125 50045	20pF
2211	4822 122 31746	1000pF 5% 50V
2212	4822 125 50045	20pF trim.
2220	5322 121 42661	330nF 5% 63V
2222	4822 122 32542	47nF 10% 63V
2227	5322 122 31842	330pF 5% 63V
2230	4822 124 40242	1µF 20% 63V
2232	4822 124 41678	22µF 20% 25V
2234	4822 122 33496	100nF 10% 63V
2235	4822 124 41578	6,8µF 20% 50V
2238	4822 121 42937	2,7nF 1% 250V
2239	4822 122 32893	100nF 80% 50V
2250	4822 121 51115	270nF 10% 63V
2251	5322 122 31647	1nF 10% 63V
2255	4822 122 31766	120pF 5% 50V
2260	4822 122 32893	100nF 80% 50V
2270	4822 122 32893	100nF 80% 50V
2340	4822 124 41506	47µF 20% 16V
2345	4822 124 41506	47µF 20% 16V
2350	4822 124 40849	330µF 20% 16V
2351	4822 124 41643	100µF 20% 16V
2380	4822 122 32927	220nF
2381	4822 122 32927	220nF
2382	4822 122 32927	220nF
2383	4822 122 32927	220nF
2384	4822 122 32927	220nF
2385	4822 122 32927	220nF
2390	4822 122 32893	100nF 80% 50V
2399	4822 122 31746	1000pF 5% 50V
2404	4822 122 31965	220pF 5% 63V
2405	4822 122 32862	10nF 80% 50V
2409	4822 122 31965	220pF 5% 63V
2410	4822 122 32862	10nF 80% 50V
2413	4822 122 31765	100pF 5% 50V

PIP module (continued)

2414	4822 122 32862	10nF 80% 50V
2415	4822 122 31965	220pF 5% 63V
2430	4822 122 32893	100nF 80% 50V
2432	4822 122 32893	100nF 80% 50V
2434	4822 122 32893	100nF 80% 50V
2438	4822 121 42472	10nF 10% 50V
2439	4822 121 41856	22nF 5% 100V
2440	4822 122 31965	220pF 5% 63V
2441	4822 122 31727	470pF 5% 63V
2442	4822 124 40242	1µF 20% 63V
2446	4822 122 32893	100nF 80% 50V
2448	4822 122 32893	100nF 80% 50V
2450	4822 122 32856	8,2nF 10% 63V
2451	4822 121 51379	82nF 10% 63V
2455	4822 122 31972	39pF 5% 50V
2459	4822 124 41997	470µF 10V
2466	4822 122 32893	100nF 80% 50V

2444	4822 051 10224	220k 2% 0,25W
3103	4822 051 10821	820Ω 2% 0,25W
3104	4822 051 10821	820Ω 2% 0,25W
3105	4822 051 10362	3k6 2% 0,25W
3106	4822 116 52233	10k 5% 0,5W
3107	4822 051 10103	10k 2% 0,25W
3108	4822 051 10103	10k 2% 0,25W
3155	4822 051 10391	390Ω 2% 0,25W
3156	4822 051 10122	1k2 2% 0,25W
3157	4822 100 11391	330Ω 30% LIN
3158	4822 051 10759	75Ω 2% 0,25W
3170	4822 051 10112	1k1 2% 0,25W
3175	4822 051 10621	620Ω 2% 0,25W
3196	4822 116 52204	1k 5% 0,5W
3200	4822 051 10103	10k 2% 0,25W
3201	4822 051 10103	10k 2% 0,25W
3202	4822 051 10103	10k 2% 0,25W
3211	4822 051 10103	10k 2% 0,25W
3212	4822 051 10103	10k 2% 0,25W
3214	4822 051 10102	1k 2% 0,25W
3220	4822 051 10512	5k1 2% 0,25W
3221	4822 116 52233	10k 5% 0,5W
3222	4822 051 10008	JUMPER
3227	4822 116 52299	7k5 5% 0,5W
3228	4822 051 10472	4k7 2% 0,25W
3231	4822 051 10682	6k8 2% 0,25W
3232	4822 051 10229	22Ω 2% 0,25W
3233	4822 051 10471	470Ω 2% 0,25W
3234	4822 051 10361	360Ω 2% 0,25W
3235	4822 051 10122	1k2 2% 0,25W
3236	4822 051 10471	470Ω 2% 0,25W
3237	4822 051 10332	3k3 2% 0,25W
3238	4822 051 10333	33k 2% 0,25W
3239	4822 100 11319	4k7 30% LIN
3241	4822 051 10271	270Ω 2% 0,25W
3242	4822 116 52204	1k 5% 0,5W
3250	4822 051 10911	910Ω 2% 0,25W
3265	4822 051 10104	100k 2% 0,25W
3270	4822 051 10103	10k 2% 0,25W
3275	4822 051 10103	10k 2% 0,25W
3276	4822 051 10102	1k 2% 0,25W
3330	4822 051 20008	jumper
3335	4822 051 10271	270Ω 2% 0,25W
3336	4822 051 10432	4k3 2% 0,25W
3337	4822 051 10122	1k2 2% 0,25W
3338	4822 051 10332	3k3 2% 0,25W
3340	4822 051 10202	2k 2% 0,25W
3341	4822 052 10229	22Ω 5% 0,33W
3345	4822 052 10229	22Ω 5% 0,33W
3353	4822 052 10568	5Ω6 5% 0,33W
3354	4822 051 10271	270Ω 2% 0,25W
3390	4822 051 10151	150Ω 2% 0,25W
3391	4822 051 10181	180Ω 2% 0,25W
3394	4822 051 10151	150Ω 2% 0,25W
3395	4822 051 10181	180Ω 2% 0,25W
3398	4822 051 10151	150Ω 2% 0,25W
3399	4822 051 10181	180Ω 2% 0,25W
3404	4822 051 10431	430Ω 2% 0,25W
3405	4822 051 10361	360Ω 2% 0,25W
3410	4822 051 10391	390Ω 2% 0,25W
3411	4822 051 10471	470Ω 2% 0,25W
3412	4822 051 10751	750Ω 2% 0,25W
3414	4822 051 10471	470Ω 2% 0,25W
3416	4822 051 10182	1k8 2% 0,25W
3434	4822 051 10473	47k 2% 0,25W
3436	4822 051 10473	47k 2% 0,25W
3437	4822 051 10101	100Ω 2% 0,25W
3438	4822 051 10513	51k 2% 0,25W
3440	4822 116 52222	390Ω 5% 0,5W
3441	4822 051 10519	51Ω 2% 0,25W
3442	4822 051 10919	91Ω 2% 0,25W
3444	4822 116 52175	100Ω 5% 0,5W
3446	4822 116 52175	100Ω 5% 0,5W
3448	4822 051 10392	3k9 2% 0,25W
3450	4822 051 10471	470Ω 2% 0,25W
3452	4822 051 10471	470Ω 2% 0,25W
3454	4822 051 10471	470Ω 2% 0,25W
3460	4822 116 52231	820Ω 5% 0,5W
3461	4822 116 52259	2k4 5% 0,5W
3462	4822 116 52287	51k 5% 0,5W
3463	4822 116 52299	7k5 5% 0,5W
3464	4822 051 10472	4k7 2% 0,25W
3470	4822 052 10108	1Ω 5% 0,33W
3997	4822 051 10339	33Ω 2% 0,25W
3997	4822 051 10279	27Ω 2% 0,25W

jumpers

4001	4822 051 10008	jumper
4002	4822 051 10008	jumper
4003	4822 051 10008	jumper
4004	4822 051 10008	jumper
4005	4822 051 10008	jumper
4006	4822 051 10008	jumper
4007	4822 051 10008	jumper
4010	4822 051 10008	jumper
4011	4822 051 10008	jumper
4012	4822 051 10008	jumper
4048	4822 051 10008	jumper
4100	4822 051 10008	jumper
4201	4822 051 10008	jumper
4401	4822 051 10008	jumper
4402	4822 051 10008	jumper
4403	4822 051 10008	jumper
4404	4822 051 10008	jumper
4406	4822 051 10008	jumper
4407	4822 051 10008	jumper
4415	4822 051 10008	jumper

5118	4822 157 60435	10,3µH 6%
5155	4822 157 60433	7,2µH 6%
5157	4822 157 60434	9,4µH 6%
5170	4822 157 60432	10,3µH
5175	4822 157 60432	10,3µH
5190	4822 157 60432	10,3µH
5400	4822 157 50943	12µH 10%
5402	4822 157 50943	12µH 10%
5404	4822 156 20915	33µH 10%
5406	4822 157 50943	12µH 10%
5408	4822 157 50943	12µH 10%
5410	4822 157 50943	12µH 10%

6300	4822 130 80906	LLZ-C7V5

7103	5322 130 41982	BC848B
7105	5322 130 41982	BC848B
7125	4822 209 62477	TDA4554/V8
7126	4822 209 70019	TDA4510/V2/S8
7200	5322 130 41982	BC848B
7210	5322 130 41982	BC848B
7233	5322 130 41983	BC858B
7234	5322 130 41982	BC848B
7335	5322 130 41982	BC848B
7337	5322 130 41982	BC848B
7338	5322 130 41982	BC848B
7350	4822 130 42616	BC818-40
7380	4822 209 60479	TEA5114A
7400	5322 130 41983	BC858B
7402	5322 130 41983	BC858B
7404	5322 130 41983	BC858B
7406	4822 209 62473	SDA9087
7408	4822 209 63291	SDA9088/2R
7410	4822 209 63644	SDA9086-3
7755	4822 209 72363	TDA2579A/N8